

# PROGRAMMING MANUAL

## DIGITAL STORAGE OSCILLOSCOPE DCS-2000E SERIES



B71-0461-01

## **■About a trademark, a registered trademark**

A company name and the brand name mentioned in this instruction manual are the trademark or the registered trademark of each company or group in each country and region.

## **■About this instruction manual**

When copying the part or all of contents of this instruction manual, seek the copyright holder.

In addition, the specifications of the product and the contents of this instruction manual are subject to change without notice for improvement. For the purpose of considering the environment and reducing waste, we are progressively eliminating the paper or CD manuals attached to our products.

The latest version of the instruction manual is posted on our website. (<https://www.texio.co.jp/>)

## **■Supported version of firmware**

Ver1.37 or higher.

# Contents


USING THE PRODUCT SAFELY.....	I - V
1. INTERFACE OVERVIEW .....	1
1-1. Front Panel Overview .....	1
1-2. Interface Configuration .....	2
2. COMMAND OVERVIEW .....	9
2-1. Command Syntax .....	9
3. COMMAND DETAILS.....	10
3-1. Common Commands .....	11
3-2. Acquisition Commands.....	16
3-3. Autoscale Commands .....	22
3-4. Vertical Commands.....	23
3-5. Math Commands.....	27
3-6. Cursor Commands .....	34
3-7. Display Commands .....	42
3-8. Hardcopy Commands.....	45
3-9. Measure Commands .....	48
3-10. Measurement Commands .....	69
3-11. Reference Commands.....	74
3-12. Run Command.....	76
3-13. Timebase Commands.....	77
3-14. Trigger Commands .....	79
3-15. System Commands .....	110
3-16. Save/Recall Commands .....	111
3-17. Ethernet Commands .....	114
3-18. Time Commands.....	114
3-19. Bus Decode Commands .....	115
3-20. Mark Commands .....	126
3-21. Search Commands.....	128
3-22. Label Commands .....	155
3-23. Segment Commands .....	159
3-24. DVM Commands .....	165
3-25. Go_NoGo Commands .....	167
3-26. Data Logging Commands .....	172
3-27. Remote DiskCommands .....	174
4. APPENDX .....	176
4-1. Error messages .....	176

# 1. INTERFACE OVERVIEW

This manual describes how to use the remote command functionality and lists the command details. The Overview chapter describes how to configure the USB remote control interface and Ethernet interface.

## 1-1. Front Panel Overview

---



## 1-2. Interface Configuration

### 1-2-1. Configure USB Interface

USB Configuration	PC side connector DCS-2000E side connector	Type A, host Type B, device
Speed	1.1/2.0 (high speed)	
USB Class	USB-CDC	
OS	Windows7(32bit/64bit) or higher	
USB Driver	TEXIO_CDC*.inf	

- Panel Operation
1. Press the Utility key.
  2. Press I/O from the bottom menu.
  3. Press *USB Device Port* from the side menu and select *Computer*.
  4. Connect the USB cable to the rear panel device port.
  5. When the PC asks for the USB driver or 'Unknown device' listed in Device Manager, install TEXIO-CDC\*.inf.
  6. If the computer can not recognize the new hardware due to the security, please go to update the driver from the "Other devices" in the Device Manager.




#### Note

You must have administrator account to install driver.

### 1-2-2. Configure the Ethernet Interface

Ethernet Configuration	MAC Address Instrument Name User Password Instrument IP Address	Domain Name DNS IP Address Gateway IP Address Subnet Mask
Background	The Ethernet interface is used for remote control using a socket server connection.	
Panel Operation	1. Connect the Ethernet cable to the LAN port on the rear panel.  2. Press the <i>Utility</i> key.  3. Press <i>I/O</i> from the bottom menu.	  


4. Press *Ethernet* from the side menu.




5. Set *DHCP/BOOTP* to *On* or *Off* from the side menu.



IP addresses will automatically be assigned with DHCP/BOOTP set to on. For Static IP Addresses, DHCP/BOOTP should be set to off.




6. Use the *Up* and *Down* arrows on the side menu to navigate to each Ethernet configuration item.



Items      MAC Address, Instrument Name, User Password, Instrument IP Address, Domain Name, DNS IP Address, Gateway IP Address, Subnet Mask

7. Use the *Variable* knob to highlight a character and use the *Select* key to choose a character.



Press *Backspace* to delete a character.

Press Save Now to save the configuration. Complete will be displayed when successful.

Save Now

### 1-2-3. Configure Socket Server

The DCS-2000E supports socket server functionality for direct and full duplex communication with a client PC or device over LAN. By default, the Socket Server is off.

Configure Socket Server

1. Configure the IP address for the DCS-2000E.
2. Press the *Utility* key.

3. Press *I/O* from the bottom menu.

4. Press *Socket Server* from the side menu.


5. Press *Select Port* and choose the port number with the Variable knob.

Range 1024~65535

6. Press *Set Port* to confirm the port number.

7. The Current Port icon will update to the new port number.

8. Press *Server* and turn the socket server On.




Note

If there is no response from the socket port, close the socket port on the PC. Then reopen the socket port. The socket port is reset and communication is restored.

### 1-2-4. USB Functionality Check

Terminal Application (USB) Invoke the terminal application such as PuTTY or RealTerm. For USB, set the COM port, baud rate, stop bit, data bit, and parity accordingly.  
To check the COM port number and associated port settings, see the Device Manager in the PC. For Windows:  
*Control panel → Hardware and Sound→ Device Manager*

Example: Configuring RealTerm for RS-232C communication.




Functionality Check	<p>Key in this query command via the terminal application. *idn?</p> <p>This should return the Manufacturer, Model number, Serial number, and Firmware version in the following format.</p> <p>TEXIO, DCS-2204E, PXXXXXX, V1.00</p>
---------------------	---

#### 1-2-5. Socket Server Functionality Check


NI Measurement and Automation Explorer	To test the socket server functionality, National Instruments MAX (Measurement and Automation Explorer) can be used. This program is available on the NI website, <a href="http://www.ni.com">www.ni.com</a> .  The following display and operation will differ depending on the version of MAX. Please use in accordance with the display for your MAX.
Operation	<ol style="list-style-type: none"><li>1. Configure the IP address for the DCS-2000E.</li><li>2. Configure the socket port.</li><li>3. Start the NI Measurement and Automation Explorer (MAX) program. Using Windows, press: <i>Start&gt;All Programs&gt;National Instruments&gt;Measurement &amp; Automation</i></li></ol>




4. From the Configuration panel access;  
*My System>Devices and Interfaces>Network Devices*
5. Right click *Network Devices* and select *Create New Visa TCP/IP Resource...*



6. Select *Manual Entry of Raw Socket* from the popup window.
7. Click *Next*.



8. Enter the IP address and socket port number of the DCS-2000E.
9. Click *Validate*.
10. A popup will appear to tell you if a VISA socket session was successfully created.
11. Click *Next*.




12. Choose an alias for the socket connection if you like.
13. Click *Finish* to finish the configuration.




14. The DCS-2000E will now appear under Network Devices in the Configuration Panel.
15. Click the *Open Visa Test Panel* to send a remote command to the DCS-2000E.


## Functionality Check



16. Click on the *Configuration* icon.
17. Select the *I/O Settings* tab.
18. Mark the *Enable Termination Character* checkbox. Make sure the termination character is a line feed (/n, value: xA).
19. Click *Apply Changes*.



20. Click the *Input/Output* icon.
21. Make sure \*IDN? query is selected in the *Select or Enter Command* drop box.
22. Click on *Query*.
23. The manufacturer, model number, serial number and firmware version will be displayed in the buffer. For example:  
TEXIO,DCS-2202E,PXXXXXX,V1.00



## 2. COMMAND OVERVIEW

The Command overview chapter lists all DCS-2000E commands in functional order as well as alphabetical order. The command syntax section shows you the basic syntax rules you have to apply when using commands.

### 2-1. Command Syntax

Compatible standard	<ul style="list-style-type: none"><li>• USB CDC_ACN compatible</li><li>• SCPI, 1994 (partially compatible)</li></ul>		
Command forms	Commands and queries have two different forms, long and short. The command syntax is written with the short form of the command in capitals and the remainder (long form) in lower case.		
	<pre>graph TD; Long[Long] --- TIMEbaseSCALE[":TIMEbase:SCALe?"]; TIMEbaseSCALE --- Short1[Short]; TIMEbaseSCALE --- Short2[Short]</pre>		
	The commands can be written in capitals or lower-case, just so long as the short or long forms are complete. An incomplete command will not be recognized. Below are examples of correctly written commands.		
	LONG	:TIMEbase:SCALe?	:TIMEBASE:SCALE?
	SHORT	:TIM:SCAL?	:TIM:SCAL?
Command format	:TIMEbase:SCALe <NR3>LF 1: command header 2: single space 3: parameter 4: message terminator		
Parameter	Type <Boolean> <NR1> <NR2> <NR3> <NRf>	Description boolean logic Integers floating point floating point with an exponent any of NR1, 2, 3	Example 0, 1 0, 1, 2, 3 0.1, 3.14, 8.5 4.5e-1, 8.25e+1 1, 1.5, 4.5e-1
Message terminator	LF	line feed code	
Note	Commands are non-case sensitive.		

### **3. COMMAND DETAILS**

The Command details chapter shows the detailed syntax, equivalent panel operation, and example for each command.

---

3-1. Common Commands .....	11
3-2. Acquisition Commands.....	16
3-3. Autoscale Commands .....	22
3-4. Vertical Commands.....	23
3-5. Math Commands.....	27
3-6. Cursor Commands .....	34
3-7. Display Commands .....	42
3-8. Hardcopy Commands .....	45
3-9. Measure Commands .....	48
3-10. Measurement Commands .....	69
3-11. Reference Commands.....	74
3-12. Run Command.....	76
3-13. Timebase Commands.....	77
3-14. Trigger Commands .....	79
3-15. System Commands .....	110
3-16. Save/Recall Commands .....	111
3-17. Ethernet Commands .....	114
3-18. Time Commands.....	114
3-19. Bus Decode Commands .....	115
3-20. Mark Commands .....	126
3-21. Search Commands.....	128
3-22. Label Commands .....	155
3-23. Segment Commands .....	159
3-24. DVM Commands .....	165
3-25. Go_NoGo Commands .....	167
3-26. Data Logging Commands .....	172
3-27. Remote DiskCommands .....	174

---

### **3-1. Common Commands**

---

3-1-1. *IDN?	11
3-1-2. *LRN?	11
3-1-3. *SAV	11
3-1-4. *RCL	12
3-1-5. *RST	12
3-1-6. *CLS	12
3-1-7. *ESE	12
3-1-8. *ESR	13
3-1-9. *OPC	13
3-1-10. *SRE	14
3-1-11. *STB	15

---

#### **3-1-1. \*IDN?**

→ **Query**

Description	Returns the manufacturer, model, serial number and version number of the unit.
Syntax	*IDN?
Example	*IDN? TEXIO, DCS-2204E,P930116,V0.82b

#### **3-1-2. \*LRN?**

→ **Query**

Description	Returns the oscilloscope settings as a data string.
Syntax	*LRN?
Example	*LRN? :DISPlay:WAVEform VECTOR;PERSistence 2.400E-01;INTensity:WAVEform 50;INTensity:GRATicule 50;GRATicule FULL;:CHANnel CH1:DISPlay ON;BWLimit . . 1.000e+00;PROBe:TYPE VOLTAGE;SCALE 5.000E-02;IMPedance 1E+6;EXPand GROUND;:CHANnel OFF

#### **3-1-3. \*SAV**

**Set** →

Description	Saves the current panel settings to the selected memory number.
Syntax	*SAV {1   2   3   ....   20}
Example	*SAV 1 Saves the current panel settings to Set 1

### 3-1-4. \*RCL

(Set →)

Description	Recalls a set of panel settings.
Syntax	*RCL {1   2   3  ....   20}
Example	*RCL 1 Recalls the selected setup from Set 1.

### 3-1-5. \*RST

(Set →)

Description	Resets the DCS-2000E (recalls the default panel settings).
Syntax	*RST

### 3-1-6. \*CLS

(Set →)

Description	Clears the error queue.
Syntax	*CLS

### 3-1-7. \*ESE

(Set →)

→ (Query)

Description	Sets or queries the Standard Event Status Enable register.																																				
Syntax	*ESE <NR1>																																				
Query Syntax	*ESE?																																				
Return parameter	<NR1> 0~255																																				
Bit Weight	<table><thead><tr><th>Bit#</th><th>Weight</th><th>Event</th><th>Description</th></tr></thead><tbody><tr><td>0</td><td>1</td><td>OPC</td><td>Operation Complete Bit</td></tr><tr><td>1</td><td>2</td><td>RQC</td><td>Not used</td></tr><tr><td>2</td><td>4</td><td>QYE</td><td>Query Error</td></tr><tr><td>3</td><td>8</td><td>DDE</td><td>Device Error</td></tr><tr><td>4</td><td>16</td><td>EXE</td><td>Execution Error</td></tr><tr><td>5</td><td>32</td><td>CME</td><td>Command Error</td></tr><tr><td>6</td><td>64</td><td>URQ</td><td>User Request</td></tr><tr><td>7</td><td>128</td><td>PON</td><td>Power On</td></tr></tbody></table>	Bit#	Weight	Event	Description	0	1	OPC	Operation Complete Bit	1	2	RQC	Not used	2	4	QYE	Query Error	3	8	DDE	Device Error	4	16	EXE	Execution Error	5	32	CME	Command Error	6	64	URQ	User Request	7	128	PON	Power On
Bit#	Weight	Event	Description																																		
0	1	OPC	Operation Complete Bit																																		
1	2	RQC	Not used																																		
2	4	QYE	Query Error																																		
3	8	DDE	Device Error																																		
4	16	EXE	Execution Error																																		
5	32	CME	Command Error																																		
6	64	URQ	User Request																																		
7	128	PON	Power On																																		
Example	*ESE? >4 Indicates that there is a query error.																																				

### 3-1-8. \*ESR

→Query

Description	Queries the Standard Event Status (Event) register. The Event Status register is cleared after it is read.			
Query Syntax	*ESR?			
Return parameter	<NR1> 0~255			
Bit Weight	Bit#	Weight	Event	Description
	0	1	OPC	Operation Complete Bit
	1	2	RQC	Not used
	2	4	QYE	Query Error
	3	8	DDE	Device Error
	4	16	EXE	Execution Error
	5	32	CME	Command Error
	6	64	URQ	User Request
	7	128	PON	Power On

### Example

\*ESR?

>4


Indicates that there is a query error.

### 3-1-9. \*OPC

Set →  
→Query

Description	The *OPC command sets the OPC bit (bit0) of the Standard Event Status Register when all current commands have been processed. The *OPC? Query returns 1 when all the outstanding commands have completed.		
Syntax	*OPC		
Query Syntax	*OPC?		
Return parameter	1	Returns 1 when all the outstanding commands have completed.	

### 3-1-10. \*SRE



Description	Sets or queries the Service Request Enable register. The Service Request Enable register determines which registers of the Status Byte register are able to generate service requests.																																								
Syntax	*SRE <NR1>																																								
Query Syntax	*SRE?																																								
Parameter/ Return parameter	<NR1> 0~255																																								
Bit Weight	<table border="1"> <thead> <tr> <th>Bit#</th> <th>Weight</th> <th>Event</th> <th>Description</th> </tr> </thead> <tbody> <tr> <td>0</td> <td>1</td> <td></td> <td>Not used</td> </tr> <tr> <td>1</td> <td>2</td> <td></td> <td>Not used</td> </tr> <tr> <td>2</td> <td>4</td> <td></td> <td>Not used</td> </tr> <tr> <td>3</td> <td>8</td> <td></td> <td>Not used</td> </tr> <tr> <td>4</td> <td>16</td> <td>MAV</td> <td>Message Available Bit</td> </tr> <tr> <td>5</td> <td>32</td> <td>ESB</td> <td>Event Status Bit</td> </tr> <tr> <td>6</td> <td>64</td> <td>MSS</td> <td>Master Summary Bit</td> </tr> <tr> <td>6</td> <td>64</td> <td>RQS</td> <td>Request Service Bit</td> </tr> <tr> <td>7</td> <td>128</td> <td></td> <td>Not used</td> </tr> </tbody> </table>	Bit#	Weight	Event	Description	0	1		Not used	1	2		Not used	2	4		Not used	3	8		Not used	4	16	MAV	Message Available Bit	5	32	ESB	Event Status Bit	6	64	MSS	Master Summary Bit	6	64	RQS	Request Service Bit	7	128		Not used
Bit#	Weight	Event	Description																																						
0	1		Not used																																						
1	2		Not used																																						
2	4		Not used																																						
3	8		Not used																																						
4	16	MAV	Message Available Bit																																						
5	32	ESB	Event Status Bit																																						
6	64	MSS	Master Summary Bit																																						
6	64	RQS	Request Service Bit																																						
7	128		Not used																																						
Example	<pre>*SRE? &gt;48</pre> <p>Indicates that the MAVB and ESB bit are both set.</p>																																								

## 3-1-11. \*STB




Description	Queries the bit sum of the Status Byte register with MSS (Master summary Status) replacing the RQS bit (bit 6).			
Query Syntax	*STB?			
Return parameter	<NR1> 0 ~ 255			
Bit Weight	Bit#	Weight	Event	Description
	0	1		Not used
	1	2		Not used
	2	4		Not used
	3	8		Not used
	4	16	MAV	Message Available Bit
	5	32	ESB	Event Status Bit
	6	64	MSS	Master Summary Bit
	6	64	RQS	Request Service Bit
	7	128		Not used
Example	*STB? >16 Indicates that the MAV bit is set.			

## 3-2. Acquisition Commands


3-2-1. :ACQuire:AVERage.....	16
3-2-2. :ACQuire:MODE.....	16
3-2-3. :ACQuire<X>:MEMORY? .....	17
3-2-4. :ACQuire:FILTter:SOURce.....	18
3-2-5. :ACQuire:FILTter.....	19
3-2-6. :ACQuire:FILTter:FREQuency .....	19
3-2-7. :ACQuire:FILTter:FREQuency:UPPER .....	19
3-2-8. :ACQuire:FILTter:FREQuency:LOWER.....	20
3-2-9. :ACQuire:FILTter:TYPE.....	20
3-2-10. :ACQuire:FILTter:TRACKing.....	20
3-2-11. :ACQuire<X>:STATE?.....	21
3-2-12. :ACQuire:RECORDlength .....	21
3-2-13. :HEADER.....	22

### 3-2-1. :ACQuire:AVERage



Description	Selects or returns the number of waveform acquisitions that are averaged in the average acquisition mode.
Syntax	:ACQuire:AVERage {<NR1>  ?}
Related Commands	:ACQuire:MODE
Parameter	<NR1> 2, 4, 8, 16, 32, 64, 128, 256
Note	Before using this command, select the average acquisition mode. See the example below.
Example	:ACQuire:MODE AVERage :ACQuire:AVERage 2 Selects the average acquisition mode, and sets the average number to 2.

### 3-2-2. :ACQuire:MODE




Description	Selects or returns the acquisition mode.
Syntax	:ACQuire:MODE {SAMPLE   PDETect   AVERage   ?}
Related Commands	:ACQuire:AVERage
Parameter	SAMPLE Sample mode sampling PDETect Peak detect sampling AVERage Average sampling mode
Example	:ACQuire:MODE PDETect Sets the sampling mode to peak detection.

### 3-2-3. :ACQuire<X>:MEMORY?

→Query

Description	Returns the data in acquisition memory for the selected channel as a header + raw data.
Syntax	:ACQuire<X>:MEMORY?
Related Commands	ACQuire:RECOndlength :HEADER
Parameter	<X> Channel number (1 to 4)
Return parameter	<p>Returns acquisition settings followed by raw waveform block data.</p> <p>&lt;string&gt;</p> <p>Returns the acquisition settings for the selected channel.</p> <p>Format:</p> <p>parameter(1),setting(1);parameter(2),setting(2)...parameter(n),setting(n);Waveform Data;</p> <p>&lt;waveform block data&gt;</p> <p>Header followed by the raw waveform data.</p> <p>Format:</p> <p>Header: The header (in ASCII) encodes the number of bytes for the header followed by the number of data points in bytes for the raw data.</p>



#### Raw Data:

Each two bytes (in hex) encodes the vertical data of a data point. The data is signed hex data (2's complement, -32768 ~ 32767).

#### Waveform Raw Data Example:

Header raw data.....

#### Hex:

23 34 32 30 30 30 00 1C 00 1B 00 1A 00 1A 00 1B

---


.....  
**ASCII/Decimal:**  
#42000 28 27 26 26 27.....  
The actual value of a data point can be calculated with  
the following formula:  
(Decimal value of hex data/AD Factor) \* vertical scale.  
Note: AD Factor is fixed as 25. The vertical scale is  
returned with the acquisition settings that precede the  
raw data.  
For example if the raw data for a point is 001C (=28  
decimal) then,  
 $(28/25) \times 0.5 = 0.56V$

---

Example	:ACQuire1:MEMORY? Format,2.0E;Memory Length,10000;IntpDistance,0; Trigger Address,4999;Trigger Level,1.160E+01; Source,CH1;Vertical Units,V;Vertical Units Div,0;Vertical Units Extend Div,15;Label,ACK ;Probe Type,0;Probe Ratio,1.000e+01;Vertical Scale,5.000e+00;Vertical Position,- 1.100e+01;Horizontal Units,S;Horizontal Scale,5.000E- 04;Horizontal Position,0.000E+00; Horizontal Mode,Main;SincET Mode,Real Time;Sampling Period,5.000e-07;Horizontal Old Scale,5.000E- 04;Horizontal Old Position,0.000E+00; Firmware,V0.99b8;Time,02-Oct-14 17:00:43; Waveform Data; #520000...follows waveform block data in hex.....
Note:	On Windows 10, data loss may occur due to insufficient CPU power. Adjust the transfer timing with the ":USBDelay" command and use as fast a PC as possible.


---

### 3-2-4. :ACQuire:FILTter:SOURce




Description	Returns the source of the filter.
Syntax	:ACQuire:FILTter:SOURce {CH1 CH2 CH3 CH4 ?}
Parameter/ Return parameter	CH1 ~ CH4   Source channel
Example	:ACQuire:FILTter:SOURce? CH1 Sets the filter source to CH1.

### 3-2-5. :ACQuire:FILT<sub>E</sub>




Description	Turns the filter on/off or queries its status.	
Syntax	:ACQuire:FILT <sub>E</sub> {OFF   ON   ?}	
Parameter/Return parameter	OFF	Turns the digital filter off.
Example	:ACQuire:FILT <sub>E</sub> OFF Turns the digital filter off.	

### 3-2-6. :ACQuire:FILT<sub>E</sub>:FREQuency




Description	Sets or queries the filter frequency.	
Syntax	:ACQuire:FILT <sub>E</sub> :FREQuency {DEFault <NRf> ?}	
Parameter/ Return parameter	DEFault	Sets the filter frequency to the default.
Example	<NRf> Manually sets the filter frequency. (1Hz ~ 500MHz)	

### 3-2-7. :ACQuire:FILT<sub>E</sub>:FREQuency:UPPER




Parameter	DEFault	Sets the frequency to default.
	<NRf>	Sets the frequency to user.(Range:1Hz~500MHz)
Example	:ACQuire:FILT <sub>E</sub> :FREQuency:UPPER 4.95e+05 :ACQuire:FILT <sub>E</sub> :FREQuency:UPPER? 4.950000e+05	

### 3-2-8. :ACQuire:FILTter:FREQuency:LOWER




Description	Sets or returns the filter lower frequency.	
Syntax	<b>:ACQuire:FILTter:FREQuency:LOWER {DEFault}</b> <b>:ACQuire:FILTter:FREQuency:LOWER &lt;NRf&gt;</b> <b>:ACQuire:FILTter:FREQuency:LOWER?</b>	
Parameter	DEFault	Sets the frequency to default.
	<NRf>	Sets the frequency to user. (Range:1Hz~500MHz)
Example	<b>:ACQuire:FILTter:FREQuency:LOWER 1.25e+05</b> <b>:ACQuire:FILTter:FREQuency:LOWER?</b> <b>1.250000e+05</b>	

### 3-2-9. :ACQuire:FILTter:TYPe



Description	Sets or returns the filter type.	
Syntax	<b>:ACQuire:FILTter:TRACKing {LOWPass   HIGHPass  BANDPass}</b> <b>:ACQuire:FILTter:TYPe?</b>	
Parameter	LOWPass	Lowpass Type.
	HIGHPass	Highpass Type.
	BANDPass	bandpass Type.
Example	<b>:ACQuire:FILTter:TYPe?</b> <b>&gt;LOWPass</b> Returns low pass type as present filter type	

### 3-2-10. :ACQuire:FILTter:TRACKing



Description	Turns filter tracking on/off or queries its state.	
Syntax	<b>:ACQuire:FILTter:TRACKing {ON OFF ?}</b>	
Parameter/ Return parameter	OFF	Tracking off
	ON	Tracking on
Example	<b>:ACQuire:FILTter:TRACKing ON</b> Turns filter tracking on.	

### 3-2-11. :ACQuire<X>:STATe?

→Query

Description	Returns the status of waveform data.	
Syntax	:ACQuire<X>:STATe?	
Parameter	<X>	Channel number (1 to 4)
Return parameter	0	Raw data is not ready
	1	Raw data is ready
Example	<pre>:ACQuire1:STATe? 0 Returns 0. The channel 1's raw data is not ready. Note: If the oscilloscope changes the acquisition status from STOP to RUN, the status will be reset as zero.</pre>	

### 3-2-12. :ACQuire:RECOndlength

Set →

→Query

Description	Sets or queries the record length. Please see the user manual for full details.	
Syntax	:ACQuire:RECOndlength {<NRf>  ?}	
Parameter/Return parameter	<NRf>	Record length. Settable record length: (1e+3   1e+4   1e+5   1e+6   1e+7)
Example	<pre>:ACQuire:RECOndlength 1e+3 Sets the record length to 1000 points.</pre>	

### 3-2-13. :HEADER

Set →  
→ Query

Description	Configures whether the :ACQuire:MEM or :ACQuire:LMEM return data will contain header information or not. It is set to ON by default.	
Syntax	:HEADER {OFF   ON   ?}	
Related Commands	:ACQuire<X>:MEMORY?	
Parameter	<X>	Channel number (1 to 4)
	ON	Add header information.
	OFF	Don't add header information.
Return parameter	Returns the configuration (ON, OFF) for the selected channel.	
Example	:HEADER ON	

### 3-3. Autoscale Commands

#### 3-3-1. :AUTOSet

Set →

Description	Runs the Autoset function to automatically configure the horizontal scale, vertical scale, and trigger according to the input signal.	
Syntax	:AUTOSet	

#### 3-3-2. :AUTORSET:MODE


Set →  
→ Query

Description	Sets the Autoset mode or queries its state.	
Syntax	:AUTORSET:MODE {FITScreen   ACPriority   ?}	
Related Commands	:AUTOSet	
Parameter/Return parameter	FITScreen	Fit Screen mode
	ACPriority	AC priority mode
Example	:AUTORSET? FITSCREEN	

### 3-4. Vertical Commands


3-4-1. :CHANnel<X>:BWLimit .....	23
3-4-2. :CHANnel<X>:COUPLing .....	23
3-4-3. :CHANnel<X>:DESKew .....	24
3-4-4. :CHANnel<X>:DISPlay .....	24
3-4-5. :CHANnel<X>:EXPand .....	24
3-4-6. :CHANnel<X>:IMPedance? .....	25
3-4-7. :CHANnel<X>:INVert .....	25
3-4-8. :CHANnel<X>:POSition .....	25
3-4-9. :CHANnel<X>:PROBe:RATio .....	26
3-4-10. :CHANnel<X>:PROBe:TYPe .....	26
3-4-11. :CHANnel<X>:SCALE .....	26

#### 3-4-1. :CHANnel<X>:BWLimit




Description	Sets or returns the bandwidth limit on/off.	
Syntax	:CHANnel<X>:BWLimit {FULL   <NR3>   ?}	
Parameter	<X>	Channel 1,2,3,4
	FULL	Full bandwidth
	<NR3>	Sets the bandwidth limit to a pre-defined bandwidth. 100E+6: 100MHz 20E+6: 20MHz
Return Parameter	<NR3>	Returns the bandwidth. Full Full bandwidth
Example	:CHANnel1:BWLImit 2.000E+07 Sets the channel 1 bandwidth 20MHz	

#### 3-4-2. :CHANnel<X>:COUPLing




Description	Selects or returns the coupling mode.	
Syntax	CHANnel<X>:COUPLing {AC   DC   GND   ?}	
Parameter	<X>	Channel 1,2,3,4
	AC	AC coupling
	DC	DC coupling
	GND	Ground coupling
Return parameter	Returns the coupling mode.	
Example	:CHANnel1:COUPLing DC Sets the coupling to DC for Channel 1.	

### 3-4-3. :CHANnel<X>:DESKew




Description	Sets the deskew time in seconds.	
Syntax	:CHANnel<X>:DESKew { <NR3>   ? }	
Parameter	<X>	Channel 1,2,3,4
	<NR3>	Deskew time: -5.00E -11 to 5.00E-11 -50ns to 50 ns.
Return parameter	<NR3> Returns the deskew time.	
Example	:CHANnel1:DESKew 1.300E-9 Sets the deskew time to 1.3 nano seconds.	

### 3-4-4. :CHANnel<X>:DISPlay



Description	Turns a channel on/off or returns its status.	
Syntax	:CHANnel<X>:DISPlay {OFF   ON   ?}	
Parameter	<X>	Channel 1,2,3,4
	OFF	Channel off
	ON	Channel on
Return Parameter	ON	Channel is on.
	OFF	Channel is off
Example	:CHANnel1:DISPlay ON Turns on Channel 1	

### 3-4-5. :CHANnel<X>:EXPand



Description	Sets Expand By Ground or Expand By Center for a channel or queries its status.	
Syntax	:CHANnel<X>:EXPand {GND   CENTER   ?}	
Parameter	<X>	Channel 1,2,3,4
	GND	Ground
	CENTER	Center
Return parameter	GND	Expand By Ground
	CENTER	Expand By Center
Example	:CHANnel1:EXPand GND Sets Channel 1 to Expand By Ground.	

### 3-4-6. :CHANnel<X>:IMPedance?

→Query

Description	Returns the impedance of the oscilloscope.	
Syntax	:CHANnel<X>:IMPedance?	
Parameter	<x>	Channel
	1/2/3/4	CH1/2/3/4
Return parameter	<NR3>	Returns the impedance value.
Example	:CHANnel1:IMPedance?	1.000000E+06 The impedance is 1M ohms.

### 3-4-7. :CHANnel<X>:INVert

Set →  
→Query


Description	Inverts a channel or returns its status.	
Syntax	:CHANnel<X>:INVert {OFF   ON   ?}	
Parameter	<X>	Channel 1, 2, 3, 4
	OFF	Invert off
	ON	Invert on
Return parameter	ON	Invert on
	OFF	Invert off
Example	:CHANnel1:INVert ON Inverts Channel 1	

### 3-4-8. :CHANnel<X>:POSIon

Set →  
→Query


Description	Sets or returns the position level for a channel.	
Note	The vertical position will only be set to closest allowed value. The position level range depends on the vertical scale. The scale must first be set before the position can be set.	
Syntax	:CHANnel<X>:POSIon { <NRf>   ?}	
Parameter	<X>	Channel 1, 2, 3, 4
	<NRf>	Position. Range depends on the vertical scale.
Return parameter	<NR3>	Returns the position value.
Example 1	:CHANnel1:POSIon 2.4E-3 Sets the Channel 1 position to 2.4mV/mA	
Example 2	:CHANnel1:POSIon? 2.4E-3 Returns 2.4mV as the vertical position.	

### 3-4-9. :CHANnel<X>:PROBe:RATio




Description	Sets or returns the probe attenuation factor.				
Syntax	:CHANnel<X>:PROBe:RATio { <NRf>   ?}				
Related Commands	:CHANnel<X>:PROBe:TYPe				
Parameter	<table border="0"> <tr> <td>&lt;X&gt;</td> <td>Channel 1, 2, 3, 4</td> </tr> <tr> <td>&lt;NRf&gt;</td> <td>Probe attenuation factor.</td> </tr> </table>	<X>	Channel 1, 2, 3, 4	<NRf>	Probe attenuation factor.
<X>	Channel 1, 2, 3, 4				
<NRf>	Probe attenuation factor.				
Return parameter	<NR3> Returns the probe factor.				
Example	:CHANnel1:PROBe:RATio 1.00E+0 Sets the Channel 1 probe attenuation factor to 1x				

### 3-4-10. :CHANnel<X>:PROBe:TYPe



Description	Sets or returns the probe type (voltage/current).						
Syntax	:CHANnel<X>:PROBe:TYPe { VOLtage   CURRent   ?}						
Related Commands	:CHANnel<X>:PROBe:RATio						
Parameter	<table border="0"> <tr> <td>&lt;X&gt;</td> <td>Channel 1, 2, 3, 4</td> </tr> <tr> <td>VOLtage</td> <td>Voltage</td> </tr> <tr> <td>CURRent</td> <td>Current</td> </tr> </table>	<X>	Channel 1, 2, 3, 4	VOLtage	Voltage	CURRent	Current
<X>	Channel 1, 2, 3, 4						
VOLtage	Voltage						
CURRent	Current						
Return parameter	Returns the probe type.						
Example	:CHANnel1:PROBe:TYPe VOLtage Sets the Channel 1 probe type to voltage.						

### 3-4-11. :CHANnel<X>:SCALe



Description	Sets or returns the vertical scale. The scale depends on the probe attenuation factor.  Note the probe attenuation factor should be set before the scale.				
Syntax	:CHANnel<X>:SCALe { <NRf>   ?}				
Parameter	<table border="0"> <tr> <td>&lt;X&gt;</td> <td>Channel 1, 2, 3, 4</td> </tr> <tr> <td>&lt;NRf&gt;</td> <td>Vertical scale: 2e-3 to 1e+1 2mV to 10V (Probe x1)</td> </tr> </table>	<X>	Channel 1, 2, 3, 4	<NRf>	Vertical scale: 2e-3 to 1e+1 2mV to 10V (Probe x1)
<X>	Channel 1, 2, 3, 4				
<NRf>	Vertical scale: 2e-3 to 1e+1 2mV to 10V (Probe x1)				
Return parameter	<NR3> Returns the vertical scale in volts or amps.				
Example	:CHANnel1:SCALe 2.00E-2 Sets the Channel 1 vertical scale to 20mV/div				


### **3-5. Math Commands**

---

3-5-1. :MATH:DISP .....	27
3-5-2. :MATH:TYPe.....	27
3-5-3. :MATH:DUAL:SOURce<X>.....	28
3-5-4. :MATH:DUAL:OPERator .....	28
3-5-5. :MATH:DUAL:POSiition .....	28
3-5-6. :MATH:DUAL:SCALe .....	29
3-5-7. :MATH:FFT:SOURce .....	29
3-5-8. :MATH:FFT:MAG .....	29
3-5-9. :MATH:FFT:WINDow .....	30
3-5-10. :MATH:FFT:POSiition .....	30
3-5-11. :MATH:FFT:SCALe .....	30
3-5-12. :MATH:FFT:HORizontal:SCALe .....	31
3-5-13. :MATH:FFT:HORizontal:POSiition .....	31
3-5-14. :MATH:DEFine.....	32
3-5-15. :MATHVAR? .....	32
3-5-16. :MATHVAR:VAR<X>.....	33
3-5-17. :MATH:ADVanced:POSiition .....	33
3-5-18. :MATH:ADVanced:SCALe.....	33


---

#### **3-5-1. :MATH:DISP**




Description	Turns the math display on or off on the screen.	
Syntax	:MATH:DISP {OFF ON ?}	
Parameter/ Return parameter	OFF	Math is not displayed on screen
	ON	Math is displayed on screen
Example	:MATH:DISP OFF Math is off.	

#### **3-5-2. :MATH:TYPe**




Description	Queries or sets the Math type to FFT, Advanced Math or to dual channel math operations	
Syntax	:MATH:TYPe { DUAL   ADVanced   FFT   ? }	
Related Commands	:MATH:DISP	
Parameter	DUAL	Dual channel operations
	ADVanced	Advanced math operations
	FFT	FFT operations
Return parameter	Returns the math type.	
Example	:MATH:TYPe DUAL Sets the Math type to dual channel math operation.	

### 3-5-3. :MATH:DUAL:SOURce<X>




Description	Sets the dual math source for source 1 or 2.	
Syntax	:MATH:DUAL:SOURce<X> { CH1   CH2   CH3   CH4   REF1   REF2   REF3   REF4   ? }	
Parameter	<X> CH1~4 REF1~4	Source number 1 or 2 Channel 1 to 4 Reference waveforms 1 to 4
Return parameter	Returns the source for the source 1 or 2.	
Example	:MATH:DUAL:SOURce1 CH1 Sets source1 as channel 1.	

### 3-5-4. :MATH:DUAL:OPERator




Description	Sets the math operator for dual math operations.	
Syntax	:MATH:DUAL:OPERator {PLUS   MINUS   MUL  DIV ?}	
Parameter	PLUS MINUS MUL DIV	+ operator - operator × operator ÷ operator
Return parameter	Returns operator type.	
Example	:MATH:DUAL:OPERator PLUS Sets the math operator as plus (+).	

### 3-5-5. :MATH:DUAL:POSITION




Description	Sets the vertical position of the displayed math result expressed by division.	
Syntax	:MATH:DUAL:POSITION {<NRf>   ? }	
Parameter	<NRf>	Vertical position Depends on the vertical scale (Unit/Div)
Return parameter	<NR3> Returns the vertical position.	
Example	:MATH:DUAL:POSITION 1.0E+0 Sets the vertical position to 1.00 unit/div.	

### 3-5-6. :MATH:DUAL:SCALe




Description	Sets the vertical scale of the displayed math result.
Syntax	:MATH:DUAL:SCALe {<NRf>   ?}
Parameter	<NRf> Vertical scale
Return parameter	<NR3> Returns the scale.
Example	:MATH:DUAL:SCALe 2.0E-3 Sets the vertical scale to 2mV/2mA.

### 3-5-7. :MATH:FFT:SOURce




Description	Sets and queries the FFT math source.
Syntax	:MATH:FFT:SOURce { CH1   CH2   CH3   CH4   REF1   REF2   REF3   REF4   FUNCtion   ? }
Related commands	:MATH:ADVanced:EDIT:SOURce<X> :MATH:ADVanced:EDIT:OPERator
Parameter	CH1~4 Channel 1 to 4 REF1~4 Reference waveform 1 to 4 FUNCtion F(X) waveform
Return parameter	Returns the FFT source.
Example	:MATH:FFT:SOURce CH1 Sets the FFT math source as channel 1.

### 3-5-8. :MATH:FFT:MAG




Description	Sets FFT vertical units as linear or decibels.
Syntax	:MATH:FFT:MAG {LINEAR   DB   ?}
Parameter	LINEAR Linear units (Vrms) DB Logarithmic units (dB)
Return parameter	Returns the FFT vertical units.
Example	:MATH:FFT:MAG DB Sets FFT vertical units to dB.

### 3-5-9. :MATH:FFT:WINDOW




Description	Sets the windowing filter used for the FFT function.	
Syntax	<code>:MATH:FFT:WINDOW {RECTangular HAMming HANning BLAckman ?}</code>	
Parameter	RECTangular	Rectangular window
	HAMming	Hamming window
	HANning	Hanning window
	BLAckman	Blackman window
Return parameter	Returns the FFT window.	
Example	<code>:MATH:FFT:WINDOW HAMming</code> Sets the FFT window filter to hamming.	

### 3-5-10. :MATH:FFT:POSITION



Description	Sets the vertical position of the displayed FFT result.	
Syntax	<code>MATH:FFT:POSITION { &lt;NRf&gt;   ? }</code>	
Parameter	<NRf>	Vertical position: -12e+0 to +12e+0 (12 units/division to +12 units/division.)
Return parameter	<NR3>	Returns the vertical position.
Example	<code>:MATH:FFT:POSITION -2e-1</code> Sets the FFT position to -0.2 divisions.	

### 3-5-11. :MATH:FFT:SCALE



Description	Sets the vertical scale of the displayed FFT result.	
Syntax	<code>:MATH:FFT:SCALE {&lt;NRf&gt;   ? }</code>	
Parameter	<NRf>	Vertical scale: Linear: 2e-3 to 1e+ (32mV~1kV) dB: 1e+0 to 2e+1 (1~20dB)
Return parameter	<NR3>	Returns vertical scale.
Example	<code>:MATH:FFT:SCALE 1.0e+0</code> Sets the scale to 1dB.	

### 3-5-12. :MATH:FFT:HORizontal:SCALe

 Set  
 Query


Description	Sets or queries the zoom scale for FFT math.
Syntax	:MATH:FFT:HORizontal:SCALe {<NRf>   ?}
Parameter	<NRf> Zoom scale: 1 to 20 times
Return parameter	<NR3> Returns zoom scale.
Example	:MATH:FFT:HORizontal:SCALe 5 Sets the zoom scale to 5X.

### 3-5-13. :MATH:FFT:HORizontal:POSIon

 Set  
 Query


Description	Sets the horizontal position of the displayed FFT result.
Syntax	MATH:FFT:HORizontal:POSIon { <NRf>   ? }
Parameter	<NRf> Horizontal position: 0Hz ~ 999.9kHz
Return parameter	<NR3> Returns the vertical position.
Example	:MATH:FFT:HORizontal:POSIon 6.0e5 Sets the FFT horizontal position to 600kHz.

### 3-5-14. :MATH:DEFine



Description	Sets or queries the advanced math expression as a string.
Syntax	:MATH:DEFine {<string>} ?
Related	:MATH:DISP :MATH:TYPE
Parameter	<p>&lt;string&gt; An expression enclosed in double quotes. Note, ensure parentheses are used correctly in the expression. The expression can contain the following parts:</p> <p>Source CH1~CH4, Ref1~Ref4</p> <p>Function Intg(), Diff(), log(), ln(), Exp(), Sqrt(), Abs(), Rad(), Deg(), sin(), cos(), tan(), asin(), acos(), atan()</p> <p>Variable VAR1, VAR2</p> <p>Operator +, -, *, /, (, ), !(, &lt;, &gt;, &lt;=, &gt;=, ==, !=,   , &amp;&amp;</p> <p>Figure 0, 1, 2, 3, 4, 5, 6, 7, 8, 9, ., E</p> <p>Measure- Pk-Pk(), Max(), Min(), Amp(), High(), ment Low(), Mean(), CycleMean(), RMS(), CycleRMS(), Area(), CycleArea(), ROVShoot(), FOVShoot(), Freq(), Period(), Rise(), Fall(), PosWidth(), NegWidth(), DutyCycle(), FRR(), FRF(), FFR(), FFF(), LRR(), LRF(), LFR(), LFF(), Phase()</p>
Return parameter	Returns the expression as a string.
Example	<pre>:MATH:DISP ON :MATH:TYPE ADVanced :MATH:DEFine "CH1-CH2" Sets the math expression to CH1-CH2.</pre>

### 3-5-15. :MATHVAR?



Description	Returns the value of the VAR1 and VAR2 variables.
Syntax	:MATHVAR?
Related	:MATHVAR:VAR<X>
Commands	:MATH:DEFine
Return parameter	<string> VAR1 <NR3>; VAR2 <NR3>
Example	<pre>:MATHVAR? VAR1 1.000000E+06; VAR2 1.0E+1 Returns the value of both variables.</pre>

### 3-5-16. :MATHVAR:VAR<X>

Set →  
→ Query

Description	Sets or returns the VAR1 or VAR2 variables.	
Syntax	:MATHVAR:VAR<x> {<NRf>   ?}	
Related Commands	:MATH:DEFine	
Parameter	<X>	1, 2 (VAR1 or VAR2)
	<NRf>	Value of VAR1/VAR2
Return parameter	<NR3>	Returns the value of VAR1/VAR2
Example	:MATHVAR:VAR1 6.0e4	Sets VAR1 to 60000.

### 3-5-17. :MATH:ADVanced:POSIon

Set →  
→ Query

Description	Sets the vertical position of the advanced math result, expressed in unit/div.	
Syntax	:MATH:ADVanced:POSIon { <NRf>   ? }	
Parameter	<NRf>	Vertical position: -12e+0 to +12e+0 (12 units/division to +12 units/division.)
Return parameter	<NR3>	Returns the vertical position.
Example	:MATH:ADVanced:POSIon 1.0e+0 Sets the position as 1.00 unit/div.	

### 3-5-18. :MATH:ADVanced:SCALe

Set →  
→ Query

Description	Sets or queries the vertical scale the advanced math result.	
Syntax	:MATH:ADVanced:SCALe {<NRf>   ?}	
Parameter	<NRf>	Vertical scale
Return parameter	<NR3>	Returns the vertical scale.
Example	:MATH:ADVanced:SCALe 2.0E-3 Sets the vertical scale to 2mV/S	


### **3-6. Cursor Commands**

---

3-6-1. :CURSor:MODE .....	34
3-6-2. :CURSor:SOURce .....	35
3-6-3. :CURSor:HUNI.....	35
3-6-4. :CURSor:HUSE.....	35
3-6-5. :CURSor:VUNI.....	36
3-6-6. :CURSor:VUSE.....	36
3-6-7. :CURSor:DDT .....	36
3-6-8. :CURSor:H1Position .....	37
3-6-9. :CURSor:H2Position .....	37
3-6-10. :CURSor:HDELta .....	37
3-6-11. :CURSor:V1Position.....	38
3-6-12. :CURSor:V2Position.....	38
3-6-13. :CURSor:VDELta .....	38
3-6-14. :CURSor:XY:RECTangular:X:POSition<X> .....	39
3-6-15. :CURSor:XY:RECTangular:X:DELta .....	39
3-6-16. :CURSor:XY:RECTangular:Y:POSition<X> .....	39
3-6-17. :CURSor:XY:RECTangular:Y:DELta .....	40
3-6-18. :CURSor:XY:POLar:RADIUS:POSition<X> .....	40
3-6-19. :CURSor:XY:POLar:RADIUS:DELta .....	40
3-6-20. :CURSor:XY:POLar:THETA:POSITION<X> .....	40
3-6-21. :CURSor:XY:POLar:THETA:DELta .....	41
3-6-22. :CURSor:XY:PRODUCT:POSITION<X> .....	41
3-6-23. :CURSor:XY:PRODUCT:DELta .....	41
3-6-24. :CURSor:XY:RATio:POSition<X> .....	41
3-6-25. :CURSor:XY:RATio:DELta .....	42

---

#### **3-6-1. :CURSor:MODE**



Description	Sets cursor mode to horizontal (H) or horizontal and vertical (HV). Note: When the cursor source is set to bus, then only the horizontal cursor is available.	
Syntax	:CURSor:MODE {OFF   H   HV   ? }	
Parameter	OFF	Turns the cursors off.
	H	Turns the horizontal cursors on.
	HV	Turns horizontal and vertical cursors on.
Return parameter	Returns the state of the cursors (H, HV, OFF).	
Example	:CURSor:MODE OFF Turns the cursors off.	

### 3-6-2. :CURSOR:SOURce

Set →  
→ Query

---

Description	Sets or queries the cursor source.	
Syntax	:CURSOR:SOURce {CH1   CH2   CH3   CH4   REF1   REF2   REF3   REF4   MATH   BUS1   ?}	
Parameter	CH1~CH4 REF1~4 MATH BUS1	Channel 1 to 4 Reference waveform 1 to 4 Math source Bus source
Return parameter	Returns the cursor source.	
Example	:CURSOR:SOURce CH1 Turns the cursor source as channel 1.	

---

### 3-6-3. :CURSOR:HUNI

Set →  
→ Query

---

Description	Sets or queries the units for the horizontal bar cursors.	
Syntax	:CURSOR:HUNI {SEConds   HERtz   DEGrees   PERcent   ?}	
Related Commands	:CURSOR:MODE	
Parameter	SEConds HERtz DEGrees PERcent	Sets the cursor units to time in seconds. Sets the cursor units to frequency. Sets the cursor units to degrees. Sets the cursor units to percent.
Return parameter	Returns the unit type.	
Example	:CURSOR:HUNI SEConds Sets the units to time in seconds.	

---

### 3-6-4. :CURSOR:HUSE

Set →

---

Description	Sets the current cursor position as the phase or ratio reference for the Percent or Degrees (horizontal) cursors.	
Note	This command can only be used when :CURSOR:HUNI is set to DEGrees or PERcent.	
Syntax	:CURSOR:HUSE {CURREnt}	
Related Commands	:CURSOR:MODE :CURSOR:HUNI	
Parameter	CURREnt	Uses the current horizontal position
Example	:CURSOR:HUSE CURREnt.	

---

### 3-6-5. :CURSor:VUNI

Set →  
→ Query

Description	Sets or queries the units for the vertical bar cursors.	
Syntax	:CURSor:VUNI {BASE   PERcent   ?}	
Related Commands	:CURSor:MODE	
Parameter	BASE	Sets the vertical cursor units the same as the scope units (V or A).
	PERcent	Sets the displayed units to percent.
Return parameter	Returns the unit type.	
Example	:CURSor:VUNI BASE Sets the units to the base units.	

### 3-6-6. :CURSor:VUSE

Set →


Description	Sets the current cursor position as the ratio reference for the Percent (vertical) cursors.	
Note	This command can only be used when :CURSor:VUNI is set to PERcent.	
Syntax	:CURSor:VUSE {CURRent}	
Related Commands	:CURSor:MODE :CURSor:VUNI	
Parameter	CURRent	Uses the current vertical position
Example	:CURSor:VUSE CURRent.	

### 3-6-7. :CURSor:DDT

→ Query


Description	Returns the deltaY/deltaT (dy/dT) readout.	
Syntax	:CURSor:DDT {?}}	
Related Commands	:CURSor:MODE	
Return Parameter	<NR3>	Returns the readout in <NR3> format.
Example	:CURSor:DDT? 4.00E-05	

### 3-6-8. :CURSOR:H1Position



Description	Sets or returns the first horizontal cursor (H1) position.
Syntax	:CURSOR:H1Position {<NRf>  ?}
Related Commands	:CURSOR:H2Position
Parameter	<NRf>      Horizontal position
Return parameter	Returns the cursor position.
Example	:CURSOR:H1Position? -1.34E-3 Returns the H1 cursor position as -1.34ms.

### 3-6-9. :CURSOR:H2Position




Description	Sets or returns the second horizontal cursor (H2) position.
Syntax	:CURSOR:H2Position {<NRf>   ?}
Related Commands	:CURSOR:H1Position
Parameter	<NRf>      Horizontal Position
Return parameter	Returns the cursor position.
Example	:CURSOR:H2Position 1.5E-3 Sets the H2 cursor position to 1.5ms.

### 3-6-10. :CURSOR:HDELta




Description	Returns the delta of H1 and H2.
Syntax	:CURSOR:HDELta {?}
Return Parameter	<NR3>      Returns the distance between two horizontal cursors.
Example	:CURSOR:HDELta? 5.0E-9 Returns the horizontal delta as 5ns.

### 3-6-11. :CURSOR:V1Position



Description	Sets the first vertical cursor (V1) position.	
Syntax	:CURSOR:V1Position {<NRf>   ?}	
Parameter	<NRf>	Vertical position. Depends on the vertical scale.
Return parameter	<NR3>	Returns the cursor position.
Example	:CURSOR:V1Position 1.6E -1 Sets the V1 cursor position to 160mA.	

### 3-6-12. :CURSOR:V2Position




Description	Sets the first vertical cursor (V2) position.	
Syntax	:CURSOR:V2Position {<NRf>   ?}	
Parameter	<NRf>	Vertical position. Depends on the vertical scale.
Return parameter	<NR3>	Returns the cursor position.
Example	:CURSOR:V2Position 1.1E-1 Sets the V2 cursor position to 110mA.	

### 3-6-13. :CURSOR:VDELta



Description	Returns the delta of V1 and V2.	
Syntax	:CURSOR:VDELta {?}	
Return Parameter	<NR3>	Returns the difference between two vertical cursors.
Example	:CURSOR:VDELta? 4.00E+0 Returns the vertical delta as 4 volts.	

### 3-6-14. :CURSOR:XY:RECTangular:X:POSIon<X>




Description	Sets or queries the horizontal position in XY mode for the X rectangular coordinates for cursor 1 or 2.
Syntax	:CURSOR:XY:RECTangular:X:POSIon<X> {NRf ?}
Parameter	<X> Cursor 1, 2 <NRf> Horizontal position co-ordinates
Return parameter	<NR3> Returns the cursor position.
Example	:CURSOR:XY:RECTangular:X:POSIon1 4.0E-3 Sets the X-coordinate cursor 1 position to 40mV/mV.

### 3-6-15. :CURSOR:XY:RECTangular:X:DELta



Description	Returns the delta value of cursor 1 and 2 on the X coordinate.
Syntax	:CURSOR:XY:RECTangular:X:DELta {?}
Return Parameter	<NR3> Returns the delta value of cursor 1 and 2 as <NR3>.
Example	:CURSOR:XY:RECTangular:X:DELta? 80.0E-3 Returns the horizontal delta as 80mV.

### 3-6-16. :CURSOR:XY:RECTangular:Y:POSIon<X>



Description	Sets or queries the vertical position in XY mode for the Y rectangular coordinates for cursor 1 or 2.
Syntax	:CURSOR:XY:RECTangular:Y:POSIon<X> {NRf ?}
Parameter	<X> Cursor 1, 2 <NRf> Vertical position co-ordinates
Return parameter	<NR3> Returns the cursor position.
Example	:CURSOR:XY:RECTangular:Y:POSIon1 4.0E-3 Sets the Y-coordinate cursor 1 position to 40mV/mV.

### 3-6-17. :CURSOR:XY:RECTangular:Y:DELta

→Query

Description	Returns the delta value of cursor 1 and 2 on the Y coordinate.
Syntax	:CURSOR:XY:RECTangular:Y:DELta {?}
Return Parameter	<NR3> Returns the delta value of cursor 1 and 2 as <NR3>.
Example	:CURSOR:XY:RECTangular:Y:DELta? 80.0E-3 Returns the horizontal delta as 80mV.

### 3-6-18. :CURSOR:XY:POLar:RADIUS:POSITION<X>

→Query

Description	Queries the polar radius position for the specified cursor in XY mode, where X can be either cursor 1 or 2.
Syntax	:CURSOR:XY:POLar:RADIUS:POSITION <X>{?}
Parameter	<X> 1, 2 (cursor 1, cursor 2)
Return Parameter	<NR3> Returns the polar radius position.
Example	:CURSOR:XY:POLar:RADIUS:POSITION? 80.0E-3 Returns the polar radius position as 80.0mV.

### 3-6-19. :CURSOR:XY:POLar:RADIUS:DELta

→Query

Description	Returns the radius delta value of cursor 1 and 2.
Syntax	:CURSOR:XY:POLar:RADIUS:DELta {?}
Return Parameter	<NR3> Returns the radius delta.
Example	:CURSOR:XY:POLar:RADIUS:DELta? 31.4E-3 Returns the radius delta as 31.4mV.

### 3-6-20. :CURSOR:XY:POLar:THETA:POSITION<X>

→Query

Description	Queries the polar angle for the specified cursor in XY mode, where X can be either 1 or 2.
Syntax	:CURSOR:XY:POLar:THETA:POSITION <X> {?}
Parameter	<X> 1, 2 (Cursor 1, Cursor 2)
Return parameter	<NR3> Returns the polar angle.
Example	:CURSOR:XY:POLAR:RADIUS:POSITION1? 8.91E+1 Returns the polar angle for cursor1 as 89.1°.

### 3-6-21. :CURSOR:XY:POLar:THETA:DELta

→Query

Description	Queries the polar angle delta between cursor1 and cursor2.
Syntax	:CURSOR:XY:POLar:THETA:DELta {?}
Return parameter	<NR3> Returns the theta delta between cursor1 and cursor2.
Example	:CURSOR:XY:POLar:THETA:DELta? 9.10E+0 Returns the delta as 9.1°.

### 3-6-22. :CURSOR:XY:PRODuct:POsition<X>

→Query

Description	Queries the product in XY mode for the specified cursor, where x can be either 1 or 2.
Syntax	:CURSOR:XY:PRODuct:POsition<X> {?}
Parameter	<X> 1, 2 (Cursor 1, Cursor 2)
Return parameter	<NR3> Returns the product value of the Cursor1 or Cursor2.
Example	:CURSOR:XY:PRODuct:POsition1? 9.44E-5 Returns the product of cursor1 as 94.4uVV.

### 3-6-23. :CURSOR:XY:PRODuct:DELta

→Query

Description	Queries the product delta in XY mode.
Syntax	:CURSOR:XY:PRODuct:DELta {?}
Return parameter	<NR3> Returns the product delta.
Example	:CURSOR:XY:PRODuct:DELta? 1.22E-5 Returns the product delta as 12.2uVV.

### 3-6-24. :CURSOR:XY:RATio:POsition<X>

→Query

Description	Queries the ratio in XY mode for the specified cursor, where x can be either cursor 1 or 2.
Syntax	:CURSOR:XY:RATio:POsition<X> {?}
Parameter	<X> 1, 2 (Cursor 1, Cursor 2)
Return parameter	<NR3> Returns the ratio.
Example	:CURSOR:XY:RATio:POsition? 6.717E+1 Returns the ratio value as 6.717V/V.

### 3-6-25. :CURSor:XY:RATio:DELta

→(Query)

Description      Queries the ratio delta in XY mode.

Syntax      :CURSor:XY:RATio:DELta {?}

Return parameter <NR3>      Returns the ratio delta.

Example      :CURSor:XY:RATio:DELta?

5.39E+1

Returns the ratio delta as 53.9V/V.

## 3-7. Display Commands

3-7-1. :DISPlay:INTensity:WAVEform.....	42
3-7-2. :DISPlay:INTensity:GRATicule.....	43
3-7-3. :DISPlay:INTensity:BACKLight.....	43
3-7-4. :DISPlay:INTensity:BACKLight:AUTODim:ENAbLe .....	43
3-7-5. :DISPlay:INTENSITy:BACKLight:AUTODim:TIme .....	43
3-7-6. :DISPlay:PERSistence .....	44
3-7-7. :DISPlay:GRATicule.....	44
3-7-8. :DISPlay:WAVEform .....	44
3-7-9. :DISPlay:OUTPut .....	45

### 3-7-1. :DISPlay:INTensity:WAVEform

→(Set)

→(Query)

Description      Sets or queries the waveform intensity level.

Syntax      :DISPlay:INTensity:WAVEform {<NRf> | ?}


Parameter      <NRf>      0.0E+0 to 1.0E+2 (0% to 100%)

Return Parameter <NR3>      Returns the display intensity.

Example      :DISPlay:INTensity:WAVEform 5.0E+1


Sets the waveform intensity to 50%.

### 3-7-2. :DISPlay:INTensity:GRATicule




Description	Sets or queries the graticule intensity level.
Syntax	:DISPlay:INTensity:GRATicule {<NRf>   ?}
Parameter	<NRf> 1.0E+0 to 1.0E+2 (10% to 100%)
Return Parameter	<NR3> Returns the graticule intensity.
Example	:DISPlay:INTensity:GRATicule 5.0E+1 Sets the graticule intensity to 50%.

### 3-7-3. :DISPlay:INTensity:BACKLight




Description	Sets or queries the intensity of the backlight display.
Syntax	:DISPlay:INTensity:BACKLight {<NRf>   ?}
Parameter	<NRf> 1.0E+0 to 1.0E+2 (10% to 100%)
Return Parameter	<NR3> Returns the backlight intensity.
Example	:DISPlay:INTensity:BACKLight 5.0E+1 Sets the backlight intensity to 50%.

### 3-7-4. :DISPlay:INTensity:BACKLight:AUTODim:ENAbLe




Description	Sets or queries the display auto-dim function.
Syntax	:DISPlay:INTensity:BACKLight:AUTODim:ENAbLe {OFF   ON   ?}
Parameter/ Return parameter	OFF Turn auto-dim on. ON Turn auto-dim off.
Example	:DISPlay:INTensity:BACKLight:AUTODim:ENAbLe ON Turns the auto-dim function on.

### 3-7-5. :DISPlay:INTENSITy:BACKLight:AUTODim:TIME




Description	Sets or queries the display auto-dim time.
Syntax	:DISPlay:INTensity:BACKLight:AUTODim:TIME { <NR1>   ? }
Parameter/ Return parameter	<NR1> 1 ~ 180 minutes. Time in minutes.
Example	:DISPlay:INTensity:BACKLight:AUTODim:TIME 10 Sets the auto-dim time to 10 minutes.

### 3-7-6. :DISPLAY:PERStance




Description	Sets or queries the waveform persistence level.			
Syntax	:DISPLAY:PERStance { INFInite   OFF   <NRf>   ? }			
Parameter	<NRf>	16E-3, 30E-3, 60E-3, 120E-3, 240E-3, 500E-3, 750E-3, 1, 1.5, 2, ..., 9.5, 10 (16mS to 10S)	INFInite	Infinite persistence
	OFF		No persistence	
Return Parameter	<NR3>	Returns the persistence time.		
	INFInite	Infinite persistence		
	OFF	No persistence		
Example	:DISPLAY:PERStance 2.0E+0	Sets the persistence to 2 seconds.		

### 3-7-7. :DISPLAY:GRATICule



Description	Sets or queries graticule display type.			
Syntax	:DISPLAY:GRATICule { FULL   GRID   CROSs   FRAME   ? }			
Parameter	FULL		CROSs	
	FRAME		GRID	
Return parameter	Returns the graticule type.			
Example	:DISPLAY:GRATICule FULL Sets the graticule to .			

### 3-7-8. :DISPLAY:WAVEform



Description	Sets or queries whether the waveforms are drawn as vectors or dots.	
Syntax	:DISPLAY:WAVEform { VECTOr   DOT   ? }	
Parameter	VECTOr	Vectors
	DOT	Dots
Return parameter	Returns VECTOr or DOT.	
Example	:DISPLAY:WAVEform VECTOr Sets the waveform to vectors.	

### 3-7-9. :DISPlay:OUTPut

→Query

Description	Returns the screen image as a 16 bit RGB run length encoded image.
Syntax	:DISPlay:OUTPut ?
Return parameter	Returns: header + data + LF
Example	For example assuming the image data size is 31649 bytes then the following would be returned: #531649<[count] [color] [count] [color]..... ><LF> Where #531649 is the header, each [count] and [color] data are 2 bytes and <LF> is a line feed character.
Note:	On Windows 10, data loss may occur due to insufficient CPU power. Adjust the transfer timing with the ":USBDelay" command and use as fast a PC as possible.

## 3-8. Hardcopy Commands


3-8-1. :HARDcopy:START.....	45
3-8-2. :HARDcopy:MODE.....	46
3-8-3. :HARDcopy:PRINTINKSaver .....	46
3-8-4. :HARDcopy:SAVEINKSaver.....	46
3-8-5. :HARDcopy:SAVEFORMAT .....	47
3-8-6. :HARDcopy:ASSIGN.....	47

### 3-8-1. :HARDcopy:START

Set →


Description	Executing the HARDcopy:START command is the equivalent of pressing the Hardcopy key on the front panel.
Syntax	:HARDcopy:START
Related Commands	:HARDcopy:MODE :HARDcopy:PRINTINKSaver :HARDcopy:SAVEINKSaver :HARDcopy:SAVEFORMAT :HARDcopy:ASSIGN

### 3-8-2. :HARDcopy:MODE



Description	Sets or queries whether hardcopy is set to print or save.	
Syntax	:HARDcopy:MODE { PRINT   SAVE   ? }	
Related Commands	:HARDcopy:START	
Parameter	PRINT	Print mode
	SAVE	Save mode
Return parameter	Returns the mode.(PRINT/SAVE)	
Example	:HARDcopy:MODE PRINT Sets hardcopy to print.	

### 3-8-3. :HARDcopy:PRINTINKSaver




Description	Sets Inksaver On or Off for printing.	
Syntax	:HARDcopy:PRINTINKSaver { OFF   ON   ? }	
Related Commands	:HARDcopy:START :HARDcopy:MODE	
Parameter	ON	Inksaver ON
	OFF	Inksaver OFF
Return parameter	Returns the print Ink Saver mode.(ON/OFF)	
Example	:HARDcopy:PRINTINKSaver ON Sets Ink Saver to ON for printing.	

### 3-8-4. :HARDcopy:SAVEINKSaver




Description	Sets Inksaver On or Off for saving screen images.	
Syntax	:HARDcopy:SAVEINKSaver { OFF   ON   ? }	
Related Commands	:HARDcopy:START :HARDcopy:MODE	
Parameter	ON	Inksaver ON
	OFF	Inksaver OFF
Return parameter	Returns the screen image Ink Saver mode (ON/OFF).	
Example	:HARDcopy:SAVEINKSaver ON Sets Inksaver to ON for saving screen images.	

### 3-8-5. :HARDcopy:SAVEFORMAT



Description	Sets or queries the image save file type.	
Syntax	:HARDcopy:SAVEFORMAT { PNG   BMP   ? }	
Related Commands	:HARDcopy:START :HARDcopy:MODE	
Parameter	PNG	PNG file format
	BMP	BMP file format
Return parameter	Returns the image file format (PNG/BMP).	
Example	:HARDcopy:SAVEFORMAT PNG Sets the file format to PNG.	

### 3-8-6. :HARDcopy:ASSIGN



Description	Sets or queries what file type the hardcopy key has been assigned to save.	
Syntax	:HARDcopy:ASSIGN {IMAGe   WAVEform   SETUp   ALL   ?}	
Related Commands	:HARDcopy:START :HARDcopy:MODE	
Parameter	IMAGe	Save image files.
	WAVEform	Save waveforms.
	SETUp	Save the panel setup.
	ALL	Save All (image, waveform,setup)
Return parameter	Returns the file type. (IMAGE/WAVEFORM/SETUP/ALL)	
Example	:HARDcopy:ASSIGN IMAGE. Set the hardcopy key to save image files.	


### **3-9. Measure Commands**

---

3-9-1. :MEASure:GATing .....	49
3-9-2. :MEASure:SOURce .....	49
3-9-3. :MEASure:METHod .....	49
3-9-4. :MEASUrement:REFLevel:PERCent:HIGH .....	50
3-9-5. :MEASUrement:REFLevel:PERCent:LOW .....	50
3-9-6. :MEASUrement:REFLevel:PERCent:MID .....	50
3-9-7. :MEASUREMENT:REFLevel:PERCent:MID2 .....	50
3-9-8. :MEASure:FALL .....	51
3-9-9. :MEASure:FOVShoot .....	51
3-9-10. :MEASure:FPReShoot .....	51
3-9-11. :MEASure:FREQuency .....	52
3-9-12. :MEASure:NWIDth .....	52
3-9-13. :MEASure:PDUTy .....	53
3-9-14. :MEASure:PERiod .....	53
3-9-15. :MEASure:PWIDth .....	54
3-9-16. :MEASure:RISe .....	54
3-9-17. :MEASure:ROVShoot .....	55
3-9-18. :MEASure:RPReShoot .....	55
3-9-19. :MEASure:PPULSE .....	56
3-9-20. :MEASure:NPULSE .....	56
3-9-21. :MEASure:PEDGE .....	57
3-9-22. :MEASure:NEDGE .....	57
3-9-23. :MEASure:AMPlitude .....	58
3-9-24. :MEASure:MEAN .....	58
3-9-25. :MEASure:CMEan .....	59
3-9-26. :MEASure:HIGH .....	59
3-9-27. :MEASure:LOW .....	60
3-9-28. :MEASure:MAX .....	60
3-9-29. :MEASure:MIN .....	61
3-9-30. :MEASure:PK2PK .....	61
3-9-31. :MEASure:RMS .....	62
3-9-32. :MEASure:CRMS .....	62
3-9-33. :MEASure:AREa .....	63
3-9-34. :MEASure:CARea .....	63
3-9-35. :MEASure:FRRDelay .....	64
3-9-36. :MEASure:FRFDelay .....	64
3-9-37. :MEASure:FFRDelay .....	65
3-9-38. :MEASure:FFFDelay .....	65
3-9-39. :MEASure:LRRDelay .....	66
3-9-40. :MEASure:LRFDelay .....	66
3-9-41. :MEASure:LFRDelay .....	67
3-9-42. :MEASure:LFFDelay .....	67
3-9-43. :MEASure:PHAse .....	68


---

### 3-9-1. :MEASure:GATing




Description	Sets or queries the measurement gating.	
Syntax	:MEASure:GATing { OFF   SCREen   CURSor   ? }	
Parameter	OFF	Full record
	SCREen	Gating set to screen width
	CURSor	Gating between cursors
Return parameter	Returns the gating. (OFF, SCREEN, CURSOR)	
Example	:MEASure:GATing OFF Turns gating off (full record).	

### 3-9-2. :MEASure:SOURce




Description	Sets or queries the measurement source for source1 or source2.	
Syntax	:MEASure:SOURce<X> { CH1   CH2   CH3   CH4   MATH   ? }	
Parameter	<X>	Source1 or source2
	CH1~CH4	Channel 1 to 4
	MATH	Math
Return parameter	Returns the source (CH1, CH2, CH3, CH4, MATH)	
Example	:MEASure:SOURce1 CH1 Sets source1 to channel 1.	

### 3-9-3. :MEASure:METHod




Description	Sets or queries the method used to determine the High-Low measurement values.	
Syntax	:MEASure:METHod { AUTO   HIStogram   MINMax   ? }	
Parameter	AUTO	Set to auto.
	HIStogram	Set to the Histogram method.
	MINMax	Set to the Min-Max method.
Return parameter	Returns the measurement method (AUTO, HISTOGRAM, MINMAX)	
Example	:MEASure:METHod: AUTO Set the measurement method to auto.	

### 3-9-4. :MEASUrement:REFLevel:PERCent:HIGH




Description	Sets or queries the high reference level as a percentage.
Syntax	:MEASUrement:REFLevel:PERCent:HIGH {<NRf>   ?}
Parameter	<NRf> 0 - 100%
Return parameter	Returns the high reference level
Example	:MEASUrement:REFLevel:PERCent:HIGH 50.1 Set the high reference level to 50.1%.

### 3-9-5. :MEASUrement:REFLevel:PERCent:LOW




Description	Sets or queries the low reference level as a percentage.
Syntax	:MEASUrement:REFLevel:PERCent:LOW {<NRf>   ?}
Parameter	<NRf> 0 - 100%
Return parameter	Returns the low reference level.
Example	:MEASUrement:REFLevel:PERCent:LOW 40.1 Set the low reference level to 40.1%.

### 3-9-6. :MEASUrement:REFLevel:PERCent:MID



Description	Sets or queries the first mid reference level as a percentage.
Syntax	:MEASUrement:REFLevel:PERCent:MID {<NRf>   ?}
Parameter	<NRf> 0 - 100%
Return parameter	Returns the mid reference level.
Example	:MEASUrement:REFLevel:PERCent:MID 50 Set the mid reference level to 50%.

### 3-9-7. :MEASUrement:REFLevel:PERCent:MID2



Description	Sets or queries the second mid reference level as a percentage.
Syntax	:MEASUrement:REFLevel:PERCent:MID2 {<NRf>   ?}
Parameter	<NRf> 0 - 100%
Return parameter	Returns the mid reference level of the second source.
Example	:MEASUrement:REFLevel:PERCent:MID2 50 Set the mid reference level to 50%.

### 3-9-8. :MEASure:FALL

→(Query)

Description	Returns the fall time measurement result.
Syntax	:MEASure:FALL{?}
Related Commands	:MEASure:SOURce<X>
Return parameter	<NR3> Indicates the source channel is not Chan Off activated.
Note	Before using this command, select the measurement channel. See the example below.
Example	:MEASure:SOURce1 CH1 :MEASure:FALL? Selects Channel 1 as the source, and then measures the fall time.

### 3-9-9. :MEASure:FOVShoot

→(Query)

Description	Returns the fall overshoot amplitude.
Syntax	:MEASure:FOVShoot{?}
Related Commands	:MEASure:SOURce<X>
Return parameter	<NR3> Returns the fall overshoot as a percentage Chan Off Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.
Example	:MEASure:SOURce1 CH1 :MEASure:FOVShoot? 1.27E+0 Selects Channel 1, and then measures the fall overshoot.

### 3-9-10. :MEASure:FPReShoot

→(Query)

Description	Returns fall preshoot amplitude.
Syntax	:MEASure:FPReShoot{?}
Related Commands	:MEASure:SOURce<X>
Returns	Returns the fall preshoot as <NR3>.
Return parameter	<NR3> Returns the fall preshoot as a percentage. Chan Off Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.
Example	:MEASure:SOURce1 CH1 :MEASure:FPReShoot? Selects Channel 1, and then measures the fall preshoot.

### 3-9-11. :MEASure:FREQuency

→Query

Description	Returns the frequency value.
Syntax	:MEASure:FREQuency{?}
Related Commands	:MEASure:SOURce<X>
Return parameter	<NR3> Returns the frequency in Hz. Chan Off Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.
Example	:MEASure:SOURce1 CH1 :MEASure:FREQuency? 1.0E+3 Selects Channel 1, and then measures the frequency.

### 3-9-12. :MEASure:NWIDth

→Query

Description	Returns the first negative pulse width timing.
Syntax	:MEASure:NWIDth{?}
Related Commands	:MEASure:SOURce<X>
Return parameter	<NR3> Returns the negative pulse width in seconds. Chan Off Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.
Example	:MEASure:SOURce1 CH1 :MEASure:NWIDth? 4.995E-04 Selects Channel 1, and then measures the negative pulse width.

### 3-9-13. :MEASure:PDUTy

→ **Query**

Description	Returns the positive duty cycle ratio as percentage.	
Syntax	:MEASure:PDUTy{?}	
Related commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the positive duty ratio.
	Chan Off	Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.	
Example	<pre>:MEASure:SOURce1 CH1 :MEASure:PDUTy? 5.000E+01</pre> Selects Channel 1, and then measures the positive duty cycle.	

### 3-9-14. :MEASure:PERiod

→ **Query**

Description	Returns the period.	
Syntax	:MEASure:PERiod{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the period.
	Chan Off	Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.	
Example	<pre>:MEASure:SOURce1 CH1 :MEASure:PERiod? 1.0E-3</pre> Selects Channel 1, and then measures the period.	

### 3-9-15. :MEASure:PWIDth

→Query

Description	Returns the first positive pulse width.
Syntax	:MEASure:PWIDth{?}
Related Commands	:MEASure:SOURce<X>
Return parameter	<NR3> Returns the positive pulse width. Chan Off Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.
Example	:MEASure:SOURce1 CH1 :MEASure:PWIDth? 5.0E-6 Selects Channel 1, and then measures the positive pulse width.

### 3-9-16. :MEASure:RISe

→Query

Description	Returns the first pulse rise time.
Syntax	:MEASure:RISe{?}
Related Commands	:MEASure:SOURce<X>
Return parameter	<NR3> Returns the rise time. Chan Off Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.
Example	:MEASure:SOURce1 CH1 :MEASure:RISe? 8.5E-6 Selects Channel 1, and then measures the rise time.

### 3-9-17. :MEASure:ROVShoot

→(Query)

Description	Returns the rising overshoot over the entire waveform in percentage.	
Syntax	:MEASure:ROVShoot{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the overshoot.
	Chan Off	Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.	
Example	<pre>:MEASure:SOURce1 CH1 :MEASure:ROVShoot? 5.00E+00 Selects Channel 1, and then measures the rise overshoot.</pre>	

### 3-9-18. :MEASure:RPReShoot

→(Query)

Description	Returns rising preshoot over the entire waveform in percentage.	
Syntax	:MEASure:RPReShoot{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the rising preshoot.
	Chan Off	Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.	
Example	<pre>:MEASure:SOURce1 CH1 :MEASure:RPReShoot? 2.13E-2 Selects Channel 1, and then measures the rise preshoot.</pre>	

### 3-9-19. :MEASure:PPULSE

→Query

Description	Returns the number of positive pulses.	
Syntax	:MEASure:PPULSE{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the number of positive pulses.
	Chan Off	Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.	
Example	<pre>:MEASure:SOURce1 CH1 :MEASure:PPULSE? 6.000E+00</pre> Selects Channel 1, and then measures the number of positive pulses.	

### 3-9-20. :MEASure:NPULSE

→Query

Description	Returns the number of negative pulses.	
Syntax	:MEASure:NPULSE{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the number of negative pulses.
	Chan Off	Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.	
Example	<pre>:MEASure:SOURce1 CH1 :MEASure:NPULSE? 4.000E+00</pre> Selects Channel 1, and then measures the number of negative pulses.	

### 3-9-21. :MEASure:PEDGE

→ **Query**

Description	Returns the number of positive edges.	
Syntax	:MEASure:PEDGE{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the number of positive edges.
	Chan Off	Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.	
Example	<pre>:MEASure:SOURce1 CH1 :MEASure:PEDGE? 1.100E+01</pre> Selects Channel 1, and then measures the number of positive edges.	

### 3-9-22. :MEASure:NEDGE

→ **Query**

Description	Returns the number of negative edges.	
Syntax	:MEASure:NEDGE{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the number of negative edges.
	Chan Off	Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.	
Example	<pre>:MEASure:SOURce1 CH1 :MEASure:NEDGE? 1.100E+01</pre> Selects Channel 1, and then measures the number of negative edges.	

### 3-9-23. :MEASure:AMPLitude

→(Query)


Description	Returns the amplitude difference between the Vhigh-Vlow.	
Syntax	:MEASure:AMPLitude{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the amplitude.
	Chan Off	Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.	
Example	:MEASure:SOURce1 CH1 :MEASure:AMPLitude? 3.76E-3 Selects Channel 1, and then measures the amplitude.	

### 3-9-24. :MEASure:MEAN

→(Query)


Description	Returns the mean voltage/current of one or more full periods.	
Syntax	:MEASure:MEAN{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the mean.
	Chan Off	Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.	
Example	:MEASure:SOURce1 CH1 :MEASure:MEAN? 1.82E-3 Selects Channel 1, and then measures the mean value.	

## 3-9-25. :MEASure:CMEan



Description	Returns the mean voltage/current of one full period.	
Syntax	:MEASure:CMEan{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the cyclic mean.
	Chan Off	Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.	
Example	:MEASure:SOURce1 CH1 :MEASure:CMEan? 9.480E-01 Selects Channel 1, and then measures the mean value of the first period.	

## 3-9-26. :MEASure:HIGH



Description	Returns the high voltage/current.	
Syntax	:MEASure:HIGH{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the high value.
	Chan Off	Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.	
Example	:MEASure:SOURce1 CH1 :MEASure:HIGH? 3.68E-3 Selects Channel 1, and then measures the high voltage/current.	

## 3-9-27. :MEASure:LOW



Description	Returns the low voltage/current.				
Syntax	:MEASure:LOW{?}				
Related Commands	:MEASure:SOURce<X>				
Return parameter	<table border="0"> <tr> <td>&lt;NR3&gt;</td> <td>Returns the global low value.</td> </tr> <tr> <td>Chan Off</td> <td>Indicates the source channel is not activated.</td> </tr> </table>	<NR3>	Returns the global low value.	Chan Off	Indicates the source channel is not activated.
<NR3>	Returns the global low value.				
Chan Off	Indicates the source channel is not activated.				
Note	Before using this command, select the measurement channel. See the example below.				
Example	<pre>:MEASure:SOURce1 CH1 :MEASure:LOW? 1.00E-0 Selects Channel 1, and then measures the low current/voltage.</pre>				

## 3-9-28. :MEASure:MAX



Description	Returns the maximum amplitude.				
Syntax	:MEASure:MAX{?}				
Related Commands	:MEASure:SOURce<X>				
Return parameter	<table border="0"> <tr> <td>&lt;NR3&gt;</td> <td>Returns the maximum amplitude.</td> </tr> <tr> <td>Chan Off</td> <td>Indicates the source channel is not activated.</td> </tr> </table>	<NR3>	Returns the maximum amplitude.	Chan Off	Indicates the source channel is not activated.
<NR3>	Returns the maximum amplitude.				
Chan Off	Indicates the source channel is not activated.				
Note	Before using this command, select the measurement channel. See the example below.				
Example	<pre>:MEASure:SOURce1 CH1 :MEASure:MAX? 1.90E-3 Selects Channel 1, and then measures the maximum amplitude.</pre>				

### 3-9-29. :MEASure:MIN

→ **Query**

Description	Returns the minimum amplitude.	
Syntax	:MEASure:MIN{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the minimum amplitude.
	Chan Off	Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.	
Example	<pre>:MEASure:SOURce1 CH1 :MEASure:MIN? -8.00E-3</pre> Selects Channel 1, and then measures the minimum amplitude.	

### 3-9-30. :MEASure:PK2PK

→ **Query**

Description	Returns the peak-to-peak amplitude (difference between maximum and minimum amplitude).	
Syntax	:MEASure:PK2Pk{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the voltage or current peak to peak measurement.
	Chan Off	Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.	
Example	<pre>:MEASure:SOURce1 CH1 :MEASure:PK2Pk? 2.04E-1</pre> Selects Channel 1, and then measures the peak-to-peak amplitude.	

### 3-9-31. :MEASure:RMS

→Query

Description	Returns the root-mean-square voltage/current of one or more full periods.	
Syntax	:MEASure:RMS{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the RMS value.
	Chan Off	Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.	
Example	:MEASure:SOURce1 CH1 :MEASure:RMS? 1.31E-3 Selects Channel 1, and then measures the RMS voltage/current.	

### 3-9-32. :MEASure:CRMS

→Query

Description	Returns the root-mean-square voltage/current of one full periods.	
Syntax	:MEASure:CRMS{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the CRMS value.
	Chan Off	Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.	
Example	:MEASure:SOURce1 CH1 :MEASure:CRMS? 1.31E-3 Selects Channel 1, and then measures the CRMS voltage/current.	

### 3-9-33. :MEASure:AREA

→(Query)

Description	Returns the voltage/current area over one or more full periods.	
Syntax	:MEASure:AREa{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the area value.
	Chan Off	Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.	
Example	:MEASure:SOURce1 CH1 :MEASure:AREA? 1.958E-03 Selects Channel 1, and then measures the area.	

### 3-9-34. :MEASure:CARA

→(Query)

Description	Returns the voltage/current area over one full period.	
Syntax	:MEASure:CARA{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the area value.
	Chan Off	Indicates the source channel is not activated.
Note	Before using this command, select the measurement channel. See the example below.	
Example	:MEASure:SOURce1 CH1 :MEASure:CARA? 1.958E-03 Selects Channel 1, and then measures the area.	

### 3-9-35. :MEASure:FRRDelay

→(Query)

Description	Returns the delay between the first rising edge of source1 and the first rising edge of source2.	
Syntax	:MEASure:FRRDelay{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the delay.
	Chan Off	Indicates the source channel is not activated.
Note	Select the two source channels before entering this command.	
Example	<pre>:MEASure:SOURce1 CH1 :MEASure:SOURce2 CH2 :MEASure:FRRDelay? -4.68E-6</pre> Select channel 1 and 2 as source1/2, and then measure FRR.	

### 3-9-36. :MEASure:FRFDelay

→(Query)

Description	Returns the delay between the first rising edge of source1 and the first falling edge of source2.	
Syntax	:MEASure:FRFDelay{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the delay.
	Chan Off	Indicates the source channel is not activated.
Note	Select the two source channels before entering this command.	
Example	<pre>:MEASure:SOURce1 CH1 :MEASure:SOURce2 CH2 :MEASure:FRFDelay? 3.43E-6</pre> Select channel 1 and 2 as source1/2, and then measure FRF.	

### 3-9-37. :MEASure:FFRDelay

→(Query)

Description	Returns the delay between the first falling edge of source1 and the first rising edge of source2.	
Syntax	:MEASure:FFRDelay {?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3> Chan Off	Returns the delay. Indicates the source channel is not activated.
Note	Select the two source channels before entering this command.	
Example	:MEASure:SOURce1 CH1 :MEASure:SOURce2 CH2 :MEASure:FFRDelay? -8.56E-6 Select channel 1 and 2 as delay source1/2, and then measure FFR.	

### 3-9-38. :MEASure:FFFDelay

→(Query)

Description	Returns the delay between the first falling edge of source1 and the first falling edge of source2.	
Syntax	:MEASure:FFFDelay{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3> Chan Off	Returns the delay. Indicates the source channel is not activated.
Note	Select the two source channels before entering this command.	
Example	:MEASure:SOURce1 CH1 :MEASure:SOURce2 CH2 :MEASure:FFFDelay? -8.89E-6 Select channel 1 and 2 as delay source1/2, and then measure FFF.	

### 3-9-39. :MEASure:LRRDelay

→Query

Description	Returns the delay between the first rising edge of source1 and the last rising edge of source2.	
Syntax	:MEASure:LRRDelay{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the delay.
	Chan Off	Indicates the source channel is not activated.
Note	Select the two source channels before entering this command.	
Example	<pre>:MEASure:SOURce1 CH1 :MEASure:SOURce2 CH2 :MEASure:LRRDelay? -8.89E-6</pre> Select channel 1 and 2 as delay source1/2, and then measure LRR.	

### 3-9-40. :MEASure:LRFDelay

→Query

Description	Returns the delay between the first rising edge of source1 and the last rising edge of source2.	
Syntax	:MEASure:LRFDelay{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the delay.
	Chan Off	Indicates the source channel is not activated.
Note	Select the two source channels before entering this command.	
Example	<pre>:MEASure:SOURce1 CH1 :MEASure:SOURce2 CH2 :MEASure:LRFDelay? -4.99E-6</pre> Select channel 1 and 2 as delay source1/2, and then measure LRF.	

### 3-9-41. :MEASure:LFRDelay

→Query

Description	Returns the delay between the first falling edge of source1 and the last rising edge of source2.	
Syntax	:MEASure:LFRDelay{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the delay.
	Chan Off	Indicates the source channel is not activated.
Note	Select the two source channels before entering this command.	
Example	<pre>:MEASure:SOURce1 CH1 :MEASure:SOURce2 CH2 :MEASure:LFRDelay? -9.99E-6</pre> Select channel 1 and 2 as delay source1/2, and then measure LFR.	

### 3-9-42. :MEASure:LFFDelay

→Query

Description	Returns the delay between the first falling edge of source1 and the last falling edge of source2.	
Syntax	:MEASure:LFFDelay{?}	
Related Commands	:MEASure:SOURce<X>	
Return parameter	<NR3>	Returns the delay.
	Chan Off	Indicates the source channel is not activated.
Note	Select the two source channels before entering this command.	
Example	<pre>:MEASure:SOURce1 CH1 :MEASure:SOURce2 CH2 :MEASure:LFFDelay? -9.99E-6</pre> Select channel 1 and 2 as delay source1/2, and then measure LFF.	

## 3-9-43. :MEASURE:PHASE


 Query

Description	Returns the phase between source 1 and source 2.	
Syntax	:MEASURE:PHASE{?}	
Related Commands	:MEASURE:SOURce<X>	
Return parameter	<NR3>	Returns the phase difference.
	Chan Off	Indicates the source channel is not activated.
Note	Select the two source channels before entering this command.	
Example	<pre>:MEASURE:SOURce1 CH1 :MEASURE:SOURce2 CH2 :MEASURE:PHASE? 4.50E+01</pre> <p>Select channel 1 and 2 as phase source1/2, and then measure the phase in degrees.</p>	

### 3-10. Measurement Commands


3-10-1. :MEASUREMENT:MEAS<X>:SOURCE<X>	69
3-10-2. :MEASUREMENT:MEAS<X>:TYPe	70
3-10-3. :MEASUREMENT:MEAS<X>:STATE	70
3-10-4. :MEASUREMENT:MEAS<X>:VALue	71
3-10-5. :MEASUREMENT:MEAS<X>:MAXimum	71
3-10-6. :MEASUREMENT:MEAS<X>:MEAN	72
3-10-7. :MEASUREMENT:MEAS<X>:MINimum	72
3-10-8. :MEASUREMENT:MEAS<X>:STDdev	73
3-10-9. :MEASUREMENT:STATISTICS:MODE	73
3-10-10. :MEASUREMENT:STATISTICS:WEighting	73
3-10-11. :MEASUREMENT:STATISTICS	74

#### 3-10-1. :MEASUREMENT:MEAS<X>:SOURCE<X>




Description	Sets or queries the measurement source for a selected automatic measurement. This is a statistics related command.	
Syntax	:MEASUREMENT:MEAS<X>:SOURCE<X> {CH1   CH2   CH3   CH4   MATH   ? }	
Related commands	:MEASUREMENT:MEAS<X>:TYPe	
Parameter	MEAS<X>	The automatic measurement number from 1 to 8.
	SOURCE<X>	SOURCE1: the source for all single channel measurements.
	SOURCE<X>	SOURCE2: the source for all delay or phase measurements.
	CH1 to CH4	Channel 1, 2, 3, 4
	MATH	Math source
Return parameter	CH1 to CH4	Channel 1, 2, 3, 4
	MATH	Math source
Example	:MEASUREMENT:MEAS1:SOURCE1 CH1 Returns the (first) source for measurement 1.	

### 3-10-2. :MEASUREMENT:MEAS<X>:TYPE



Description	Sets or queries the measurement type for a selected automatic measurement. This is a statistics related command.
Syntax	:MEASUREMENT:MEAS<X>:TYPE {PK2pk   MAXimum   MINimum   AMPlitude   HIGH   LOW   MEAN   CMEan   RMS   CRMs   AREa   CAREa   ROVShoot   FOVShoot   RPReShoot   FPReShoot   FREQuency   PERIod   RISe   FALL   PWlDth   NWlDth   PDUTy   PPULSE   NPULSE   PEDGE   NEDGE   FRRDelay   FRFDelay   FFRDelay   FFFDelay   LRRDelay   LRFDelay   LFRDelay   LFFDelay   PHAsE   ?}
Related commands	:MEASUREMENT:MEAS<X>:SOURCE<X>
Parameter	MEAS<X> The automatic measurement number from 1 to 8.
Return parameter	Returns the measurement type
Example	:MEASUREMENT:MEAS1:TYPE RMS Sets measurement 1 to RMS measurement.

### 3-10-3. :MEASUREMENT:MEAS<X>:STATE



Description	Sets or queries the state of a selected measurement. This is a statistics related command.
Syntax	:MEASUREMENT:MEAS<X>:STATE { ON   OFF   1   0   ? }
Related commands	:MEASUREMENT:MEAS<X>:SOURCE<X> :MEASUREMENT:MEAS<X>:TYPE
Parameter	MEAS<X> The automatic measurement number from 1 to 8. ON/1 Turn the measurement on. OFF/0 Turn the measurement off.
Return parameter	0 Measurement is off. 1 Measurement is on.
Example	:MEASUREMENT:MEAS1:STATE 1 Turns measurement 1 on.

### 3-10-4. :MEASUREMENT:MEAS<X>:VALUE

→(Query)

Description	Returns the measurement results for the selected measurement. This is a statistics related command.
Syntax	:MEASUREMENT:MEAS<X>:VALUE?
Related Commands	:MEASure:SOURce<X>
Return parameter	MEAS<X> The automatic measurement number from 1 to 8.
Note	The measurement source(s), measurement number, measurement type and measurement state must first be set before a measurement result can be returned.
Example	:MEASUREMENT:MEAS1:SOURce1 CH1 :MEASUREMENT:MEAS1:TYPE PK2PK :MEASUREMENT:MEAS1:STATE ON :MEASUREMENT:MEAS1:VALUE? 5.000E+0 Selects channel 1 as the source for measurement 1, sets measurement 1 to peak to peak measurement and then turns on the measurement. The result returns the peak to peak measurement.

### 3-10-5. :MEASUREMENT:MEAS<X>:MAXimum

→(Query)

Description	Returns the maximum measurement results for the selected measurement from the last time the statistics were reset. This is a statistics related command.
Syntax	:MEASUREMENT:MEAS<X>:MAXimum?
Related Commands	:MEASUREMENT:STATistics:MODe
Parameter	MEAS<X> The automatic measurement number from 1 to 8.
Example	:MEASUREMENT:MEAS3:SOURce1 CH1 :MEASUREMENT:MEAS3:TYPE PK2PK :MEASUREMENT:MEAS3:STATE ON :MEASUREMENT:STATIstics:MODe ON :MEASUREMENT:MEAS3:MAXimum? 2.800E-02 Returns the maximum measurement result for measurement number 3.

### 3-10-6. :MEASUREMENT:MEAS<X>:MEAN

→(Query)

Description	Returns the mean measurement results for the selected measurement from the last time the statistics were reset. This is a statistics related command.
Syntax	:MEASUREMENT:MEAS<X>:MEAN?
Related Commands	:MEASUREMENT:STATISTICS:MODE
Parameter	MEAS<X> The automatic measurement number from 1 to 8.
Example	:MEASUREMENT:MEAS3:SOURce1 CH1 :MEASUREMENT:MEAS3:TYPE PK2PK :MEASUREMENT:MEAS3:STATE ON :MEASUREMENT:STATISTICS:MODE ON :MEASUREMENT:MEAS3:MEAN? 2.090E-02 Returns the mean measurement result for measurement number 3.

### 3-10-7. :MEASUREMENT:MEAS<X>:MINIum

→(Query)

Description	Returns the minimum measurement results for the selected measurement from the last time the statistics were reset. This is a statistics related command.
Syntax	:MEASUREMENT:MEAS<X>:MINIum?
Related Commands	:MEASUREMENT:STATISTICS:MODE
Parameter	MEAS<X> The automatic measurement number from 1 to 8.
Example	:MEASUREMENT:MEAS3:SOURce1 CH1 :MEASUREMENT:MEAS3:TYPE PK2PK :MEASUREMENT:MEAS3:STATE ON :MEASUREMENT:STATISTICS:MODE ON :MEASUREMENT:MEAS3:MINIum? 1.600E-02 Returns the minimum measurement result for measurement number 3.

### 3-10-8. :MEASurement:MEAS<X>:STDdev

→(Query)

Description	Returns the standard deviation for the selected measurement from the last time the statistics were reset. This is a statistics related command.
Syntax	:MEASurement:MEAS<X>:STDdev?
Related Commands	:MEASurement:STATIstics:MODe
Parameter	MEAS<X> The automatic measurement number from 1 to 8.
Example	:MEASurement:MEAS3:SOURce1 CH1 :MEASurement:MEAS3:TYPe PK2PK :MEASurement:MEAS3:STATE ON :MEASurement:STATIstics:MODe ON :MEASurement:MEAS3:STDdev? 1.530E-03 Returns the standard deviation for measurement number 3.

### 3-10-9. :MEASurement:STATIstics:MODe

(Set) →  
→(Query)

Description	Puts the statics measurement results on the display or queries whether the statics are displayed.
Syntax	:MEASurement:STATIstics:MODe {OFF   ON   ?}
Related commands	:MEASurement:STATIstics
Parameter/ Return parameter	ON      Display the statics on the screen. OFF     Remove the statics from the screen
Example	:MEASurement:STATIstics:MODe ON Displays statics on the screen.

### 3-10-10. :MEASurement:STATIstics:WElghting

(Set) →  
→(Query)

Description	Sets and queries the number of samples used for the statics calculations.
Syntax	:MEASurement:STATIstics:WElghting { <NR1>   ? }
Parameter/ Return parameter	<NR1>    Number of samples (2~1000)
Example	:MEASurement:STATIstics:WElghting 5 Sets the number of samples to 5.

### 3-10-11. :MEASurement:STATIstics

 Set →


Description	Resets the statics calculations. This command will clear all the currently accumulated measurements.
Syntax	:MEASurement:STATIstics RESET

## 3-11. Reference Commands

3-11-1. :REF<X>:DISPlay .....	74
3-11-2. :REF<X>:TIMEbase:POSIon.....	74
3-11-3. :REF<X>:TIMEbase:SCALe .....	75
3-11-4. :REF<X>:OFFSet.....	75
3-11-5. :REF<x>:SCALe .....	75

### 3-11-1. :REF<X>:DISPlay


 Set →

 → Query

Description	Sets or queries a reference waveform to be shown on the display. A reference waveform must first be saved before this command can be used.						
Syntax	:REF<x>:DISPlay { OFF  ON  ? }						
Parameter	<table><tr><td>&lt;X&gt;</td><td>Reference waveform 1, 2, 3 ,4.</td></tr><tr><td>OFF</td><td>Turns the selected reference waveform off</td></tr><tr><td>ON</td><td>Turns the selected reference waveform on</td></tr></table>	<X>	Reference waveform 1, 2, 3 ,4.	OFF	Turns the selected reference waveform off	ON	Turns the selected reference waveform on
<X>	Reference waveform 1, 2, 3 ,4.						
OFF	Turns the selected reference waveform off						
ON	Turns the selected reference waveform on						
Return parameter	Returns the status of the selected reference waveform. (OFF, ON)						
Example	:REF1:DISPlay ON Turns on reference1 (REF 1) on the display.						


### 3-11-2. :REF<X>:TIMEbase:POSIon

 Set →

 → Query


Description	Sets or returns the selected reference waveform time base position.				
Syntax	:REF<X>:TIMEbase:POSIon { <NRf>   ? }				
Related commands	:REF<x>:DISPlay				
Parameter	<table><tr><td>&lt;X&gt;</td><td>Reference waveform 1, 2, 3 ,4.</td></tr><tr><td>&lt;NRf&gt;</td><td>Horizontal co-ordinates</td></tr></table>	<X>	Reference waveform 1, 2, 3 ,4.	<NRf>	Horizontal co-ordinates
<X>	Reference waveform 1, 2, 3 ,4.				
<NRf>	Horizontal co-ordinates				
Return parameter	<NR3> Returns the reference waveform position				
Example	:REF1:TIMEbase:POSIon -5.000E-5 Selects reference 1, and then sets the horizontal position to -50us.				

### 3-11-3. :REF<X>:TIMEbase:SCALE




Description	Sets or returns the selected reference waveform time base scale.				
Syntax	:REF<X>:TIMEbase:SCALE { <NRf>   ?}				
Related commands	:REF<X>:DISPLAY				
Parameter	<table border="0"> <tr> <td>&lt;X&gt;</td> <td>Reference waveform 1, 2, 3 ,4.</td> </tr> <tr> <td>&lt;NRf&gt;</td> <td>Horizontal scale</td> </tr> </table>	<X>	Reference waveform 1, 2, 3 ,4.	<NRf>	Horizontal scale
<X>	Reference waveform 1, 2, 3 ,4.				
<NRf>	Horizontal scale				
Return parameter	<NR3> Returns the reference waveform scale.				
Example	<pre>:REF1:TIMEbase:SCALE 5.00E-4 Selects reference 1, and then sets the horizontal scale to 500us/div.</pre>				

### 3-11-4. :REF<X>:OFFSet



Description	Sets or returns the selected reference waveform vertical position (offset).				
Syntax	:REF<X>:OFFSet { <NRf>   ?}				
Related commands	:REF<X>:DISPLAY				
Parameter	<table border="0"> <tr> <td>&lt;X&gt;</td> <td>Reference waveform 1, 2, 3 ,4.</td> </tr> <tr> <td>&lt;NRf&gt;</td> <td>Vertical offset</td> </tr> </table>	<X>	Reference waveform 1, 2, 3 ,4.	<NRf>	Vertical offset
<X>	Reference waveform 1, 2, 3 ,4.				
<NRf>	Vertical offset				
Return parameter	<NR3> Returns the reference waveform vertical position.				
Example	<pre>:REF1:OFFSet -5.000E-2 Selects reference 1, and then sets the vertical position to -50mV/mA.</pre>				

### 3-11-5. :REF<x>:SCALE



Description	Sets or returns the selected reference waveform vertical scale.				
Syntax	:REF<x>:SCALE { <NRf>   ?}				
Related commands	:REF<x>:DISPLAY				
Parameter	<table border="0"> <tr> <td>&lt;X&gt;</td> <td>Reference waveform 1, 2, 3 ,4.</td> </tr> <tr> <td>&lt;NRf&gt;</td> <td>Vertical scale</td> </tr> </table>	<X>	Reference waveform 1, 2, 3 ,4.	<NRf>	Vertical scale
<X>	Reference waveform 1, 2, 3 ,4.				
<NRf>	Vertical scale				
Return parameter	<NR3> Returns the reference waveform vertical scale.				
Example	<pre>:REF1:SCALE 5.000E-2 Selects reference 1, and then sets the vertical scale to 50mV mA/div.</pre>				

### **3-12. Run Command**

---

3-12-1. :RUN .....	76
3-12-2. :STOP .....	76
3-12-3. :SINGLe .....	76
3-12-4. :FORCe .....	76


---

#### **3-12-1. :RUN**

 Set →


Description	The run command allows the oscilloscope to continuously make acquisitions (equivalent to pressing the Run key on the front panel).
Syntax	:RUN

#### **3-12-2. :STOP**

 Set →


Description	The stop command stops the oscilloscope making further acquisitions (equivalent to pressing the Stop key on the front panel).
Syntax	:STOP

#### **3-12-3. :SINGLe**

 Set →

Description	The single command allows the oscilloscope to capture a single acquisition when trigger conditions have been fulfilled (equivalent to pressing the Single key on the front panel).
Syntax	:SINGLe

#### **3-12-4. :FORCe**


 Set →

Description	The Force command forces an acquisition (equivalent to pressing the Force-Trig key on the front panel).
Syntax	:FORCe

### 3-13. Timebase Commands


3-13-1. :TIMEbase:EXPand .....	77
3-13-2. :TIMEbase:POSIon .....	77
3-13-3. :TIMEbase:SCALe .....	77
3-13-4. :TIMEbase:MODE .....	78
3-13-5. :TIMEbase:WINDOW:POSIon .....	78
3-13-6. :TIMEbase:WINDOW:SCALe .....	78

#### 3-13-1. :TIMEbase:EXPand




Description	Sets or queries the horizontal expansion mode.
Syntax	:TIMEbase:EXPand {CENTer TRIGger ?}
Parameter/	CENTer      Expand from the center of the display.
Return parameter	TRIGger      Expand from the trigger point.
Example	:TIMEbase:EXPand TRIGger Sets the expansion point to the trigger point.

#### 3-13-2. :TIMEbase:POSIon




Description	Sets or queries the horizontal position.
Syntax	:TIMEbase:POSIon {<NRf>   ?}
Parameter	<NRf>      Horizontal position
Return parameter	<NR3>      Returns the horizontal position.
Example	:TIMEbase:POSIon 5.00E-4 Sets the horizontal position as 500us.

#### 3-13-3. :TIMEbase:SCALe




Description	Sets or queries the horizontal scale.
Syntax	:TIMEbase:SCALe {<NRf>   ?}
Parameter	<NRf>      Horizontal scale
Return parameter	<NR3>      Returns the horizontal scale.
Example	:TIMEbase:SCALe 5.00E-2 Sets the horizontal scale to 50ms/div.

### 3-13-4. :TIMEbase:MODE




Description	Sets or queries the time base mode. The time base mode determines the display view window on the scope.	
Syntax	:TIMEbase:MODE {MAIN   WINDOW   XY   ?}	
Parameter	MAIN	Sets the time base mode to the main screen.
	WINDOW	Sets the time base mode to the zoom window.
	XY	Sets the time base mode to the XY display.
Return parameter	Returns the time base mode (MAIN, WINDOW, XY)	
Example	:TIMEbase:MODE MAIN Sets the time base mode to the main mode.	

### 3-13-5. :TIMEbase:WINDOW:POSITION



Description	Sets or queries the zoom horizontal position.	
Syntax	:TIMEbase:WINDOW:POSITION {<NRf>   ?}	
Related commands	:TIMEbase:MODe	
Parameter	<NRf>	Horizontal position for zoom window
Return parameter	<NR3>	Returns the zoom horizontal position.
Example	:TIMEbase:WINDOW:POSITION 2.0E-3 Sets the zoom horizontal position as 20ms.	

### 3-13-6. :TIMEbase:WINDOW:SCALE



Description	Sets or queries the zoom horizontal scale.	
Note	If the oscilloscope is under "ZOOM" mode, the main timebase function will be disabled and cannot be modified.	
Syntax	:TIMEbase:WINDOW:SCALe {<NRf>   ?}	
Related commands	:TIMEbase:MODe	
Parameter	<NRf>	Zoom horizontal scale. The range will depend on the time base.
Return parameter	<NR3>	Returns the zoom horizontal scale.
Example	:TIMEbase:WINDOW:SCALe 2.0E-3 Sets the zoom horizontal scale to 2ms.	

### **3-14. Trigger Commands**

---

3-14-1. :TRIGger:FREQuency .....	80
3-14-2. :TRIGger:TYPE .....	80
3-14-3. :TRIGger:SOURce .....	81
3-14-4. :TRIGger:COUPLE .....	81
3-14-5. :TRIGger:NREJ .....	81
3-14-6. :TRIGger:MODE .....	82
3-14-7. :TRIGger:HOLDoff .....	82
3-14-8. :TRIGger:LEVEL .....	82
3-14-9. :TRIGger:HLEVel .....	83
3-14-10. :TRIGger:LLEVel .....	83
3-14-11. :TRIGger:EDGE:SLOP .....	84
3-14-12. :TRIGger:DELay:SLOP .....	84
3-14-13. :TRIGger:DELay:TYPE .....	84
3-14-14. :TRIGger:DELay:TIME .....	85
3-14-15. :TRIGger:DELay:EVENT .....	85
3-14-16. :TRIGger:DELay:LEVEL .....	85
3-14-17. :TRIGger:PULSEWidth:POLarity .....	86
3-14-18. :TRIGger:RUNT:POLarity .....	86
3-14-19. :TRIGger:RUNT:WHEn .....	86
3-14-20. :TRIGger:RUNT:TIME .....	87
3-14-21. :TRIGger:RISEFall:SLOP .....	87
3-14-22. :TRIGger:RISEFall:WHEn .....	87
3-14-23. :TRIGger:RISEFall:TIME .....	88
3-14-24. :TRIGger:VIDeo:TYPE .....	88
3-14-25. :TRIGger:VIDeo:FIELD .....	89
3-14-26. :TRIGger:VIDeo:LINE .....	89
3-14-27. :TRIGger:VIDeo:POLarity .....	89
3-14-28. :TRIGger:PULSe:WHEn .....	90
3-14-29. :TRIGger:PULSe:TIME .....	90
3-14-30. :TRIGger:TIMEOut:WHEn .....	90
3-14-31. :TRIGger:TIMEOut:TIMER .....	91
3-14-32. :TRIGger:ALTernate .....	91
3-14-33. :TRIGger:STATe .....	91
3-14-34. :TRIGger:EXTERnal:PROBe:TYPE .....	92
3-14-35. :TRIGger:EXTERnal:PROBe:RATio .....	92
3-14-36. :TRIGger:BUS:TYPE .....	92
3-14-37. :TRIGger:BUS:THreshold:CH<x> .....	93
3-14-38. :TRIGger:BUS:B1:I2C:CONDITION .....	93
3-14-39. :TRIGger:BUS:B1:I2C:ADDRess:MODE .....	94
3-14-40. :TRIGger:BUS:B1:I2C:ADDRess:TYPE .....	94
3-14-41. :TRIGger:BUS:B1:I2C:ADDRess:VALue .....	95
3-14-42. :TRIGger:BUS:B1:I2C:ADDRess:DIRECTION .....	95
3-14-43. :TRIGger:BUS:B1:I2C:DATA:SIZE .....	96
3-14-44. :TRIGger:BUS:B1:I2C:DATA:VALUe .....	96
3-14-45. :TRIGger:BUS:B1:UART:CONDITION .....	97
3-14-46. :TRIGger:BUS:B1:UART:RX:DATA:SIZE .....	97
3-14-47. :TRIGger:BUS:B1:UART:RX:DATA:VALUe .....	98
3-14-48. :TRIGger:BUS:B1:UART:TX:DATA:SIZE .....	98
3-14-49. :TRIGger:BUS:B1:UART:TX:DATA:VALUe .....	99
3-14-50. :TRIGger:BUS:B1:SPI:CONDITION .....	99
3-14-51. :TRIGger:BUS:B1:SPI:DATA:SIZE .....	100

3-14-52. :TRIGger:BUS:B1:SPI:DATa:MISO:VALue.....	100
3-14-53. :TRIGger:BUS:B1:SPI:DATa:MOSt:VALue.....	101
3-14-54. :TRIGger:BUS:B1:CAN:CONDition .....	102
3-14-55. :TRIGger:BUS:B1:CAN:FRAMEtpe .....	102
3-14-56. :TRIGger:BUS:B1:CAN:IDentifier:MODE .....	103
3-14-57. :TRIGger:BUS:B1:CAN:IDentifier:VALue.....	103
3-14-58. :TRIGger:BUS:B1:CAN:IDentifier:DIRection.....	104
3-14-59. :TRIGger:BUS:B1:CAN:DATa:QUALifier.....	104
3-14-60. :TRIGger:BUS:B1:CAN:DATa:SIZE.....	105
3-14-61. :TRIGger:BUS:B1:CAN:DATa:VALue.....	105
3-14-62. :TRIGger:BUS:B1:LIN:CONDition .....	106
3-14-63. :TRIGger:BUS:B1:LIN:DATa:QUALifier.....	107
3-14-64. :TRIGger:BUS:B1:LIN:DATa:SIZE.....	108
3-14-65. :TRIGger:BUS:B1:LIN:DATa:VALue.....	108
3-14-66. :TRIGger:BUS:B1:LIN:ERRTYPE.....	109
3-14-67. :TRIGger:BUS:B1:LIN:IDentifier:VALue.....	109

---

### 3-14-1. :TRIGger:FREQuency

→(Query)

Description	Queries the trigger frequency.
Syntax	:TRIGger:FREQuency{?}
Return parameter	<NR3> Returns the trigger frequency.
Example	:TRIGger:FREQuency? 1.032E+3 Returns the trigger frequency.


### 3-14-2. :TRIGger:TYPe

(Set) →

→(Query)


Description	Sets or queries the trigger type.	
Syntax	:TRIGger:TYPe {EDGE   DELay   PULSEWidth   VIDeo   RUNT   RISEFall   BUS   TIMEOut   ? }	
Parameter	EDGE	Edge trigger
	DELay	Delay trigger
	PULSEWidth	Pulse width trigger
	VIDeo	Video trigger
	RUNT	Runt trigger
	RISEFall	Rise and fall trigger
	BUS	Bus trigger
	TIMEOut	Timeout trigger
Return parameter	Returns the trigger type.	
Example	:TRIGger:TYPe EDGE Sets the trigger type to edge.	

### 3-14-3. :TRIGger:SOURce




Description	Sets or queries the trigger source.	
Syntax	:TRIGger:SOURce { CH1   CH2   CH3   CH4   EXT   LINe   ? }	
Parameter	CH1 to CH4	Channel 1 to channel 4
	EXT	External source
	LINe	AC Line
Return parameter	Returns the trigger source.	
Example	:TRIGger:SOURce CH1 Sets the trigger source to channel 1.	

### 3-14-4. :TRIGger:COUPle




Description	Sets or queries the trigger coupling.	
Note	Applicable for edge and delay triggers only.	
Syntax	:TRIGger:COUPle {AC   DC   ?}	
Parameter	AC	AC Mode
	DC	DC Mode
	HF	High frequency rejection
	LF	Low frequency rejection
Return parameter	Returns the trigger coupling.	
Example	:TRIGger:COUPle AC Sets the trigger coupling to AC.	

### 3-14-5. :TRIGger:NREJ




Description	Sets or queries noise rejection status.	
Syntax	:TRIGger:NREJ {OFF ON ?}	
Parameter	OFF	Turns noise rejection off
	ON	Turns noise rejection on
Return parameter	Returns the noise rejection status (ON, OFF).	
Example	:TRIGger:NREJ ON Turns noise rejection on.	

### 3-14-6. :TRIGger:MODE




Description	Sets or queries the trigger mode.
Syntax	:TRIGger:MODE {AUTo   NORMAL   ?}
Parameter	AUTo      Auto trigger (Untriggered roll) NORMAL    Normal trigger
Return parameter	Returns the trigger mode.
Example	:TRIGger:MODE NORMAL Sets the trigger mode to normal.

### 3-14-7. :TRIGger:HOLDOff




Description	Sets or queries the holdoff time.
Syntax	:TRIGger:HOLDOff {<NRf>   ?}
Parameter	<NRf>      Holdoff time
Return parameter	<NR3>      Returns the trigger holdoff time.
Example	:TRIGger:HOLDOff 1.00E-8 Sets the trigger holdoff time to 10ns.

### 3-14-8. :TRIGger:LEVel




Description	Sets or queries the level.
Syntax	:TRIGger:LEVel {TTL   ECL   SETTO50   <NRf>   ?}
Related commands	:TRIGger:TYPe
Parameter	<NRf>      Trigger level value TTL           Sets the trigger level to TTL. ECL           Sets the trigger level to ECL. SETTO50       Sets the trigger level to the User level (50% by default).
Return parameter	<NR3>      Returns the trigger level.
Example1	:TRIGger:LEVel TTL Sets the trigger to TTL.
Example2	:TRIGger:LEVel 3.30E-1 Sets the trigger level to 330mV/mA.

### 3-14-9. :TRIGger:HLEVel




Description	Sets or queries the high trigger level.	
Note	Applicable for Rise and Fall/Pulse Runt triggers.	
Syntax	:TRIGger:HLEVel {TTL   ECL}   <NRf>   ?	
Related commands	:TRIGger:TYPe	
Parameter	<NRf>	High level value. TTL Sets the high trigger level to TTL. ECL Sets the high trigger level to ECL.
Return parameter	<NR3>	Returns the trigger high level.
Example1	:TRIGger:HLEVel TTL Sets the trigger high level to TTL.	
Example2	:TRIGger:HLEVel 3.30E-1 Sets the trigger high level to 330mV/mA.	

### 3-14-10. :TRIGger:LLEVel




Description	Sets or queries the low trigger level.	
Note	Applicable for Rise and Fall/Pulse Runt triggers.	
Syntax	:TRIGger:LLEVel {TTL   ECL}   <NRf>   ?	
Related commands	:TRIGger:TYPe	
Parameter	<NRf>	Low level value. TTL Sets the low trigger level to TTL. ECL Sets the log trigger level to ECL.
Return parameter	<NR3>	Returns the trigger low level.
Example1	:TRIGger:LLEVel TTL Sets the trigger low level to TTL.	
Example2	:TRIGger:LLEVel -3.30E-3 Sets the trigger low level to -330mV/mA.	

### 3-14-11. :TRIGger:EDGe:SLOP




Description	Sets or queries the trigger slope.	
Syntax	:TRIGger:EDGe:SLOP {RISe   FALL   EITher   ? }	
Related commands	:TRIGger:TYPE	
Parameter	RISe	Rising slope
	FALL	Falling slope
	EITher	Either rising or falling slope
Return parameter	Returns the trigger slope.	
Example	:TRIGger:EDGe:SLOP FALL Sets the trigger slope to falling.	

### 3-14-12. :TRIGger:DELay:SLOP




Description	Sets or queries the trigger slope for the delay trigger.	
Syntax	:TRIGger:DELay:SLOP {RISe   FALL   EITher   ? }	
Related commands	:TRIGger:TYPE	
Parameter	RISe	Rising slope
	FALL	Falling slope
	EITher	Either rising or falling slope
Return parameter	Returns the trigger slope.	
Example	:TRIGger:DELay:SLOP FALL Sets the trigger slope to falling.	

### 3-14-13. :TRIGger:DELay:TYPe




Description	Sets or queries the trigger delay type.	
Syntax	:TRIGger:DELay:TYPe {TIME   EVENT   ? }	
Related commands	:TRIGger:TYPE	
Parameter	TIME	Sets the delay type to time.
	EVENT	Sets the delay type to event.
Return parameter	Returns the trigger delay type.	
Example	:TRIGger:DELay:TYPe TIME Sets the delay type to time delay.	

### 3-14-14. :TRIGger:DELay:TIME




Description	Sets or queries the delay time value.
Syntax	:TRIGger:DELay:TIME {<NRf>   ?}
Related commands	:TRIGger:DELay:TYPE
Parameter	<NRf> Delay time (1.00E-8~1.00E+1)
Return parameter	<NR3> Returns the delay time.
Example	:TRIGger:DELay:TIME 1.00E-6 Sets the delay time to 1us.

### 3-14-15. :TRIGger:DELay:EVENT




Description	Sets or queries the number of events for the event delay trigger.
Syntax	:TRIGger:DELay:EVENT {<NR1>   ?}
Related commands	:TRIGger:DELay:TYPE
Parameter	<NR1> 1~65535 events
Return parameter	<NR1> Returns the number of events.
Example	:TRIGger:DELay:EVENT 2 Sets the number of events to 2.

### 3-14-16. :TRIGger:DELay:LEVel




Description	Sets or queries the trigger delay level.
Syntax	:TRIGger:DELay:LEVel {<NRf>   ?}
Parameter	<NRf> Delay trigger level
Return parameter	<NR3> Returns the delay trigger.
Example	:TRIGger:DELay:LEVel 5.00E-3 Sets the delay trigger to 5mV/mA.

### 3-14-17. :TRIGger:PULSEWidth:POLarity




Description	Sets or queries the pulse width trigger polarity.	
Syntax	:TRIGger:PULSEWidth:POLarity { POSitive   NEGative   ? }	
Related commands	:TRIGger:TYPe	
Parameter	POSitive	Positive polarity
	NEGative	Negative polarity
Return parameter	Returns the pulse width polarity.	
Example	:TRIGger:PULSEWidth:POLarity POSitive Sets the pulse width polarity to positive.	

### 3-14-18. :TRIGger:RUNT:POLarity




Description	Sets or queries the Pulse Runt trigger polarity.	
Syntax	:TRIGger:RUNT:POLarity { POSitive   NEGative   EITHER   ? }	
Related commands	:TRIGger:TYPe	
Parameter	POSitive	Positive polarity
	NEGative	Negative polarity
	EITHER	Positive or negative polarity
Return parameter	Returns the pulse runt trigger polarity.	
Example	:TRIGger:RUNT:POLarity POSitive Sets the Pulse Runt trigger polarity to positive.	

### 3-14-19. :TRIGger:RUNT:WHEn




Description	Sets or queries the Pulse Runt trigger conditions.	
Syntax	:TRIGger:RUNT:WHEn { THAN   LESSthan   EQUAL   UNEQual   ? }	
Related commands	:TRIGger:TYPe :TRIGger:RUNT:TIME	
Parameter	THAN	>
	LESSthan	<
	Equal	=
	UNEQual	≠
Return parameter	Returns the pulse runt trigger condition.	
Example	:TRIGger:RUNT:WHEn UNEQual Sets the Pulse Runt trigger condition to unequal (≠).	

### 3-14-20. :TRIGger:RUNT:TIME




Description	Sets or queries the Pulse Runt trigger time.	
Syntax	:TRIGger:RUNT:TIME {<NRf>   ? }	
Related commands	:TRIGger:TYPE :TRIGger:RUNT:WHEn	
Parameter	<NRf>	Pulse runt time (4nS to 10S)
Return Parameter	<NR3>	Returns the runt time in seconds.
Example	:TRIGger:RUNT:TIME 4.00E-5 Sets the runt time to 40.0uS.	

### 3-14-21. :TRIGger:RISEFall:SLOP




Description	Sets or queries the Rise & Fall slope.	
Syntax	:TRIGger:RISEFall:SLOP {RISe   FALL   EITher   ? }	
Parameter	RISe	Rising slope
	FALL	Falling slope
	EITher	Either rising or falling slope
Return parameter	Returns the rise & fall slope.	
Example	:TRIGger:RISEFall:SLOP RISe Sets the Rise & Fall slope to rising.	

### 3-14-22. :TRIGger:RISEFall:WHEn




Description	Sets or queries the rise/fall trigger conditions	
Syntax	:TRIGger:RISEFall:WHEn { THAN   LESSthan   EQUAL   UNEQual   ? }	
Related commands	:TRIGger:TYPE :TRIGger:RISEFall:TIME	
Parameter	THAN	>
	LESSthan	<
	Equal	=
	UNEQual	≠
Return parameter	Returns the rise/fall trigger condition.	
Example	:TRIGger:RISEFall:WHEn UNEQual Sets the Rise and Fall trigger condition to unequal (#).	

### 3-14-23. :TRIGger:RISEFall:TIME




Description	Sets or queries the Rise and Fall time.
Syntax	:TRIGger:RISEFall:TIME {<NRf>   ? }
Related commands	:TRIGger:TYPE :TRIGger:RISEFall:WHEn
Parameter	<NRf> Rise and Fall time (4nS to 10S)
Return Parameter	<NR3> Returns the rise and fall time in seconds.
Example	:TRIGger:RISEFall:TIME 4.00E-5 Sets the trigger rise & fall to 40.0us.

### 3-14-24. :TRIGger:VIDeo:TYPE




Description	Sets or queries the video trigger type.
Syntax	:TRIGger:VIDeo:TYPE {NTSC   PAL   SECam   EDTV480P   EDTV576P   HDTV720P   HDTV1080I   HDTV1080P   ? }
Related commands	:TRIGger:TYPE
Parameter	NTSC NTSC PAL PAL SECam SECAM EDTV480P Extra definition TV 480P EDTV576P Extra definition TV 576P HDTV720P High definition TV 720P HDTV1080I High definition TV 1080i HDTV1080P High definition TV 1080P
Return parameter	Returns the video trigger type.
Example	:TRIGger:VIDeo:TYPE NTSC Sets the video trigger to NTSC.

### 3-14-25. :TRIGger:VIDeo:FIELd




Description	Sets or queries the video trigger field.	
Syntax	:TRIGger:VIDeo:FIELd { FIELD1   FIELD2   ALLFields   ALLLines   ? }	
Related commands	:TRIGger:TYPE	
Parameter	FIELD1	Trigger on field 1
	FIELD2	Trigger on field 2
	ALLFields	Trigger on all fields
	ALLLines	Trigger on all lines
Return parameter	Returns the video trigger field.	
Example	:TRIGger:VIDeo:FIELd ALLFields Sets the video trigger to trigger on all fields.	

### 3-14-26. :TRIGger:VIDeo:LINE




Description	Sets or queries the video trigger line.	
Syntax	:TRIGger:VIDeo:LINE { <NR1>   ? }	
Related commands	:TRIGger:TYPE	
Parameter	<NR1>	Video line
Return parameter	<NR3>	Returns the video trigger line.
Example	:TRIGger:VIDeo:LINE 1 Sets the video trigger to line 1.	

### 3-14-27. :TRIGger:VIDeo:POLarity



Description	Sets or queries the video trigger polarity.	
Syntax	:TRIGger:VIDeo:POLarity { POSitive   NEGative   ? }	
Related commands	:TRIGger:TYPE	
Parameter	POSitive	Positive polarity
	NEGative	Negative polarity
Return parameter	Returns the video trigger polarity.	
Example	:TRIGger:VIDeo:POLarity POSitive Sets the video trigger polarity to positive.	

### 3-14-28. :TRIGger:PULSe:WHEn





---

Description	Sets or queries the pulse width trigger conditions.
Syntax	:TRIGger:PULSe:WHEn { THAN   LESSthan   EQual   UNEQual   ? }
Related commands	:TRIGger:TYPe :TRIGger:PULSe:TIME
Parameter	THAN > LESSthan < EQual = UNEQual ≠
Return parameter	Returns the pulse width trigger conditions.
Example	:TRIGger:PULSe:WHEn UNEQual Sets the trigger pulse width conditions to not equal to (#).

---

### 3-14-29. :TRIGger:PULSe:TIME





---

Description	Sets or queries the pulse width time.
Syntax	:TRIGger:PULSe:TIME {<NRf>   ?}
Related commands	:TRIGger:TYPe :TRIGger:PULSe:WHEn
Parameter	<NRf> Pulse width time (4ns~10s)
Return parameter	<NR3> Returns the pulse width time in seconds.
Example	:TRIGger:PULSe:TIME 4.00E-5 Sets the trigger pulse width to 40.0us.

---

### 3-14-30. :TRIGger:TIMEOut:WHEn





---

Description	Sets or queries the timeout trigger condition.
Syntax	:TRIGger:TIMEOut:WHEn {HIGH LOW EITher ?}
Related commands	:TRIGger:TIMEOut:TIMER
Parameter	HIGH Signal is high. LOW Signal is low. EITher Signal is high or low.
Return parameter	Returns the timeout condition (HIGH, LOW, EITHER).
Example1	:TRIGger:TIMEOut:WHEn LOW Sets the timeout condition to low.


---

### 3-14-31. :TRIGger:TIMEOut:TIMER




Description	Sets or returns timeout trigger time.
Syntax	:TRIGger:TIMEOut:TIMER {<NRf>   ? }
Related commands	:TRIGger:TIMEOut:WHEn
Parameter	<NRf>      Timeout time. (4nS to 10S).
Return parameter	Returns the timeout time as <NR3>.
Example	:TRIGger:TIMEOut:TIMER? 8.960e-05

### 3-14-32. :TRIGger:ALTerNate




Description	Sets alternating between source triggers on or off or queries its state.
Syntax	:TRIGger:ALTerNate {OFF   ON   ?}
Parameter	OFF      Alternate off ON      Alternate on
Return parameter	Returns the Alternate trigger status (ON, OFF).
Example	:TRIGger:ALTerNate ON Turns on alternating between source triggers.

### 3-14-33. :TRIGger:STATe




Description	Returns the current state of the triggering system.
Syntax	:TRIGger:STATe?
Return parameter	*ARMED      Indicates that the oscilloscope is acquiring pretrigger information. *AUTO      Indicates that the oscilloscope is in the automatic mode and acquires data even in the absence of a trigger. *READY      Indicates that all pretrigger information has been acquired and that the oscilloscope is ready to accept a trigger. *SAVE      Indicates that the oscilloscope is in save mode and is not acquiring data. *TRIGGE R      Indicates that the oscilloscope triggered and is acquiring the post trigger information.
Example	:TRIGger:STATe? AUTO The trigger is in auto mode.

### 3-14-34. :TRIGger:EXTERnal:PROBe:TYPE



Description	Sets or queries the external probe type.	
Syntax	:TRIGger:EXTERnal:PROBe:TYPE { VOLtage   CURRent   ? }	
Related commands	:TRIGger:EXTERnal:PROBe:RATio	
Parameter	VOLtage	Voltage
	CURRent	Current
Return parameter	Returns the probe type.	
Example	:TRIGger:EXTERnal:PROBe:TYPE? CURRENT	

### 3-14-35. :TRIGger:EXTERnal:PROBe:RATio




Description	Sets or queries the external probe ratio (attenuation).	
Syntax	:TRIGger:EXTERnal:PROBe:RATio { <NRf>   ? }	
Related commands	:TRIGger:EXTERnal:PROBe:TYPE	
Parameter	<NRf>	External probe attenuation factor.
Return parameter	<NR3>	Returns the probe attenuation factor.
Example	:TRIGger:EXTERnal:PROBe:RATio? 5.00000e+01	

### 3-14-36. :TRIGger:BUS:TYPE




Description	Returns the current bus type.	
Syntax	:TRIGger:BUS:TYPE?	
Return parameter	I2C	I2C mode
	SPI	SPI mode
	UART	UART mode
	PARALLEL	Parallel mode
Example	:TRIGger:BUS:TYPE? UART	

### 3-14-37. :TRIGger:BUS:THreshold:CH<x>




Description	Sets or queries the threshold level for the selected channel.
Syntax	:TRIGger:BUS:THreshold:CH<X> {<NR3>   ?} <X> CH1 ~ CH4 <NR3> Threshold level
Return Parameter	<NR3> Returns the threshold level
Example	:TRIGger:BUS:THreshold:CH1 1 Sets the CH1 threshold to 1V.

### 3-14-38. :TRIGger:BUS:B1:I2C:CONDition




Description	Sets or queries the I <sup>2</sup> C trigger conditions.														
Syntax	:TRIGger:BUS:B1:I2C:CONDition {START   STOP   REPEATstart   ACKMISS   ADDRess   DATA   ADDRANDDATA   ? }														
Parameter	<table border="0"> <tr> <td>STARt</td> <td>Set Start as the I<sup>2</sup>C trigger condition.</td> </tr> <tr> <td>STOP</td> <td>Set Stop as the I<sup>2</sup>C trigger condition.</td> </tr> <tr> <td>REPEATstart</td> <td>Set Repeat of Start as the I<sup>2</sup>C trigger condition.</td> </tr> <tr> <td>ACKMISS</td> <td>Set Missing Acknowledgement as the I<sup>2</sup>C trigger condition.</td> </tr> <tr> <td>ADDRess</td> <td>Set Address as the I<sup>2</sup>C trigger condition.</td> </tr> <tr> <td>DATA</td> <td>Set Data as the I<sup>2</sup>C trigger condition.</td> </tr> <tr> <td>ADDRANDDATA</td> <td>Set Address and Data as the I<sup>2</sup>C trigger condition.</td> </tr> </table>	STARt	Set Start as the I <sup>2</sup> C trigger condition.	STOP	Set Stop as the I <sup>2</sup> C trigger condition.	REPEATstart	Set Repeat of Start as the I <sup>2</sup> C trigger condition.	ACKMISS	Set Missing Acknowledgement as the I <sup>2</sup> C trigger condition.	ADDRess	Set Address as the I <sup>2</sup> C trigger condition.	DATA	Set Data as the I <sup>2</sup> C trigger condition.	ADDRANDDATA	Set Address and Data as the I <sup>2</sup> C trigger condition.
STARt	Set Start as the I <sup>2</sup> C trigger condition.														
STOP	Set Stop as the I <sup>2</sup> C trigger condition.														
REPEATstart	Set Repeat of Start as the I <sup>2</sup> C trigger condition.														
ACKMISS	Set Missing Acknowledgement as the I <sup>2</sup> C trigger condition.														
ADDRess	Set Address as the I <sup>2</sup> C trigger condition.														
DATA	Set Data as the I <sup>2</sup> C trigger condition.														
ADDRANDDATA	Set Address and Data as the I <sup>2</sup> C trigger condition.														
Return parameter	Returns the I <sup>2</sup> C bus trigger condition.														
Example	:TRIGger:BUS:B1:I2C:CONDition ADDRess Set Address as the I <sup>2</sup> C trigger condition.														

## 3-14-39. :TRIGger:BUS:B1:I2C:ADDRess:MODE




Description	Sets or queries the I <sup>2</sup> C addressing mode (7 or 10 bits).	
Syntax	:TRIGger:BUS:B1:I2C:ADDRess:MODE {ADDR7   ADDR10   ?}	
Related commands	:TRIGger:BUS:B1:I2C:CONDition	
Parameter	ADDR7	7 bit addressing
	ADDR10	10 bit addressing
Return Parameter	0	7 bit addressing
	1	10 bit addressing
Example	:TRIGger:BUS:B1:I2C:ADDRess:MODE? 0 The addressing mode is current set to 7 bits.	

## 3-14-40. :TRIGger:BUS:B1:I2C:ADDRess:TYPE




Description	Sets the I <sup>2</sup> C bus address type, or queries what the setting is.	
Syntax	:TRIGger:BUS:B1:I2C:ADDRess:TYPE {GENeralcall   STARtbyte   HSmode   EEPROM   CBUS   ?}	
Related commands	:TRIGger:BUS:B1:I2C:CONDition	
Parameter	GENeralcal	Set a general call address (0000 000 0).
	I	
	STARtbyte	Set a start byte address. (0000 000 1)
	HSmode	Set a high-speed mode address. (0000 1xx x)
	EEPROM	Set an EEPROM address. (1010 xxx x)
	CBUS	Set a CBUS address. (0000 001 x)
Return Parameter	Returns the address type	
Example	:TRIGger:BUS:B1:I2C:ADDRess:TYPE? CBUS	

### 3-14-41. :TRIGger:BUS:B1:I2C:ADDRess:VALue




Description	Sets or queries the I <sup>2</sup> C bus address value when the I <sup>2</sup> C bus is set to trigger on Address or Address/Data.	
Syntax	:TRIGger:BUS:B1:I2C:ADDRess:VALue {string   ? }	
Related commands	:TRIGger:BUS:B1:I2C:ADDRess:MODE	
Parameter	<string>	7/10 characters, must be enclosed in double quotes, "string". x = don't care 1 = binary 1 0 = binary 0
Return Parameter	Returns the address value.	
Example 1	:TRIGger:BUS:B1:I2C:ADDRess:VALue "xxx0101" Sets the address to XXX0101	
Example 2	:TRIGger:BUS:B1:I2C:ADDRess:VALue? XXX0101	

### 3-14-42. :TRIGger:BUS:B1:I2C:ADDRess:DIRECTION




Description	Sets or queries the address bit as read write or don't care.	
Note	This setting only applies when the I <sup>2</sup> C trigger is set to trigger on Address or Address/Data	
Syntax	:TRIGger:BUS:B1:I2C:ADDRess:DIRECTION { READ   WRITE   NOCARE   ? }	
Related commands	:TRIGger:BUS:B1:I2C:CONDition	
Parameter	READ	Set read as the data direction.
	WRITE	Set write as the data direction.
	NOCARE	Set either as the data direction.
Return Parameter	Returns the direction (READ, WRITE, NOCARE).	
Example	:TRIGger:BUS:B1:I2C:ADDRess:DIRECTION READ Sets the direction to READ.	

### 3-14-43. :TRIGger:BUS:B1:I2C:DATa:SIZE




Description	Sets or queries the data size in bytes for the I <sup>2</sup> C bus.
Note	This setting only applies when the I <sup>2</sup> C trigger is set to trigger on Data or Address/Data
Syntax	:TRIGger:BUS:B1:I2C:DATa:SIZE {<NR1>   ? }
Related commands	:TRIGger:BUS:B1:I2C:CONDition
Parameter	<NR1> Number of data bytes (1 to 5 ).
Return parameter	<NR1> Returns the number of bytes.
Example	:TRIGger:BUS:B1:I2C:DATa:SIZE 3 Sets the number of bytes to 3.

### 3-14-44. :TRIGger:BUS:B1:I2C:DATa:VALue




Description	Sets or queries the triggering data value for the I <sup>2</sup> C bus when the I <sup>2</sup> C bus is set to trigger on Data or Address/Data.
Syntax	:TRIGger:BUS:B1:I2C:DATa:VALue {string   ? }
Related commands	:TRIGger:BUS:B1:I2C:DATa:SIZE
Parameter	<string> The number of characters in the string depends on the data size setting. The string must be enclosed in double quotes, "string". x = don't care 1 = binary 1 0 = binary 0
Return Parameter	Returns the data value.
Example1	:TRIGger:BUS:B1:I2C:DATa:SIZE 1 :TRIGger:BUS:B1:I2C:DATa:VALue "1x1x0101" Sets the value to XXX0101
Example 2	:TRIGger:BUS:B1:I2C:DATa:VALue? 1X1X0101

### 3-14-45. :TRIGger:BUS:B1:UART:CONDition




Description	Sets or queries the UART triggering condition.	
Syntax	:TRIGger:BUS:B1:UART:CONDition { RXSTArt   RXDATA   RXENDPacket   TXSTArt   TXDATA   TXENDPacket   TXPARItyerr   RXPARItyerr   ? }	
Parameter	RXSTArt	Set trigger on the RX Start Bit.
	RXDATA	Set trigger on RX Data.
	RXENDPack et	Set trigger on the RX End of Packet condition.
	RXPARItyerr	Set trigger on RX Parity error condition.
	TXSTArt	Set trigger on the TX Start Bit.
	TXDATA	Set trigger on TX Data.
	TXENDPacke t	Set trigger on the TX End of Packet condition.
	TXPARItyerr	Set trigger on TX Parity error condition.
Return Parameter	Returns the triggering condition.	
Example	:TRIGger:BUS:B1:UART:CONDition TXDATA Sets the UART bus to trigger on Tx Data.	

### 3-14-46. :TRIGger:BUS:B1:UART:RX:DATa:SIze




Description	Sets or queries the number of bytes for UART data.	
Note	This setting only applies when the UART trigger is set to trigger on Rx Data	
Syntax	:TRIGger:BUS:B1:UART:RX:DATa:SIze {<NR1>   ?}	
Related commands	:TRIGger:BUS:B1:UART:CONDition	
Parameter	<NR1>	Number of bytes (1 to 10).
Return parameter	<NR1>	Returns the number of bytes.
Example	:TRIGger:BUS:B1:UART:RX:DATa:SIze 5 Sets the number of bytes to 5.	

### 3-14-47. :TRIGger:BUS:B1:UART:RX:DATa:VALue




Description	Sets or queries the triggering data value for the UART bus when the bus is set to trigger on Rx Data.
Syntax	:TRIGger:BUS:B1:UART:RX:DATa:VALue {string   ? }
Related commands	:TRIGger:BUS:B1:UART:RX:DATa:SIZE
Parameter	<p>&lt;string&gt;</p> <p>The number of characters in the string depends on the data size setting. The string must be enclosed in double quotes, "string".</p> <p>x = don't care 1 = binary 1 0 = binary 0</p>
Return Parameter	Returns the data value.
Example 1	<pre>:TRIGger:BUS:B1:UART:CONDition RXDATA :TRIGger:BUS:B1:UART:RX:DATa:SIZE 1 :TRIGger:BUS:B1:UART:RX:DATa:VALue "1x1x0101" Sets the value to 1x1x0101</pre>
Example 2	<pre>:TRIGger:BUS:B1:UART:RX:DATa:VALue? 1X1X0101</pre>

### 3-14-48. :TRIGger:BUS:B1:UART:TX:DATa:SIZE




Description	Sets or queries the number of bytes for UART data.
Note	This setting only applies when the UART trigger is set to trigger on Tx Data
Syntax	:TRIGger:BUS:B1:UART:TX:DATa:SIZE {<NR1>   ? }
Related commands	:TRIGger:BUS:B1:UART:CONDition
Parameter	<NR1> Number of bytes (1 to 10).
Return parameter	<NR1> Returns the number of bytes.
Example	<pre>:TRIGger:BUS:B1:UART:TX:DATa:SIZE 5 Sets the number of bytes to 5.</pre>

### 3-14-49. :TRIGger:BUS:B1:UART:TX:DATA:VALue




Description	Sets or queries the triggering data value for the UART bus when the bus is set to trigger on Tx Data.
Syntax	:TRIGger:BUS:B1:UART:TX:DATA:VALue {string   ? }
Related commands	:TRIGger:BUS:B1:UART:TX:DATA:SIZE
Parameter	<p>&lt;string&gt;</p> <p>The number of characters in the string depends on the data size setting. The string must be enclosed in double quotes, "string".</p> <p>x = don't care 1 = binary 1 0 = binary 0</p>
Return Parameter	Returns the data value.
Example1	<pre>:TRIGger:BUS:B1:UART:CONDition TXDATA :TRIGger:BUS:B1:UART:TX:DATA:SIZE 1 :TRIGger:BUS:B1:UART:TX:DATA:VALue "1x1x0101" Sets the value to 1x1x0101</pre>
Example 2	<pre>:TRIGger:BUS:B1:UART:TX:DATA:VALue? 1X1X0101</pre>

### 3-14-50. :TRIGger:BUS:B1:SPI:CONDition




Description	Sets or queries the SPI triggering condition.								
Syntax	:TRIGger:BUS:B1:SPI:CONDition {SS   MISO   MOSI   MISOMOSI   ? }								
Parameter	<table> <tr> <td>SS</td><td>Set to trigger on the Slave Selection condition.</td></tr> <tr> <td>MISO</td><td>Set to trigger on the Master-In Slave-Out condition.</td></tr> <tr> <td>MOSI</td><td>Set to trigger on the Master-Out Slave-In condition.</td></tr> <tr> <td>MISOMOSI</td><td>Set to trigger on the Master-In Slave-Out and Master-Out Slave-In conditions.</td></tr> </table>	SS	Set to trigger on the Slave Selection condition.	MISO	Set to trigger on the Master-In Slave-Out condition.	MOSI	Set to trigger on the Master-Out Slave-In condition.	MISOMOSI	Set to trigger on the Master-In Slave-Out and Master-Out Slave-In conditions.
SS	Set to trigger on the Slave Selection condition.								
MISO	Set to trigger on the Master-In Slave-Out condition.								
MOSI	Set to trigger on the Master-Out Slave-In condition.								
MISOMOSI	Set to trigger on the Master-In Slave-Out and Master-Out Slave-In conditions.								
Return Parameter	Returns the triggering condition.								
Example	<pre>:TRIGger:BUS:B1:SPI:CONDition MISO Sets the SPI bus to trigger on MISO.</pre>								

### 3-14-51. :TRIGger:BUS:B1:SPI:DATa:SIZE




Description	Sets or queries the number of words for SPI data.
Note	This setting only applies when the SPI trigger is set to trigger on MISO, MOSI or MISO/MOSI
Syntax	:TRIGger:BUS:B1:SPI:DATa:SIZE {<NR1>   ?}
Related commands	:TRIGger:BUS:B1:SPI:CONDITION
Parameter	<NR1> Number of words (1 to 32).
Return parameter	<NR1> Returns the number of words.
Example	:TRIGger:BUS:B1:SPI:DATa:SIZE 10 Sets the number of words to 10.

### 3-14-52. :TRIGger:BUS:B1:SPI:DATa:MISO:VALue




Description	Sets or queries the triggering data value for the SPI bus when the bus is set to trigger on MISO or MISO/MOSI.
Syntax	:TRIGger:BUS:B1:SPI:DATa:MISO:VALue {string   ?}
Related commands	:TRIGger:BUS:B1:SPI:DATa:SIZE
Parameter	<string> The number of characters in the string depends on the data size setting. The string must be enclosed in double quotes, "string". x = don't care 1 = binary 1 0 = binary 0
Return Parameter	Returns the data value.
Example1	:TRIGger:BUS:B1:SPI:CONDITION MISO :TRIGger:BUS:B1:SPI:DATa:SIZE 2 :TRIGger:BUS:B1:SPI:DATa:MISO:VALue "1x1x0101" Sets the value to 1x1x0101
Example 2	:TRIGger:BUS:B1:SPI:DATa:MISO:VALue? 1X1X0101

### 3-14-53. :TRIGger:BUS:B1:SPI:DATa:MOStI:VALUe




Description	Sets or queries the triggering data value for the SPI bus when the bus is set to trigger on MOSI or MISO/MOSI.	
Syntax	:TRIGger:BUS:B1:SPI:DATa:MOStI:VALUe {string   ? }	
Related commands	:TRIGger:BUS:B1:SPI:DATa:SIze	
Parameter	<string>	The number of characters in the string depends on the data size setting. The string must be enclosed in double quotes, "string". x = don't care 1 = binary 1 0 = binary 0
Return Parameter	Returns the data value.	
Example1	:TRIGger:BUS:B1:SPI:CONDition MOSI :TRIGger:BUS:B1:SPI:DATa:SIze 2 :TRIGger:BUS:B1:SPI:DATa:MOStI:VALUe "1x1x0101" Sets the value to 1x1x0101	
Example2	:TRIGger:BUS:B1:SPI:DATa:MOStI:VALUe? 1X1X0101	

### 3-14-54. :TRIGger:BUS:B1:CAN:CONDition




Description	Sets or returns the CAN trigger condition.	
Syntax	<code>:TRIGger:BUS:B1:CAN:CONDition</code> <code>{SOF FRAMETYPE IDentifier DATA IDANDDATA EOF ACKMISS STUFFERR ?}</code>	
Parameter/ Return parameter	SOF FRAMETYPE Identifier DATA IDANDDATA EOF ACKMISS STUFFERR	Triggers on a start of frame Triggers on the type of frame Triggers on a matching identifier Triggers on matching data Triggers on matching identifier and data field Triggers on the end of frame Triggers on a missing acknowledge Triggers on a bit stuffing error
Example1	<code>:TRIGger:BUS:B1:CAN:CONDition SOF</code> Triggers on a start of frame.	
Example2	<code>:TRIGger:BUS:B1:CAN:CONDition?</code> <code>&gt;SOF</code>	

### 3-14-55. :TRIGger:BUS:B1:CAN:FRAMETYPE



Description	Sets or returns the frame type for a CAN FRAMETYPE trigger.	
Syntax	<code>:TRIGger:BUS:B1:CAN:FRAMETYPE</code> <code>{DATA REMote ERRor OVERLoad ?}</code>	
Parameter/ Return parameter	DATA REMote ERRor OVERLoad	Sets the frame type to data frame Sets the frame type to remote frame Sets the frame type to error frame Sets the frame type to overload
Example	<code>:TRIGger:BUS:B1:CAN:FRAMETYPE DATA</code> Sets the frame type to DATA.	

3-14-56. :TRIGger:BUS:B1:CAN:IDentifier:MODe




Description Sets or returns the CAN addressing mode for the bus.

Syntax :TRIGger:BUS:B1:CAN:IDentifier:MODe  
{STANDARD|EXTended|?}

Parameter/ Return parameter STANDARD Standard addressing mode  
EXTended Extended addressing mode

Example :TRIGger:BUS:B1:CAN:IDentifier:MODe?  
>STANDARD  
Returns the addressing mode.

3-14-57. :TRIGger:BUS:B1:CAN:IDentifier:VALue



Description Sets or returns the binary address string used for the CAN trigger.  
Note: Only applicable when the trigger condition is set to ID or IDANDDATA.


Syntax :TRIGger:BUS:B1:CAN:IDentifier:VALue {<string>|?}

Related Commands :TRIGger:BUS:B1:CAN:IDentifier:MODe

Parameter/ Return parameter <string>  
The size of the string depends on the data size setting. The string must be enclosed in double quotes, "string".  
String contents:  
x = don't care  
1 = binary 1  
0 = binary 0


Example :TRIGger:BUS:B1:CAN:CONDition ID  
:TRIGger:BUS:B1:CAN:IDentifier:MODe STANDARD  
:TRIGger:BUS:B1:CAN:IDentifier:VALue "01100X1X01X"  
:TRIGger:BUS:B1:CAN:IDentifier:VALue?  
>01100X1X01X

### 3-14-58. :TRIGger:BUS:B1:CAN:IDentifier:DIRECTION




Description	Sets or queries the address bit as read, write or don't care.	
Syntax	:TRIGger:BUS:B1:CAN:IDentifier:DIRECTION {READ WRITE NOCARE ?}	
Parameter/ Return parameter	READ	Sets read as the data direction
	WRITE	Sets write as the data direction
	NOCARE	Sets either as the data direction
Example1	:TRIGger:BUS:B1:CAN:IDentifier:DIRECTION? >WRITE	
Example2	:TRIGger:BUS:B1:CAN:IDentifier:DIRECTION READ :TRIGger:BUS:B1:CAN:IDentifier:DIRECTION? > READ	

### 3-14-59. :TRIGger:BUS:B1:CAN:DATa:QUALifier




Description	Sets or returns the CAN data qualifier. Note: Only applicable when the triggering condition is set to DATA or IDANDDATA.	
Syntax	:TRIGger:BUS:B1:CAN:DATa:QUALifier {LESSthan THAN EQUAL UNEQual LESSEQual MOREEQual ?}	
Parameter/ Return parameter	LESSthan	Triggers when the data is less than the qualifier value.
	THAN	Triggers when the data is greater than the qualifier value.
	EQUAL	Triggers when the data is equal to the qualifier value.
	UNEQual	Triggers when the data is not equal to the qualifier value.
	LESSEQual	Triggers when the data is less than or equal to the qualifier value.
	MOREEQual	Triggers when the data is more than or equal to the qualifier value.
Example	:TRIGger:BUS:B1:CAN:DATa:QUALifier? >EQUAL :TRIGger:BUS:B1:CAN:DATa:QUALifier THAN :TRIGger:BUS:B1:CAN:DATa:QUALifier? >THAN	

### 3-14-60. :TRIGger:BUS:B1:CAN:DATA:SIZE




Description	Sets or returns the length of the data string in bytes for a CAN trigger. Note: Only applicable when the condition is set to DATA or IDANDDATA.
Syntax	:TRIGger:BUS:B1:CAN:DATA:SIZE {<NR1>} ?
Parameter/ Return parameter	<NR1> 1~8 (bytes)
Example	:TRIGger:BUS:B1:CAN:DATA:SIZE? >1 :TRIGger:BUS:B1:CAN:DATA:SIZE 2 :TRIGger:BUS:B1:CAN:DATA:SIZE? >2

### 3-14-61. :TRIGger:BUS:B1:CAN:DATA:VALue




Description	Sets or returns the binary data string to be used for a CAN trigger. Note: Only applicable when the condition is set to DATA or IDANDDATA.
Related Commands	:TRIGger:BUS:B1:CAN:DATA:SIZE
Syntax	:TRIGger:BUS:B1:CAN:DATA:VALue {<string>} ?
Parameter/ Return parameter	<string> The size of the string depends on the data size setting. The string must be enclosed in double quotes, "string". String contents: x = don't care 1 = binary 1 0 = binary 0
Example	:TRIGger:BUS:B1:CAN:DATA:SIZE 1 :TRIGger:BUS:B1:CAN:DATA:VALue "01010X1X" :TRIGger:BUS:B1:CAN:DATA:VALue? >01010X1X

## 3-14-62. :TRIGger:BUS:B1:LIN:CONDition




Description	Sets or returns the LIN trigger condition.	
Syntax	<pre>:TRIGger:BUS:B1:LIN:CONDition {{SYNCField IDentifier DATA IDANDDATA WAKEUp SLEEP ERRor ?}}</pre>	
Parameter/ Return parameter	SYNCField	Sets the LIN trigger condition to the sync field.
	IDentifier	Sets the LIN trigger condition to identifier field.
	DATA	Sets the LIN trigger condition to the data field.
	IDANDDATA	Sets the LIN trigger condition to identifier and data field
	WAKEUp	Sets the LIN trigger condition to wake up.
	SLEEP	Sets the LIN trigger condition to sleep.
	ERRor	Sets the LIN trigger condition to error.
Example	<pre>:TRIGger:BUS:B1:LIN:CONDition? &gt;IDANDDATA :TRIGger:BUS:B1:LIN:CONDition DATA :TRIGger:BUS:B1:LIN:CONDition? &gt;DATA</pre>	

## 3-14-63. :TRIGger:BUS:B1:LIN:DATa:QUALifier




Description	Sets or returns the LIN data qualifier. Note: Only applicable when the trigger condition is set to DATA or IDANDDATA.	
Syntax	:TRIGger:BUS:B1:LIN:DATa:QUALifier {LESSthan THAN EQUAL UNEQual LESSEQual MOREEqual ?}	
Parameter/ Return parameter	LESSthan	Triggers when the data is less than the qualifier value.
	THAN	Triggers when the data is greater than the qualifier value.
	EQUAL	Triggers when the data is equal to the qualifier value.
	UNEQual	Triggers when the data is not equal to the qualifier value.
	LESSEQual	Triggers when the data is less than or equal to the qualifier value.
	MOREEqual	Triggers when the data is more than or equal to the qualifier value.
	LESSthan	Triggers when the data is less than the qualifier value.
Example	<pre>:TRIGger:BUS:B1:LIN:DATa:QUALifier? &gt;EQUAL :TRIGger:BUS:B1:LIN:DATa:QUALifier THAN :TRIGger:BUS:B1:LIN:DATa:QUALifier? &gt;THAN</pre>	

### 3-14-64. :TRIGger:BUS:B1:LIN:DATa:SIZE




Description	Sets or returns the length of the data string in bytes for the LIN trigger. Note: Only applicable when the condition is set to DATA or IDANDDATA.
Syntax	:TRIGger:BUS:B1:LIN:DATa:SIZE {<NR1> ?}
Parameter/ Return parameter	<NR1>      1~8 (bytes)
Example	:TRIGger:BUS:B1:LIN:DATa:SIZE? >1 :TRIGger:BUS:B1:LIN:DATa:SIZE 2 :TRIGger:BUS:B1:LIN:DATa:SIZE? >2

### 3-14-65. :TRIGger:BUS:B1:LIN:DATa:VALue




Description	Sets or returns the binary data string to be used for the LIN trigger. Note: Only applicable when the condition is set to DATA or IDANDDATA.
Related Commands	:TRIGger:BUS:B1:LIN:DATa:SIZE
Syntax	:TRIGger:BUS:B1:LIN:DATa:VALue {<string> ?}
Parameter/ Return parameter	<string>      The size of the string depends on the data size setting. The string must be enclosed in double quotes, "string". String contents: x = don't care 1 = binary 1 0 = binary 0
Example	:TRIGger:BUS:B1:LIN:DATa:SIZE 1 :TRIGger:BUS:B1:LIN:DATa:VALue "01010X1X" :TRIGger:BUS:B1:LIN:DATa:VALue? >01010X1X

### 3-14-66. :TRIGger:BUS:B1:LIN:ERRTYPE



Description	Sets or returns the error type be used for the LIN trigger.
Syntax	:TRIGger:BUS:B1:LIN:ERRTYPE {SYNC PARIty CHECKsum ?}
Parameter/ Return parameter	SYNC Sets the LIN error type to SYNC. PARIty Sets the LIN error type to parity. CHECKsum Sets the LIN error type to checksum.
Example	:TRIGger:BUS:B1:LIN:ERRTYPE? >SYNC :TRIGger:BUS:B1:LIN:ERRTYPE CHECKSUM :TRIGger:BUS:B1:LIN:ERRTYPE? >CHECKSUM


### 3-14-67. :TRIGger:BUS:B1:LIN:IDentifier:VALue



Description	Sets or returns the binary address string to be used for the LIN trigger.  Note: Only applicable when the condition is set to DATA or IDANDDATA.
Syntax	:TRIGger:BUS:B1:LIN:IDentifier:VALue {<string> ?}
Parameter/ Return parameter	<string> The size of the string depends on the data size setting. The string must be enclosed in double quotes, "string".  String contents: x = don't care 1 = binary 1 0 = binary 0
Example	:TRIGger:BUS:B1:LIN:CONDition ID :TRIGger:BUS:B1:LIN:IDentifier:VALue "00X1X01X" :TRIGger:BUS:B1:LIN:IDentifier:VALue? >01100X1X01X


### 3-15. System Commands

#### 3-15-1. :SYSTem:LOCK




Description	Turns the panel lock on off.				
Syntax	:SYSTem:LOCK {OFF   ON   ? }				
Parameter	<table><tr><td>OFF</td><td>System lock off</td></tr><tr><td>ON</td><td>System lock on</td></tr></table>	OFF	System lock off	ON	System lock on
OFF	System lock off				
ON	System lock on				
Return parameter	Returns the status of the panel lock (ON, OFF).				
Example	:SYSTem:LOCK ON Turns the panel lock on.				

#### 3-15-2. :SYSTem:ERRor



Description	Queries the error queue. See the appendix on page 176 for details.
Syntax	:SYSTem:ERRor?
Return parameter	Returns the last message in the error queue.
Example	:SYSTem:ERRor? +0, "No error."

#### 3-15-3. :USBDelay



Description	Sets or returns the USB delay function for the PC connection which Windows 10 installed				
Syntax	:USBDelay {OFF ON} :USBDelay?				
Parameter/ Return parameter	<table><tr><td>&lt;ON&gt;</td><td>Turns on the USB delay function</td></tr><tr><td>&lt;OFF&gt;</td><td>Turns off the USB delay function</td></tr></table>	<ON>	Turns on the USB delay function	<OFF>	Turns off the USB delay function
<ON>	Turns on the USB delay function				
<OFF>	Turns off the USB delay function				
Example	:USBDelay ON Turns on the USB delay function when the scope connected with window 10 installed PC..				

### 3-16. Save/Recall Commands


3-16-1. :RECALL:SETUp.....	111
3-16-2. :RECALL:WAVEform.....	111
3-16-3. :SAVE:IMAGE.....	111
3-16-4. :SAVE:IMAGE:FILEFormat .....	112
3-16-5. :SAVE:IMAGE:INKSaver.....	112
3-16-6. :SAVE:SETUp .....	112
3-16-7. :SAVE:WAVEform .....	113
3-16-8. :SAVE:WAVEform:FILEFormat.....	114

#### 3-16-1. :RECALL:SETUp

 Set →


Description	Recalls setup settings from memory or USB.	
Syntax	:RECALL:SETUp {S1~S20   <file path>"Disk:/xxx.SET", "USB:/xxx.SET")}	
Parameter	S1~S20 <file path>	Recall Set1~Set20 Recall a file from the DSO internal files system or from a USB flash drive.
Example	<code>:RECALL:SETUP S1</code> Recalls setup setting S1 from memory. <code>:RECALL:SETUP "Disk:/DS0001.SET"</code> Recall setup setting DS0001.SET from system internal disk.	

#### 3-16-2. :RECALL:WAVEform

 Set →

Description	Recalls a waveform from wave1~wave20 or from file to REF1~4.	
Note	Only *.LSF files can be recalled using this command. *.CSV files cannot be recalled.	
Syntax	:RECALL:WAVEform{W<n>   <file path>"Disk:/xxx.LSF", "USB:/xxx.LSF")},REF<X>	
Parameter	n xxx.LSF <X>	1~20 (Wave1~wave20) Filename in file path. 1,2,3,4 (REF1, REF2, REF3, REF4)
Example	<code>:RECALL:WAVEform W1, REF1</code> Recalls the waveform stored in Wave1 to reference 1.	


#### 3-16-3. :SAVE:IMAGE

 Set →

Description	Saves a screen image to the assigned file path with a specified filename.	
Syntax	:SAVE:IMAGE {<file path>"Disk:/xxx.PNG", "USB:/xxx.BMP)}	


Related commands	:SAVe:IMAGe:FILEFormat :SAVe:IMAGe:INKSaver
Parameter	xxx.PNG or File name (8 characters max) xxx.BMP
Example	:SAVe:IMAGe "Disk:/pic1.PNG" Saves a screen image named pic1.png to the root directory (Disk:/) of the scope. :SAVe:IMAGe "USB:/pic1.BMP" Saves a screen image named pic1.bmp to the root directory of the external USB flash disk.

#### 3-16-4. :SAVe:IMAGe:FILEFormat




Description	Sets the file format for image.
Syntax	:SAVe:IMAGe:FILEFormat {PNG   BMP   ?}
Related commands	:SAVe:IMAGe :SAVe:IMAGe:INKSaver
Parameter	PNG Sets the file format to PNG BMP Sets the file format to BMP
Return parameter	Returns the file format (PNG, BMP).
Example	:SAVe:IMAGe:FILEFormat PNG Sets the image file format to PNG.

#### 3-16-5. :SAVe:IMAGe:INKSaver



Description	Turns Ink Saver on or off.
Syntax	:SAVe:IMAGe:INKSaver {OFF   ON   ?}
Related commands	:SAVe:IMAGe :SAVe:IMAGe:FILEFormat
Parameter	OFF Turns Inksaver off. ON Turns Inksaver on.
Return parameter	Returns Ink Saver status (ON, OFF).
Example	:SAVe:IMAGe:INKSaver ON Turns Ink Saver on.


#### 3-16-6. :SAVe:SETUp



Description	Saves the current setup to internal memory (Set1~Set20) or the designated file path.
Syntax	:SAVe:SETUp <file path> ("Disk:/xxx.SET", "USB:/xxx.SET")   S1~S20)

Parameter	S1~S20 File path	Saves the setup to Set1~Set20 Saves the setup to disk to the specified file path.
Example	:SAVe:SETUp S1 Saves the current setup to Set1 in internal memory. :SAVe:SETUp "Disk:/DS0001.SET" Saves the current setup to DS0001.SET in the external USB flash disk.	


### 3-16-7. :SAVe:WAVEform



Description	Saves a waveform to internal memory or to a designated file path.	
Syntax	:SAVe:WAVEform {CH1~REF4, REF<X>}   {CH1~REF4, W1~W20}   {CH1~ALL, file path}	
Parameter	CH1~REF4, <X> W1~W20 ALL File path	CH1~CH4, Math, REF1~4 1,2,3,4 (REF1, REF2, REF3, REF4) Wave1~Wave20 All the displayed waveforms on screen. Saves the waveform(s) to disk or USB to the specified file path.
Example	:SAVe:WAVEform CH1, REF2 Saves the channel1 waveform to REF2. :SAVe:WAVEform ALL, "Disk:/ALL001" Creates a folder which named "ALL001" and saves all displayed waveforms to the "ALL001" directory in the LSF format. :SAVe:WAVEform ALL, "Disk:/ALL002" Save the all channels waveform to the root directory (Disk:/) of the internal flash disk in the CSV format. :SAVe:WAVEform CH2, "Disk:/DS0003.LSF" Save the channel 2's waveform to the root directory (Disk:/) of the internal flash disk in the LSF format.	

*Note: Only LSF file format can be recalled by scope using remote commands.*


### 3-16-8. :SAVe:WAVEform:FILEFormat



Description	Sets the waveform savefile format.	
Syntax	:SAVe:WAVEform:FILEFormat {LSF   DCSV   FCSV   ?}	
Parameter	LSF	Sets the file format to the DCS-2000E's internal file format, LSF. (xxx.LSF)(no support LA)
	DCSV	Sets the file format to detail CSV. (xxx.CSV)
	FCSV	Sets the file format to fast CSV. (xxx.CSV)
Return parameter	Returns the file format	
Example	:SAVe:WAVEform:FILEFormat LSF Sets the file format to LSF.	

### 3-17. Ethernet Commands

#### 3-17-1. :ETHERnet:DHCp



Description	Sets or queries the DHCP settings.	
Syntax	:ETHERnet:DHCp { OFF   ON   ? }	
Parameter	ON	Turns DHCP on.
	OFF	Turns DHCP off.
Example	:ETHERnet:DHCp ON Turns DHCP on.	

### 3-18. Time Commands

#### 3-18-1. :DATE



Description	Sets the system date and time.	
Syntax	:DATE {string}	
Parameter	{string}	"YYYYMMDDhhmmss" YYYY: year, MM: month, DD: day hh: hour, mm: minute, ss: second
Example	:date "20101202142830" Sets the time and date as: Year: 2010, Month: 12, Day: 02, Hour: 14 (2PM), Minute: 28, Second: 30.	

### **3-19. Bus Decode Commands**

---

3-19-1. :BUS1 .....	116
3-19-2. :BUS1:STATE .....	116
3-19-3. :BUS1:TYPe .....	116
3-19-4. :BUS1:INPut .....	116
3-19-5. :BUS1:I2C:ADDRess:RWINclude .....	117
3-19-6. :BUS1:I2C:SCLK:SOURce .....	117
3-19-7. :BUS1:I2C:SDA:SOURce .....	117
3-19-8. :BUS1:UART:BITRate .....	118
3-19-9. :BUS1:UART:DATABits .....	118
3-19-10. :BUS1:UART:PARIty .....	119
3-19-11. :BUS1:UART:PACKEt .....	119
3-19-12. :BUS1:UART:EOFPacket .....	119
3-19-13. :BUS1:UART:TX:SOURce .....	120
3-19-14. :BUS1:UART:RX:SOURce .....	120
3-19-15. :BUS1:SPI:SCLK:POLARity .....	120
3-19-16. :BUS1:SPI:SS:POLARity .....	121
3-19-17. :BUS1:SPI:WORDSize .....	121
3-19-18. :BUS1:SPI:BITOrder .....	121
3-19-19. :BUS1:SPI:SCLK:SOURce .....	121
3-19-20. :BUS1:SPI:SS:SOURce .....	122
3-19-21. :BUS1:SPI:MOSI:SOURce .....	122
3-19-22. :BUS1:SPI:MISO:SOURce .....	122
3-19-23. :BUS1:DIsplay:FORMAT .....	123
3-19-24. :LISTer:DATA .....	123
3-19-25. :BUS1:CAN:SOURce .....	123
3-19-26. :BUS1:CAN:PROBe .....	124
3-19-27. :BUS1:CAN:SAMPLEpoint .....	124
3-19-28. :BUS1:CAN:BITRate .....	124
3-19-29. :BUS1:LIN:BITRate .....	125
3-19-30. :BUS1:LIN:IDFORmat .....	125
3-19-31. :BUS1:LIN:POLARity .....	125
3-19-32. :BUS1:LIN:SAMPLEpoint .....	125
3-19-33. :BUS1:LIN:SOURce .....	126
3-19-34. :BUS1:LIN:STANDARD .....	126

---

### 3-19-1. :BUS1

→Query

Description	Returns the supported BUS types.
Syntax	:BUS1?
Return Parameter	Returns the supported bus types.
Example	BUS1? I2C,SPI,UART,CAN,LIN

### 3-19-2. :BUS1:STATE

Set →  
→Query

Description	Sets or queries the state of the bus.
Syntax	:BUS1:STATE { OFF   ON   ? }
Related commands	:BUS1:TYPe
Parameter/Return parameter	OFF      Turns the bus off. ON      Turns the bus on.
Example	:BUS1:STATE ON Turns the bus on.

### 3-19-3. :BUS1:TYPe

Set →  
→Query


Description	Sets or queries the type of bus.
Syntax	:BUS1:TYPe { UART   I2C   SPI   CAN   LIN? }
Related commands	:BUS1:STATE
Parameter/Return parameter	UART      Sets the bus to UART mode. I2C      Sets the bus to I <sup>2</sup> C mode. SPI      Sets the bus to SPI mode. CAN      Sets the bus to CAN mode. LIN      Sets the bus to LIN mode.
Example	:BUS1:TYPe SPI Sets the bus to SPI mode.

### 3-19-4. :BUS1:INPut

Set →  
→Query


Description	Sets or returns the analog source.
Syntax	:BUS1:INPut {ANALog   ?}
Parameter/Return parameter	ANALog      Sets the source to the analog inputs
Example1	:BUS1:INPut ANALog :BUS1:CAN:SOURce CH1

### 3-19-5. :BUS1:I2C:ADDRess:RWINclude




Description	Sets or queries whether the read/write bit is included in the I <sup>2</sup> C address.	
Syntax	:BUS1:I2C:ADDRess:RWINclude { OFF   ON   ? }	
Related commands	:BUS1:STATE	
Parameter	OFF	The R/W is not included.
	ON	The R/W is included.
Return parameter	0	The R/W is not included.
	1	The R/W is included.
Example	:BUS1:I2C:ADDRess:RWINclude ON Includes the R/W bit in the I <sup>2</sup> C address.	

### 3-19-6. :BUS1:I2C:SCLK:SOURce



Description	Sets or queries which channel is used for the I <sup>2</sup> C SCLK source.	
Syntax	:BUS1:I2C:SCLK:SOURce { CH1   CH2   CH3   CH4   ? }	
Parameter/Return parameter	CH1 to CH4	Analog channels 1 ~ 4.
Example	:BUS1:I2C:SCLK:SOURce CH1 Sets channel CH1 as the SCLK source.	

### 3-19-7. :BUS1:I2C:SDA:SOURce



Description	Sets or queries which channel is used for the I <sup>2</sup> C SDA source.	
Syntax	:BUS1:I2C:SDA:SOURce { CH1   CH2   CH3   CH4   ? }	
Parameter/Return parameter	CH1 to CH4	Analog channels 1 ~ 4.
Example	:BUS1:I2C:SDA:SOURce CH1 Sets channel 1 as the SDA source.	

### 3-19-8. :BUS1:UART:BITRate

Set →  
→ Query

---

Description	Sets or queries the UART bit rate.				
Syntax	:BUS1:UART:BITRate {<NR1>} ?				
Parameter/Return parameter	<NR1>	UART bit rate (0~31)			
<NR1>	Rate (bps)	<NR1>	Rate (bps)		
0	50	16	15200		
1	75	17	19200		
2	110	18	28800		
3	134	19	31250		
4	150	20	38400		
5	300	21	56000		
6	600	22	57600		
7	1200	23	76800		
8	1800	24	115200		
9	2000	25	128000		
10	2400	26	230400		
11	3600	27	460800		
12	4800	28	921600		
13	7200	29	1382400		
14	9600	30	1843200		
15	14400	31	2764800		

---

Example	:BUS1:UART:BITRate 10
	Sets the bit rate to 2400.

### 3-19-9. :BUS1:UART:DATABits

Set →  
→ Query


---

Description	Sets or queries the number of UART data bits for bus 1.	
Syntax	:BUS1:UART:DATABits { 5   6   7   8   9   ? }	
Parameter/Return parameter	5	5 data bits in the UART frame.
	6	6 data bits in the UART frame.
	7	7 data bits in the UART frame.
	8	8 data bits in the UART frame.

---


Example	:BUS1:UART:DATABits 7
	Sets the UART frame to 7 bits.

### 3-19-10. :BUS1:UART:PARItY




Description	Sets or queries the UART bus parity.		
Syntax	:BUS1:UART:PARItY { <NR1>   ? }		
Parameter/Return parameter	<table style="width: 100%;"><tr><td style="width: 30%; vertical-align: top;">&lt;NR1&gt;</td><td style="width: 70%; vertical-align: top;">0: None 1: Odd parity 2: Even parity</td></tr></table>	<NR1>	0: None 1: Odd parity 2: Even parity
<NR1>	0: None 1: Odd parity 2: Even parity		
Example	:BUS1:UART:PARItY 1 Sets the parity to odd.		

### 3-19-11. :BUS1:UART:PACKEt




Description	Sets or queries the UART packet setting.		
Syntax	:BUS1:UART:PACKEt {<NR1>   ? }		
Parameter/Return parameter	<table style="width: 100%;"><tr><td style="width: 30%; vertical-align: top;">&lt;NR1&gt;</td><td style="width: 70%; vertical-align: top;">0: Off 1: On</td></tr></table>	<NR1>	0: Off 1: On
<NR1>	0: Off 1: On		
Example	:BUS1:UART:PACKEt 1 Turns UART packets on.		

### 3-19-12. :BUS1:UART:EOFPAcket




Description	Sets or queries the EOF character for the UART packet setting.		
Syntax	:BUS1:UART:EOFPAcket <NR1>		
Parameter/Return parameter	<table style="width: 100%;"><tr><td style="width: 30%; vertical-align: top;">&lt;NR1&gt;</td><td style="width: 70%; vertical-align: top;">0: NULL 1: LF (line feed) 2: CR (carriage return) 3: SP (space character) 4: FF</td></tr></table>	<NR1>	0: NULL 1: LF (line feed) 2: CR (carriage return) 3: SP (space character) 4: FF
<NR1>	0: NULL 1: LF (line feed) 2: CR (carriage return) 3: SP (space character) 4: FF		
Example	:BUS1:UART:EOFPAcket 2 Sets the OEF character to CR.		

### 3-19-13. :BUS1:UART:TX:SOURce




Description	Sets or queries which channel is used for the UART Tx source.	
Syntax	:BUS1:UART:TX:SOURce { OFF   CH1   CH2   CH3   CH4   ? }	
Parameter/Return parameter	OFF CH1 to CH4	Off, no Tx source CH1 to CH4
Example	:BUS1:UART:TX:SOURce CH1 Sets channel 1 as the Tx source.	

### 3-19-14. :BUS1:UART:RX:SOURce




Description	Sets or queries which channel is used for the UART Rx source.	
Syntax	:BUS1:UART:RX:SOURce { OFF   CH1   CH2   CH3   CH4   ? }	
Parameter/Return parameter	OFF CH1 to CH4	Off, no Rx source CH1 to CH4
Example	:BUS1:UART:RX:SOURce CH1 Sets channel 1 as the Rx source.	

### 3-19-15. :BUS1:SPI:SCLK:POLARity




Description	Sets or queries the polarity of the SCLK line for the SPI bus.	
Syntax	:BUS1:SPI:SCLK:POLARity { FALL   RISE   ? }	
Parameter/Return parameter	FALL RISE	Sets the polarity to falling edge. Sets the polarity to rising edge.
Example	:BUS1:SPI:SCLK:POLARity FALL Sets the polarity to falling edge.	

### 3-19-16. :BUS1:SPI:SS:POLARity




Description	Sets or queries the polarity of the SS line for the SPI bus.	
Syntax	:BUS1:SPI:SS:POLARity { LOW   HIGH   ? }	
Parameter/Return parameter	LOW	Active low polarity
	HIGH	Active high polarity
Example	:BUS1:SPI:SS:POLARity LOW Sets the SS line to active low.	

### 3-19-17. :BUS1:SPI:WORDSize




Description	Sets the number of bits per word for the SPI bus.	
Syntax	:BUS1:SPI:WORDSize {<NR1>   ? }	
Parameter/Return parameter	<NR1>	Bits per word (4~32)
Example	:BUS1:SPI:WORDSize 4 Sets the word size to 4 bits per word.	

### 3-19-18. :BUS1:SPI:BITORder




Description	Sets or queries the bit order for the SPI bus.	
Syntax	:BUS1:SPI:BITORder {<NR1>   ? }	
Parameter/Return parameter	<NR1>	0: MSB bit first 1: LSB bit first
Example	:BUS1:SPI:BITORder? 0 The bit order is currently set as MSB bit first.	

### 3-19-19. :BUS1:SPI:SCLK:SOURce




Description	Sets or queries which channel is used for the SPI SCLK source.	
Syntax	:BUS1:SPI:SCLK:SOURce { CH1   CH2   CH3   CH4   ? }	
Parameter/Return parameter	CH1 to CH4	CH1 to CH4
Example	:BUS1:SPI:SCLK:SOURce CH1 Sets channel 1 as the SPI SCLK source.	

## 3-19-20. :BUS1:SPI:SS:SOURce




Description	Sets or queries which channel is used for the SPI SS source.
Syntax	:BUS1:SPI:SS:SOURce { CH1   CH2   CH3   CH4   ? }
Parameter/Return parameter	CH1 to CH4    CH1 to CH4
Example	:BUS1:SPI:SS:SOURce CH1 Sets channel 1 as the SPI SS source.

## 3-19-21. :BUS1:SPI:MOSI:SOURce




Description	Sets or queries which channel is used for the SPI MOSI source.
Syntax	:BUS1:SPI:MOSI:SOURce { OFF   CH1   CH2   CH3   CH4   ? }
Parameter/Return parameter	CH1 to CH4    CH1 to CH4 OFF              No MOSI source.
Example	:BUS1:SPI:MOSI:SOURce CH1 Sets channel 1 as the SPI MOSI source.

## 3-19-22. :BUS1:SPI:MISO:SOURce



Description	Sets or queries which channel is used for the SPI MISO source.
Syntax	:BUS1:SPI:MISO:SOURce { OFF   CH1   CH2   CH3   CH4   ? }
Parameter/Return parameter	CH1 to CH4    CH1 to CH4 OFF              No MISO source.
Example	:BUS1:SPI:MISO:SOURce CH1 Sets channel CH1 as the SPI MISO source.

### 3-19-23. :BUS1:DISplay:FORMAT




Description	Sets or queries the display format for the bus, either binary or hexadecimal.
Syntax	:BUS1:DISplay:FORMAT { BINary   HEXadecimal   ? }
Parameter/Return parameter	BINary      Binary format HEXadecimal    Hexadecimal format
Example	: BUS1:DISplay:FORMAT BINary Sets the display format to binary.

### 3-19-24. :LISTer:DATA




Description	Returns the Event Table data as a binary block data.
Syntax	:LISTer:DATA?
Return parameter	Responds to the event table with decoded data. A binary header is added, the contents of the table are comma-delimited, and it is continuous with a line feed. Please obtain and expand the number of bytes specified by the data length. Binary header is in the format of # [data length digit number] [data length].
Example	LISTer:DATA?
CAN Decode	>#3366 Time,Identifier,DLC,Data,CRC,Missing Ack,[LF] -2.412ms,Bit Stuffing Error, , , ,[LF] -1.900ms,2A9,2,1F8B,1EA8, ,[LF] --1.132ms,00002327,3,7621 6A,33D9, ,[LF] -380.5us,Error Frame, , , ,[LF]
Note	The response format is changed in Ver1.37.

### 3-19-25. :BUS1:CAN:SOURce



Description	Sets or returns the CAN input source.
Syntax	:BUS1:CAN:SOURce { CH1   CH2   CH3   CH4   ? }
Parameter/Return parameter	CH1 ~ CH4      Analog channel source
Example	:BUS1:CAN:SOURCE? >CH1 Returns the CAN source.

### 3-19-26. :BUS1:CAN:PROBe




Description	Sets or returns the signal type of the CAN bus.								
Syntax	:BUS1:CAN:PROBe {CANH CANL TX RX  ? }								
Parameter/Return parameter	<table> <tr> <td>CANH</td><td>CAN-High</td></tr> <tr> <td>CANL</td><td>CAN-Low</td></tr> <tr> <td>TX</td><td>Transmit</td></tr> <tr> <td>RX</td><td>Receive</td></tr> </table>	CANH	CAN-High	CANL	CAN-Low	TX	Transmit	RX	Receive
CANH	CAN-High								
CANL	CAN-Low								
TX	Transmit								
RX	Receive								
Example	<pre>:BUS1:CAN:PROBe? &gt;CANH :BUS1:CAN:PROBe CANL :BUS1:CAN:PROBe? &gt;CANL</pre>								

### 3-19-27. :BUS1:CAN:SAMPLEpoint



Description	Returns the sample point of the CAN bus.
Syntax	:BUS1:CAN:SAMPLEpoint?
Return Parameter	Returns the sample point of the CAN bus as a percentage of the bit time.
Example	<pre>:BUS1:CAN:SAMPLEpoint? 50 Returns the sample point as a percentage.</pre>

### 3-19-28. :BUS1:CAN:BITRate




Description	Sets or returns the bit rate of the CAN bus.																
Syntax	:BUS1:CAN:BITRate {RATE10K RATE20K RATE50K RATE125K RATE250K  RATE500K RATE800K RATE1M   ?}																
Parameter/Return parameter	<table> <tr> <td>RATE10K</td><td>10 kbps</td></tr> <tr> <td>RATE20K</td><td>20 kbps</td></tr> <tr> <td>RATE50K</td><td>50 kbps</td></tr> <tr> <td>RATE125K</td><td>125 kbps</td></tr> <tr> <td>RATE250K</td><td>250 kbps</td></tr> <tr> <td>RATE500K</td><td>500 kbps</td></tr> <tr> <td>RATE800K</td><td>800 kbps</td></tr> <tr> <td>RATE1M</td><td>1 Mbps</td></tr> </table>	RATE10K	10 kbps	RATE20K	20 kbps	RATE50K	50 kbps	RATE125K	125 kbps	RATE250K	250 kbps	RATE500K	500 kbps	RATE800K	800 kbps	RATE1M	1 Mbps
RATE10K	10 kbps																
RATE20K	20 kbps																
RATE50K	50 kbps																
RATE125K	125 kbps																
RATE250K	250 kbps																
RATE500K	500 kbps																
RATE800K	800 kbps																
RATE1M	1 Mbps																

---

Example	:BUS1:CAN:BITRate? >RATE250K :BUS1:CAN:BITRate rate10k :BUS1:CAN:BITRate? >RATE10K
---------	--


### 3-19-29. :BUS1:LIN:BITRate




---

Description	Sets or returns the bit rate of the LIN bus.
Syntax	:BUS1:LIN:BITRate {<NR1>   ?}
Parameter/Return parameter	<NR1> 1200, 2400, 4800, 9600, 10417, 19200
Example	:BUS1:LIN:BITRate 9600 Sets the LIN bit rate to 9600 bps.


### 3-19-30. :BUS1:LIN:IDFORmat




---

Description	Sets or returns the LIN ID format.
Syntax	:BUS1:LIN:IDFORmat {NOPARity PARIty ?}
Parameter/Return parameter	NOPARity No parity PARIty Parity
Example	:BUS1:LIN:IDFORmat? NOPARTY Returns the ID format.

### 3-19-31. :BUS1:LIN:POLARity




---

Description	Sets or returns the LIN polarity.
Syntax	:BUS1:LIN:POLARity {NORMal INVerted ?}
Parameter/Return parameter	NORMal Normal LIN polarity INVerted Inverted LIN polarity
Example	:BUS1:LIN:POLARity? NORMAL Returns the LIN polarity.

### 3-19-32. :BUS1:LIN:SAMPLEpoint





---

Description	Returns the sample point of the LIN bus.
Syntax	:BUS1:LIN:SAMPLEpoint?

---

Return Parameter	Returns the sample point of the LIN bus as a percentage of the bit rate.
Example	:BUS1:LIN:SAMPLEpoint? 50 Returns the sample point as a percentage.


### 3-19-33. :BUS1:LIN:SOURce




---

Description	Sets or returns the LIN data source.
Syntax	:BUS1:LIN:SOURce {CH1   CH2   CH3   CH4   ?}
Parameter/Return parameter	CH1 ~ CH4      Analog channel source
Example	:BUS1:LIN:SOURCE? >CH1 Returns the LIN source.

### 3-19-34. :BUS1:LIN:STANDARD




---

Description	Sets or returns the LIN standard.
Syntax	:BUS1:LIN:STANDARD {V1X V2X BOTH ?}
Parameter/Return parameter	V1X      Lin standard version 1.x V2X      Lin standard version 2.x BOTH      Both standards
Example	:BUS1:LIN:STANDARD? >BOTH Returns the LIN standard.


## 3-20. Mark Commands

---

3-20-1. :MARK .....	126
3-20-2. :MARK:CREATE .....	127
3-20-3. :MARK:DELEte .....	127

---

### 3-20-1. :MARK




---

Description	Move to next or previous event mark.
Syntax	:MARK { NEXT   PREVIOUS }
Related commands	:MARK:CREATE :MARK:DELEte
Parameter	NEXT      Move to next mark PREVIOUS      Move to previous mark

---

<b>Example</b>	:MARK NEXT Moves to the next event mark.
----------------	---

---


### 3-20-2. :MARK:CREATE

 Set →

<b>Description</b>	Creates a mark on the waveform at the current position or creates a mark for all the events for the current waveform.
<b>Syntax</b>	:MARK:CREATE { CURRent   ALL }
<b>Related commands</b>	:MARK :MARK:DELEte
<b>Parameter</b>	CURRent      Creates a mark at the current position ALL            Creates a mark for all the events.
<b>Example</b>	:MARK:CREATE CURRent Creates a mark at the current position.

---

### 3-20-3. :MARK:DELEte

 Set →

<b>Description</b>	Deletes the current mark or all the marks on a waveform.
<b>Syntax</b>	:MARK:DELEte { CURRent   ALL }
<b>Related commands</b>	:MARK :MARK:CREATE
<b>Parameter</b>	CURRent      Deletes the current mark ALL            Deletes all the marks.
<b>Example</b>	:MARK:DELEte CURRent Deletes the current mark.

### **3-21. Search Commands**

---

3-21-1. :SEARCH:COPY .....	129
3-21-2. :SEARCH:STATE .....	129
3-21-3. :SEARCH:TOTAL .....	129
3-21-4. :SEARCH:TRIGger:TYPE.....	130
3-21-5. :SEARCH:TRIGger:SOURce.....	130
3-21-6. :SEARCH:TRIGger:EDGE:SLOP .....	130
3-21-7. :SEARCH:TRIGger:LEVel .....	131
3-21-8. :SEARCH:TRIGger:HLEVel .....	131
3-21-9. :SEARCH:TRIGger:LLEVel .....	132
3-21-10. :SEARCH:TRIGger:PULSEWidth:POLarity .....	132
3-21-11. :SEARCH:TRIGger:RUNT:POLarity .....	132
3-21-12. :SEARCH:TRIGger:RISEFall:SLOP .....	133
3-21-13. :SEARCH:TRIGger:PULSe:WHEn .....	133
3-21-14. :SEARCH:TRIGger:PULSe:TIME .....	134
3-21-15. :SEARCH:TRIGger:RUNT:WHEn.....	134
3-21-16. :SEARCH:TRIGger:RUNT:TIME .....	134
3-21-17. :SEARCH:TRIGger:RISEFall:WHEn .....	135
3-21-18. :SEARCH:TRIGger:RISEFall:TIME.....	135
3-21-19. :SEARCH:TRIGger:BUS:TYPE .....	135
3-21-20. :SEARCH:TRIGger:BUS:B1:I2C:CONDITION.....	136
3-21-21. :SEARCH:TRIGger:BUS:B1:I2C:ADDRESS:MODE .....	136
3-21-22. :SEARCH:TRIGger:BUS:B1:I2C:ADDRESS:TYPE .....	137
3-21-23. :SEARCH:TRIGger:BUS:B1:I2C:ADDRESS:VALue.....	137
3-21-24. :SEARCH:TRIGger:BUS:B1:I2C:ADDRESS:DIRECTION.....	138
3-21-25. :SEARCH:TRIGger:BUS:B1:I2C:DATA:SIZE .....	138
3-21-26. :SEARCH:TRIGger:BUS:B1:I2C:DATA:VALue .....	139
3-21-27. :SEARCH:TRIGger:BUS:B1:UART:CONDITION.....	140
3-21-28. :SEARCH:TRIGger:BUS:B1:UART:RX:DATA:SIZE .....	140
3-21-29. :SEARCH:TRIGger:BUS:B1:UART:RX:DATA:VALue .....	141
3-21-30. :SEARCH:TRIGger:BUS:B1:UART:TX:DATA:SIZE..	141
3-21-31. :SEARCH:TRIGger:BUS:B1:UART:TX:DATA:VALue .....	142
3-21-32. :SEARCH:TRIGger:BUS:B1:SPI:CONDITION.....	142
3-21-33. :SEARCH:TRIGger:BUS:B1:SPI:DATA:SIZE .....	143
3-21-34. :SEARCH:TRIGger:BUS:B1:SPI:DATA:MISO:VALue .....	143
3-21-35. :SEARCH:TRIGger:BUS:B1:SPI:DATA:莫斯I:VALue .....	144
3-21-36. :SEARCH:TRIGger:BUS:B1:CAN:CONDITION .....	145
3-21-37. :SEARCH:TRIGger:BUS:B1:CAN:FRAMETYPE .....	145
3-21-38. :SEARCH:TRIGger:BUS:B1:CAN:IDentifier:MODE .....	146
3-21-39. :SEARCH:TRIGger:BUS:B1:CAN:IDentifier:VALue .....	146
3-21-40. :SEARCH:TRIGger:BUS:B1:CAN:IDentifier:DIRECTION .....	147
3-21-41. :SEARCH:TRIGger:BUS:B1:CAN:DATA:QUALifier .....	148
3-21-42. :SEARCH:TRIGger:BUS:B1:CAN:DATA:SIZE .....	148
3-21-43. :SEARCH:TRIGger:BUS:B1:CAN:DATA:VALue .....	149
3-21-44. :SEARCH:TRIGger:BUS:B1:LIN:CONDITION.....	150
3-21-45. :SEARCH:TRIGger:BUS:B1:LIN:DATA:QUALifier .....	151
3-21-46. :SEARCH:TRIGger:BUS:B1:LIN:DATA:SIZE .....	152
3-21-47. :SEARCH:TRIGger:BUS:B1:LIN:DATA:VALue .....	152
3-21-48. :SEARCH:TRIGger:BUS:B1:LIN:ERRTYPE .....	153
3-21-49. :SEARCH:TRIGger:BUS:B1:LIN:IDentifier:VALue .....	153
3-21-50. :SEARCH:FFTPeak:METHod.....	154
3-21-51. :SEARCH:FFTPeak:METHod:MPEak .....	154

## 3-21-1. :SEARCH:COPY

Description	Copies the search settings to the trigger settings or copies the trigger settings to the search settings.	
Syntax	:SEARCH:COPY {SEARCHtotrigger TRIGgertosearch}	
Parameter	SEARCHtotrigger	Copy the search setting to the trigger settings.
	TRIGgertosearch	Copy the trigger settings to the search settings.
Example	:SEARCH:COPY SEARCHtotrigger Copies the search settings to the trigger settings.	


## 3-21-2. :SEARCH:STATE

Description	Sets or queries whether the Search function is on or off.	
Syntax	:SEARCH:STATE { OFF   ON   ? }	
Parameter/ Return parameter	OFF	Turn the Search function on.
	ON	Turn the Search function off.
Example	:SEARCH:STATE ON Turn Search on.	

## 3-21-3. :SEARCH:TOTAL


Description	Returns the total number of events found from the search function.	
Syntax	:SEARCH:TOTAL?	
Parameter	<NR1> Number of events.	
Example	:SEARCH:TOTAL? 5	

### 3-21-4. :SEARCH:TRIGger:TYPE




Description	Sets or queries the search trigger type.	
Syntax	:SEARCH:TRIGger:TYPE { EDGE   PULSEWidth   RUNT   RISEFall   BUS   ? }	
Parameter/Return parameter	EDGE	Edge trigger
	PULSEWidth	Pulse width trigger
	RUNT	Runt trigger
	RISEFall	Rise and Fall trigger
	BUS	Bus trigger
Example	:SEARCH:TRIGger:TYPE EDGE Sets the search trigger to the edge type.	

### 3-21-5. :SEARCH:TRIGger:SOURce




Description	Sets or queries the search trigger source.	
Syntax	:SEARCH:TRIGger:SOURce {CH1   CH2   CH3   CH4   ? }	
Parameter/Return parameter	CH1 to CH4	Channel 1 to Channel 4
Example	:SEARCH:TRIGger:SOURce CH1 Sets the search trigger source as CH1.	

### 3-21-6. :SEARCH:TRIGger:EDGE:SLOP




Description	Sets or queries the search trigger slope.	
Syntax	:SEARCH:TRIGger:EDGE:SLOP { RISe   FALL   EITHER   ? }	
Related commands	:SEARCH:TRIGger:TYPE	
Parameter	RISe	Rising slope
	FALL	Falling slope
	EITHER	Either rising or falling slope
Return parameter	Returns the trigger slope.	
Example	:SEARCH:TRIGger:EDGE:SLOP FALL Sets the search trigger slope to falling.	

### 3-21-7. :SEARCH:TRIGger:LEVel




Description	Sets or queries the search trigger level.	
Syntax	:SEARCH:TRIGger:LEVel {TTL   ECL  SETTO50   <NRf>   ?}	
Related commands	:SEARCH:TRIGger:TYPE	
Parameter	<NRf>	Trigger level value
	TTL	Sets the search trigger level to TTL.
	ECL	Sets the search trigger level to ECL.
	SETTO50	Sets the search trigger level to the User level (50% by default).
Return parameter	<NR3>	Returns the trigger.
Example1	:SEARCH:TRIGger:LEVel TTL Sets the search trigger level to TTL.	
Example2	:SEARCH:TRIGger:LEVel 3.30E-1 Sets the search trigger level to 330mV/mA.	

### 3-21-8. :SEARCH:TRIGger:HLEVel




Description	Sets or queries the high level search trigger.	
Note	Applicable for Rise and Fall/Pulse Runt search triggers.	
Syntax	:SEARCH:TRIGger:HLEVel {TTL   ECL   <NRf>   ?}	
Related commands	:SEARCH:TRIGger:TYPE	
Parameter	<NRf>	High level value.
	TTL	Sets the high level search trigger to TTL.
	ECL	Sets the high level search trigger to ECL.
Return parameter	<NR3>	Returns the high level search trigger.
Example1	:SEARCH:TRIGger:HLEVel TTL Sets the high level search trigger to TTL	
Example2	:SEARCH:TRIGger:HLEVel 3.30E-1 Sets the high level search trigger to 330mV/mA.	

### 3-21-9. :SEARCH:TRIGger:LLEVel




Description	Sets or queries the low level search trigger.	
Note	Applicable for Rise and Fall/Pulse Runt triggers.	
Syntax	:SEARCH:TRIGger:LLEVel {TTL   ECL   <NRf>   ?}	
Related commands	:SEARCH:TRIGger:TYPe	
Parameter	<NRf>	Low level value.
	TTL	Sets the low trigger level to TTL.
	ECL	Sets the low trigger level to ECL.
Return parameter	<NR3>	Returns the low level.
Example	:SEARCH:TRIGger:LLEVel TTL Sets the low level search trigger to TTL.	
Example	:SEARCH:TRIGger:LLEVel -3.30E-3 Sets the low level search trigger to 330mV/mA.	

### 3-21-10. :SEARCH:TRIGger:PULSEWidth:POLarity




Description	Sets or queries the pulse width search trigger polarity.	
Syntax	:SEARCH:TRIGger:PULSEWidth:POLarity {POSitive   NEGative   ?}	
Related commands	:SEARCH:TRIGger:TYPe	
Parameter	POSitive	Positive polarity
	NEGative	Negative polarity
Return parameter	Returns the pulse width polarity.	
Example	:SEARCH:TRIGger:PULSEWidth:POLarity POSitive Sets the pulse width polarity to positive.	

### 3-21-11. :SEARCH:TRIGger:RUNT:POLarity




Description	Sets or queries the Pulse Runt search trigger polarity.	
Syntax	:SEARCH:TRIGger:RUNT:POLarity {POSitive   NEGative   EITHER   ?}	
Related commands	:SEARCH:TRIGger:TYPe	
Parameter	POSitive	Positive polarity
	NEGative	Negative polarity
	EITHER	Positive or negative polarity
Return parameter	Returns the pulse runt search trigger polarity.	
Example	:SEARCH:TRIGger:RUNT:POLarity POSitive Sets the Pulse Runt search trigger polarity to positive.	

### 3-21-12. :SEARCH:TRIGger:RISEFall:SLOP




Description	Sets or queries the slope of the Rise and Fall search trigger.	
Syntax	:SEARCH:TRIGger:RISEFall:SLOP { RISe   FALL   EITHER   ? }	
Related commands	:SEARCH:TRIGger:TYPE	
Parameter	RISe      Rising slope FALL     Falling slope EITHER   Either rising or falling slope	
Return parameter	Returns the rise & fall slope.	
Example	:SEARCH:TRIGger:RISEFall :SLOP RISe Sets the Rise & Fall search trigger slope to rising.	

### 3-21-13. :SEARCH:TRIGger:PULSe:WHEn




Description	Sets or queries the pulse width search trigger conditions.	
Syntax	:SEARCH:TRIGger:PULSe:WHEn { THAN   LESSthan   EQUAL   UNEQual   ? }	
Related commands	:SEARCH:TRIGger:TYPE :SEARCH:TRIGger:PULSe:TIME	
Parameter	THAN      > LESSthan   < EQUAL     = UNEQual   ≠	
Return parameter	Returns the pulse width search trigger conditions.	
Example	:SEARCH:TRIGger:PULSe:WHEn UNEQual Sets the pulse width search trigger conditions to not equal to (≠).	

### 3-21-14. :SEARCH:TRIGger:PULSe:TIME




Description	Sets or queries the pulse width search trigger time.	
Syntax	:SEARCH:TRIGger:PULSe:TIME {<NRf>   ?}	
Related commands	:SEARCH:TRIGger:TYPE :SEARCH:TRIGger:PULSe:WHEn	
Parameter	<NRf>	Pulse width time (4ns~10s)
Return parameter	<NR3>	Returns the pulse width time in seconds.
Example	:SEARCH:TRIGger:PULSe:TIME 4.00E-5	Sets the pulse width search trigger to 40.0us.

### 3-21-15. :SEARCH:TRIGger:RUNT:WHEn




Description	Sets or queries the pulse runt search trigger conditions.	
Syntax	:SEARCH:TRIGger:RUNT:WHEn {THAN   LESSthan   EQUAL   UNEQual   ? }	
Related commands	:SEARCH:TRIGger:TYPE :SEARCH:TRIGger:RUNT:TIME	
Parameter	THAN	>
	LESSthan	<
	Equal	=
	UNEQual	≠
Return parameter	Returns the pulse runt search trigger conditions.	
Example	:SEARCH:TRIGger:RUNT:WHEn UNEQual Sets the pulse runt search trigger condition to unequal (#).	

### 3-21-16. :SEARCH:TRIGger:RUNT:TIME




Description	Sets or queries the pulse runt search trigger time.	
Syntax	:SEARCH:TRIGger:RUNT:TIME {<NRf>   ? }	
Related commands	:SEARCH:TRIGger:TYPE :SEARCH:TRIGger:RUNT:WHEn	
Parameter	<NRf>	Pulse runt time (4nS to 10S)
Return Parameter	<NR3>	Returns the runt time in seconds.
Example	:SEARCH:TRIGger:RUNT:TIME 4.00E-5	Sets the pulse runt time to 40.0uS.

### 3-21-17. :SEARCH:TRIGger:RISEFall:WHEn



Description	Sets or queries the rise and fall search trigger conditions.
Syntax	:SEARCH:TRIGger:RISEFall:WHEn {THAN   LESSthan   EQUAL   UNEQual   ? }
Related commands	:SEARCH:TRIGger:TYPE :SEARCH:TRIGger:RISEFall:TIME
Parameter	THAN > LESSthan < EQUAL = UNEQual ≠
Return parameter	Returns the rise and fall search trigger condition.
Example	:SEARCH:TRIGger:RISEFall:WHEn UNEQual Sets the rise and fall search trigger condition to unequal (#).

### 3-21-18. :SEARCH:TRIGger:RISEFall:TIME




Description	Sets or queries the rise and fall time.
Syntax	:SEARCH:TRIGger:RISEFall:TIME {<NRf>   ? }
Related commands	:SEARCH:TRIGger:TYPE :SEARCH:TRIGger:RISEFall:WHEn
Parameter	<NRf> Rise and Fall time (4nS to 10S)
Return Parameter	<NR3> Returns the rise and fall time in seconds.
Example	:SEARCH:TRIGger:RISEFall:TIME 4.00E-5 Sets the trigger rise and fall time to 40.0us.

### 3-21-19. :SEARCH:TRIGger:BUS:TYPE




Description	Returns the current bus type.
Syntax	:SEARCH:TRIGger:BUS:TYPE?
Return parameter	I2C I2C mode SPI SPI mode UART UART mode CAN CAN mode LIN LIN mode
Example	:SEARCH:TRIGger:BUS:TYPE? UART

## 3-21-20. :SEARCH:TRIGger:BUS:B1:I2C:CONDition




Description	Sets or queries the I <sup>2</sup> C search trigger conditions.	
Syntax	:SEARCH:TRIGger:BUS:B1:I2C:CONDition {START   STOP   REPEATstart   ACKMISS   ADDRess   DATA   ADDRANDDATA   ? }	
Parameter	START	Set Start as the I <sup>2</sup> C search trigger condition.
	STOP	Set Stop as the I <sup>2</sup> C search trigger condition.
	REPEATstart	Set Repeat of Start as the I <sup>2</sup> C search trigger condition.
	ACKMISS	Set Missing Acknowledgement as the I <sup>2</sup> C search trigger condition.
	ADDRess	Set Address as the I <sup>2</sup> C search trigger condition.
	DATA	Set Data as the I <sup>2</sup> C search trigger condition.
	ADDRANDDATA	Set Address and Data as the I <sup>2</sup> C search trigger condition.
Return parameter	Returns the I <sup>2</sup> C bus search trigger condition.	
Example	:SEARCH:TRIGger:BUS:B1:I2C:CONDition ADDRess Set Address as the I <sup>2</sup> C search trigger condition.	

## 3-21-21. :SEARCH:TRIGger:BUS:B1:I2C:ADDRess:MODE




Description	Sets or queries the I <sup>2</sup> C addressing mode (7 or 10 bits) for the search trigger.	
Syntax	:SEARCH:TRIGger:BUS:B1:I2C:ADDRess:MODE {ADDR7   ADDR10   ? }	
Related commands	:SEARCH:TRIGger:BUS:B1:I2C:CONDition	
Parameter	ADDR7	7 bit addressing
	ADDR10	10 bit addressing
Return Parameter	0	7 bit addressing
	1	10 bit addressing
Example	:SEARCH:TRIGger:BUS:B1:I2C:ADDRess:MODE?	0
	The addressing mode is current set to 7 bits.	

### 3-21-22. :SEARCH:TRIGger:BUS:B1:I2C:ADDRess:TYPe




Description	Sets the I <sup>2</sup> C bus address type, or queries what the setting is for the search trigger.	
Syntax	:SEARCH:TRIGger:BUS:B1:I2C:ADDRess:TYPe {GENeralcall   STARtbyte   HSmode   EEPROM   CBUS   ?}	
Related commands	:SEARCH:TRIGger:BUS:B1:I2C:CONDition	
Parameter	GENeralcall STARtbyte HSmode EEPROM CBUS	Set a general call address (0000 000 0). Set a start byte address. (0000 000 1) Set a high-speed mode address. (0000 1xx x) Set an EEPROM address. (1010 xxx x) Set a CBUS address. (0000 001 x)
Return Parameter	Returns the address type	
Example	:SEARCH:TRIGger:BUS:B1:I2C:ADDRess:TYPe? CBUS	

### 3-21-23. :SEARCH:TRIGger:BUS:B1:I2C:ADDRess:VALue




Description	Sets or queries the I <sup>2</sup> C bus address value when the I <sup>2</sup> C search trigger is set to trigger on Address or Address/Data.	
Syntax	:SEARCH:TRIGger:BUS:B1:I2C:ADDRess:VALue {string   ? }	
Related commands	:SEARCH:TRIGger:BUS:B1:I2C:ADDRess:MODe	
Parameter	<string>	7/10 characters, must be enclosed in double quotes "string". x = don't care 1 = binary 1 0 = binary 0
Return Parameter	Returns the address value in binary.	
Example1	:SEARCH:TRIGger:BUS:B1:I2C:ADDRess:MODe ADDR7 :SEARCH:TRIGger:BUS:B1:I2C:ADDRess:VALue "xxx0101" Sets the address to XXX0101	
Example 2	:SEARCH:TRIGger:BUS:B1:I2C:ADDRess:VALue? XXX0101	

## 3-21-24. :SEARCH:TRIGger:BUS:B1:I2C:ADDRess:DIRECTION




Description	Sets or queries the address bit as read write or don't care for the search function.	
Note	This setting only applies when the I <sup>2</sup> C search trigger is set to trigger on Address or Address/Data	
Syntax	:SEARCH:TRIGger:BUS:B1:I2C:ADDRess:DIRECTION { READ   WRITE   NOCARE   ? }	
Related commands	:SEARCH:TRIGger:BUS:B1:I2C:CONDition	
Parameter	READ      Set read as the data direction. WRITE     Set write as the data direction. NOCARE    Set either as the data direction.	
Return Parameter	Returns the direction (READ, WRITE, NOCARE).	
Example	:SEARCH:TRIGger:BUS:B1:I2C:ADDRess:DIRECTION READ Sets the direction to READ.	

## 3-21-25. :SEARCH:TRIGger:BUS:B1:I2C:DATA:SIZE




Description	Sets or queries the data size in bytes for the I <sup>2</sup> C bus.	
Note	This setting only applies when the I <sup>2</sup> C search trigger is set to trigger on Data or Address/Data	
Syntax	:SEARCH:TRIGger:BUS:B1:I2C:DATA:SIZE {<NR1>   ? }	
Related commands	:SEARCH:TRIGger:BUS:B1:I2C:CONDition	
Parameter	<NR1>      Number of data bytes (1 to 5).	
Return parameter	<NR1>      Returns the number of bytes.	
Example	:SEARCH:TRIGger:BUS:B1:I2C:DATA:SIZE 3 Sets the number of bytes to 3.	

### 3-21-26. :SEARCH:TRIGger:BUS:B1:I2C:DATa:VALue




Description	Sets or queries the triggering data value for the I <sup>2</sup> C bus when the I <sup>2</sup> C search trigger is set to trigger on Data or Address/Data.	
Syntax	:SEARCH:TRIGger:BUS:B1:I2C:DATa:VALue {string   ? }	
Related commands	:SEARCH:TRIGger:BUS:B1:I2C:DATa:SIZE	
Parameter	<string>	The number of characters in the string depends on the data size setting. The string must be enclosed in double quotes, "string". x = don't care 1 = binary 1 0 = binary 0
Return Parameter	Returns the data value.	
Example1	<pre>:SEARCH:TRIGger:BUS:B1:I2C:DATa:SIZE 1 :SEARCH:TRIGger:BUS:B1:I2C:DATa:VALue "1x1x0101"</pre> <p>Sets the value to XXX0101</p>	
Example 2	<pre>:SEARCH:TRIGger:BUS:B1:I2C:DATa:VALue? 1X1X0101</pre>	

### 3-21-27. :SEARCH:TRIGger:BUS:B1:UART:CONDition




Description	Sets or queries the UART search triggering condition.		
Syntax	:SEARCH:TRIGger:BUS:B1:UART:CONDition { RXSTArt   RXDATA   RXENDPacket   TXSTArt   TXDATA   TXENDPacket   TXPARItyerr   RXPARItyerr   ? }		
Parameter	RXSTArt	Set search trigger on the RX Start Bit.	
	RXDATA	Set search trigger on RX Data.	
	RXENDPacket	Set search trigger on the RX End of Packet condition.	
	RXPARItyerr	Set search trigger on RX Parity error condition.	
	TXSTArt	Set search trigger on the TX Start Bit.	
	TXDATA	Set search trigger on TX Data.	
	TXENDPacket	Set search trigger on the TX End of Packet condition.	
	TXPARItyerr	Set search trigger on TX Parity error condition.	
Return Parameter	Returns the search triggering condition.		
Example	:SEARCH:TRIGger:BUS:B1:UART:CONDition TXDATA Sets the UART bus to trigger on Tx Data for the search function.		

### 3-21-28. :SEARCH:TRIGger:BUS:B1:UART:RX:DATa:SIZE




Description	Sets or queries the number of bytes for UART data.		
Note	This setting only applies when the UART search trigger is set to trigger on Rx Data		
Syntax	:SEARCH:TRIGger:BUS:B1:UART:RX:DATa:SIZE {<NR1>   ?}		
Related commands	:SEARCH:TRIGger:BUS:B1:UART:CONDition		
Parameter	<NR1>	Number of bytes (1 to 10).	
Return parameter	<NR1>	Returns the number of bytes.	
Example	:SEARCH:TRIGger:BUS:B1:UART:RX:DATa:SIZE 5 Sets the number of bytes to 5.		

### 3-21-29. :SEARCH:TRIGger:BUS:B1:UART:RX:DATa:VALue




Description	Sets or queries the search triggering data value for the UART bus when the bus is set to trigger on Rx Data.
Syntax	:SEARCH:TRIGger:BUS:B1:UART:RX:DATa:VALue {string   ? }
Related commands	:SEARCH:TRIGger:BUS:B1:UART:RX:DATa:SIZE
Parameter	<p>&lt;string&gt;</p> <p>The number of characters in the string depends on the data size setting. The string must be enclosed in double quotes, "string".</p> <p>x = don't care</p> <p>1 = binary 1</p> <p>0 = binary 0</p>
Return Parameter	Returns the data value.
Example1	<pre>:SEARCH:TRIGger:BUS:B1:UART:CONDition RXDATA :SEARCH:TRIGger:BUS:B1:UART:RX:DATa:SIZE 1 :SEARCH:TRIGger:BUS:B1:UART:RX:DATa:VALue "1x1x0101"</pre> <p>Sets the value to 1x1x0101</p>
Example 2	<pre>:SEARCH:TRIGger:BUS:B1:UART:RX:DATa:VALue? 1X1X0101</pre>

### 3-21-30. :SEARCH:TRIGger:BUS:B1:UART:TX:DATa:SIze




Description	Sets or queries the number of bytes for UART data.
Note	This setting only applies when the UART search trigger is set to trigger on Tx Data
Syntax	:SEARCH:TRIGger:BUS:B1:UART:TX:DATa:SIZE {<NR1>   ? }
Related commands	:SEARCH:TRIGger:BUS:B1:UART:CONDition
Parameter	<NR1> Number of bytes (1 to 10).
Return parameter	<NR1> Returns the number of bytes.
Example	<pre>:SEARCH:TRIGger:BUS:B1:UART:TX:DATa:SIZE 5</pre> <p>Sets the number of bytes to 5.</p>

### 3-21-31. :SEARCH:TRIGger:BUS:B1:UART:TX:DATa:VALue




Description	Sets or queries the search triggering data value for the UART bus when the bus is set to trigger on Tx Data.
Syntax	:SEARCH:TRIGger:BUS:B1:UART:TX:DATa:VALue {string   ? }
Related commands	:SEARCH:TRIGger:BUS:B1:UART:TX:DATa:SIZE
Parameter	<p>&lt;string&gt;</p> <p>The number of characters in the string depends on the data size setting. The string must be enclosed in double quotes, "string".</p> <p>x = don't care</p> <p>1 = binary 1</p> <p>0 = binary 0</p>
Return Parameter	Returns the data value.
Example1	<pre>:SEARCH:TRIGger:BUS:B1:UART:CONDition TXDATA :SEARCH:TRIGger:BUS:B1:UART:TX:DATa:SIZE 1 :SEARCH:TRIGger:BUS:B1:UART:TX:DATa:VALue "1x1x0101" Sets the value to 1x1x0101</pre>
Example 2	<pre>:SEARCH:TRIGger:BUS:B1:UART:TX:DATa:VALue? 1X1X0101</pre>

### 3-21-32. :SEARCH:TRIGger:BUS:B1:SPI:CONDition




Description	Sets or queries the SPI search triggering condition.
Syntax	:SEARCH:TRIGger:BUS:B1:SPI:CONDition {SS   MISO   MOSI   MISOMOSI   ? }
Parameter	<p>SS</p> <p>Set to trigger on the Slave Selection condition.</p> <p>MISO</p> <p>Set to trigger on the Master-In Slave-Out condition.</p> <p>MOSI</p> <p>Set to trigger on the Master-Out Slave-In condition.</p> <p>MISOMOSI</p> <p>Set to trigger on the Master-In Slave-Out and Master-Out Slave-In conditions.</p>
Return Parameter	Returns the triggering condition.
Example	<pre>:SEARCH:TRIGger:BUS:B1:SPI:CONDition MISO Sets the SPI bus to trigger on MISO.</pre>

## 3-21-33. :SEARCH:TRIGger:BUS:B1:SPI:DATA:SIZE



Description	Sets or queries the number of words for SPI data for the search function.
Note	This setting only applies when the SPI search trigger is set to trigger on MISO, MOSI or MISO/MOSI
Syntax	:SEARCH:TRIGger:BUS:B1:SPI:DATA:SIZE {<NR1>   ?}
Related commands	:SEARCH:TRIGger:BUS:B1:SPI:CONDition
Parameter	<NR1> Number of words (1 to 32).
Return parameter	<NR1> Returns the number of words.
Example	:SEARCH:TRIGger:BUS:B1:SPI:DATA:SIZE 10 Sets the number of words to 10.

## 3-21-34. :SEARCH:TRIGger:BUS:B1:SPI:DATA:MISO:VALue




Description	Sets or queries the search triggering data value for the SPI bus when the bus is set to trigger on MISO or MISO/MOSI.
Syntax	:SEARCH:TRIGger:BUS:B1:SPI:DATA:MISO:VALue {string   ? }
Related commands	:SEARCH:TRIGger:BUS:B1:SPI:DATA:SIZE
Parameter	<string> The number of characters in the string depends on the data size setting. The string must be enclosed in double quotes, "string". x = don't care 1 = binary 1 0 = binary 0
Return Parameter	Returns the data value.
Example1	:SEARCH:TRIGger:BUS:B1:SPI:CONDition MISO :SEARCH:TRIGger:BUS:B1:SPI:DATA:SIZE 2 :SEARCH:TRIGger:BUS:B1:SPI:DATA:MISO:VALue "1x1x0101" Sets the value to 1x1x0101
Example 2	:SEARCH:TRIGger:BUS:B1:SPI:DATA:MISO:VALue? 1X1X0101

## 3-21-35. :SEARCH:TRIGger:BUS:B1:SPI:DATa:MOSI:VALue


Description	Sets or queries the search triggering data value for the SPI bus when the bus is set to trigger on MOSI or MISO/MOSI.
Syntax	:SEARCH:TRIGger:BUS:B1:SPI:DATa:MOSI:VALue {string   ? }
Related commands	:SEARCH:TRIGger:BUS:B1:SPI:DATa:SIZE
Parameter	<p>&lt;string&gt;</p> <p>The number of characters in the string depends on the data size setting. The string must be enclosed in double quotes, "string".</p> <p>x = don't care 1 = binary 1 0 = binary 0</p>
Return Parameter	Returns the data value.
Example1	<pre>:SEARCH:TRIGger:BUS:B1:SPI:CONDition MOSI :SEARCH:TRIGger:BUS:B1:SPI:DATa:SIZE 2 :SEARCH:TRIGger:BUS:B1:SPI:DATa:MOSI:VALue "1x1x0101"</pre> <p>Sets the value to 1x1x0101</p>
Example2	<pre>:SEARCH:TRIGger:BUS:B1:SPI:DATa:MOSI:VALue? 1X1X0101</pre>

### 3-21-36. :SEARCH:TRIGger:BUS:B1:CAN:CONDition




Description	Sets or returns the CAN search trigger condition.	
Syntax	<code>:SEARCH:TRIGger:BUS:B1:CAN:CONDition</code> <code>{SOF FRAMETYPE IDentifier DATA IDANDDATA EOF ACKMISS STUFFERR ?}</code>	
Parameter/ Return parameter	SOF FRAMETYPE Identifier  DATA IDANDDATA  EOF ACKMISS  STUFFERR	Sets search to trigger on a start of frame Sets search to trigger on the type of frame Sets search to trigger on a matching identifier  Sets search to trigger on matching data Sets search to trigger on matching identifier and data field  Sets search to trigger on the end of frame Sets search to trigger on a missing acknowledge  Sets search to trigger on a bit stuffing error
Example1	<code>:SEARCH:TRIGger:BUS:B1:CAN:CONDition SOF</code> Triggers search on a start of frame.	
Example2	<code>:SEARCH:TRIGger:BUS:B1:CAN:CONDition?</code> <code>&gt;SOF</code>	

### 3-21-37. :SEARCH:TRIGger:BUS:B1:CAN:FRAMETYPE




Description	Sets or returns the frame type for the CAN FRAMETYPE search trigger.	
Syntax	<code>:SEARCH:TRIGger:BUS:B1:CAN:FRAMETYPE</code> <code>{DATA REMote ERRor OVERLoad ?}</code>	
Parameter/ Return parameter	DATA REMote ERRor OVERLoad	Sets the frame type to data frame Sets the frame type to remote frame Sets the frame type to error frame Sets the frame type to overload
Example	<code>:SEARCH:TRIGger:BUS:B1:CAN:FRAMETYPE DATA</code> Sets the frame type to DATA.	

## 3-21-38. :SEARCH:TRIGger:BUS:B1:CAN:IDentifier:MODe



Description	Sets or returns the CAN addressing mode for the bus.	
Syntax	:SEARCH:TRIGger:BUS:B1:CAN:IDentifier:MODe {STANDARD EXTended ?}	
Parameter/ Return parameter	STANDARD	Standard addressing mode
	EXTended	Extended addressing mode
Example	<pre>:SEARCH:TRIGger:BUS:B1:CAN:IDentifier:MODe? &gt;STANDARD :SEARCH:TRIGger:BUS:B1:CAN:IDentifier:MODe EXTENDED :SEARCH:TRIGger:BUS:B1:CAN:IDentifier:MODe? &gt;EXTENDED</pre>	

## 3-21-39. :SEARCH:TRIGger:BUS:B1:CAN:IDentifier:VALUe



Description	Sets or returns the binary address string used for the CAN search trigger. Note: Only applicable when the search trigger condition is set to ID or IDANDDATA.	
Syntax	:SEARCH:TRIGger:BUS:B1:CAN:IDentifier:VALUe {<string> ?}	
Related Commands	:SEARCH:TRIGger:BUS:B1:CAN:IDentifier:MODe	
Parameter/ Return parameter	<string>	The size of the string depends on the data size setting. The string must be enclosed in double quotes, "string". String contents: x = don't care 1 = binary 1 0 = binary 0
Example	<pre>:SEARCH:TRIGger:BUS:B1:CAN:CONDition ID :SEARCH:TRIGger:BUS:B1:CAN:IDentifier:MODe STANDARD :SEARCH:TRIGger:BUS:B1:CAN:IDentifier:VALUe "01100X1X01X" :SEARCH:TRIGger:BUS:B1:CAN:IDentifier:VALUe? &gt;01100X1X01X</pre>	


3-21-40. :SEARCH:TRIGger:BUS:B1:CAN:IDentifier:DIRection

Set →

→ Query


Description	Sets or queries the address bit as read, write or don't care.	
Syntax	:SEARCH:TRIGger:BUS:B1:CAN:IDentifier:DIRection {READ WRITE NOCARE ?}	
Parameter/ Return parameter	READ	Sets read as the data direction
	WRITE	Sets write as the data direction
	NOCARE	Sets either as the data direction
Example2	:SEARCH:TRIGger:BUS:B1:CAN:IDentifier:DIRection? >WRITE :SEARCH:TRIGger:BUS:B1:CAN:IDentifier:DIRection READ :SEARCH:TRIGger:BUS:B1:CAN:IDentifier:DIRection?> READ	

### 3-21-41. :SEARCH:TRIGger:BUS:B1:CAN:DATA:QUALifier




Description	Sets or returns the CAN data qualifier. Note: Only applicable when the search triggering condition is set to DATA or IDANDDATA.					
Syntax	:SEARCH:TRIGger:BUS:B1:CAN:DATA:QUALifier {LESSthan THAN EQUAL UNEQual LESSEQual MOREEqual ?}					
Parameter/ Return parameter	LESSthan	Sets search to trigger when the data is less than the qualifier value.	THAN	Sets search to trigger when the data is greater than the qualifier value.	EQUAL	Sets search to trigger when the data is equal to the qualifier value.
	UNEQual	Sets search to trigger when the data is not equal to the qualifier value.	LESSEQual	Sets search to trigger when the data is less than or equal to the qualifier value.	MOREEqual	Sets search to trigger when the data is more than or equal to the qualifier value.
Example	<pre>:SEARCH:TRIGger:BUS:B1:CAN:DATA:QUALifier? &gt;EQUAL :SEARCH:TRIGger:BUS:B1:CAN:DATA:QUALifier THAN :SEARCH:TRIGger:BUS:B1:CAN:DATA:QUALifier? &gt;THAN</pre>					

### 3-21-42. :SEARCH:TRIGger:BUS:B1:CAN:DATA:SIZE




Description	Sets or returns the length of the data string in bytes for the CAN search trigger. Note: Only applicable when the condition is set to DATA or IDANDDATA.					
Syntax	:SEARCH:TRIGger:BUS:B1:CAN:DATA:SIZE {<NR1> ?}					
Parameter/ Return parameter	<NR1>	1~8 (bytes)				
Example	<pre>:SEARCH:TRIGger:BUS:B1:CAN:DATA:SIZE? &gt;1 :SEARCH:TRIGger:BUS:B1:CAN:DATA:SIZE 2 :SEARCH:TRIGger:BUS:B1:CAN:DATA:SIZE? &gt;2</pre>					

3-21-43. :SEARCH:TRIGger:BUS:B1:CAN:DATA:VALue




Description	Sets or returns the binary data string to be used for the CAN search trigger. Note: Only applicable when the condition is set to DATA or IDANDDATA.
Related Commands	:SEARCH:TRIGger:BUS:B1:CAN:DATA:SIZE
Syntax	:SEARCH:TRIGger:BUS:B1:CAN:DATA:VALue {<string>}?{}
Parameter/ Return parameter	<string> The size of the string depends on the data size setting. The string must be enclosed in double quotes, "string". String contents: x = don't care 1 = binary 1 0 = binary 0
Example	:SEARCH:TRIGger:BUS:B1:CAN:DATA:SIZE 1 :SEARCH:TRIGger:BUS:B1:CAN:DATA:VALue "01010X1X" :SEARCH:TRIGger:BUS:B1:CAN:DATA:VALue? >01010X1X

## 3-21-44. :SEARCH:TRIGger:BUS:B1:LIN:CONDition




Description	Sets or returns the LIN search trigger condition.						
Syntax	<code>:SEARCH:TRIGger:BUS:B1:LIN:CONDition</code> <code>{SYNCField IDentifier DATA IDANDDATA WAKEUp SLEEP ERRor ?}</code>						
Parameter/ Return parameter	SYNCField      Sets the LIN search trigger condition to the sync field. IDentifier      Sets the LIN search trigger condition to identifier field. DATA      Sets the LIN search trigger condition to the data field. IDANDDATA      Sets the LIN search trigger condition to identifier and data field WAKEUp      Sets the LIN search trigger condition to wake up. SLEEP      Sets the LIN search trigger condition to sleep. ERRor      Sets the LIN search trigger condition to error.						
Example	<code>:SEARCH:TRIGger:BUS:B1:LIN:CONDition?</code> <code>&gt;IDANDDATA</code> <code>:SEARCH:TRIGger:BUS:B1:LIN:CONDition DATA</code> <code>:SEARCH:TRIGger:BUS:B1:LIN:CONDition?</code> <code>&gt;DATA</code>						

## 3-21-45. :SEARCH:TRIGger:BUS:B1:LIN:DATA:QUALifier



Description	Sets or returns the LIN data qualifier. Note: Only applicable when the search trigger condition is set to DATA or IDANDDATA.														
Syntax	:SEARCH:TRIGger:BUS:B1:LIN:DATA:QUALifier {LESSthan THAN EQUAL UNEQual LESSEQual MOREEqual ?}														
Parameter/ Return parameter	<table> <tr> <td>LESSthan</td><td>Sets search to trigger when the data is less than the qualifier value.</td></tr> <tr> <td>THAN</td><td>Sets search to trigger when the data is greater than the qualifier value.</td></tr> <tr> <td>EQUAL</td><td>Sets search to trigger when the data is equal to the qualifier value.</td></tr> <tr> <td>UNEQual</td><td>Sets search to trigger when the data is not equal to the qualifier value.</td></tr> <tr> <td>LESSEQual</td><td>Sets search to trigger when the data is less than or equal to the qualifier value.</td></tr> <tr> <td>MOREEqual</td><td>Sets search to trigger when the data is more than or equal to the qualifier value.</td></tr> <tr> <td>LESSthan</td><td>Sets search to trigger when the data is less than the qualifier value.</td></tr> </table>	LESSthan	Sets search to trigger when the data is less than the qualifier value.	THAN	Sets search to trigger when the data is greater than the qualifier value.	EQUAL	Sets search to trigger when the data is equal to the qualifier value.	UNEQual	Sets search to trigger when the data is not equal to the qualifier value.	LESSEQual	Sets search to trigger when the data is less than or equal to the qualifier value.	MOREEqual	Sets search to trigger when the data is more than or equal to the qualifier value.	LESSthan	Sets search to trigger when the data is less than the qualifier value.
LESSthan	Sets search to trigger when the data is less than the qualifier value.														
THAN	Sets search to trigger when the data is greater than the qualifier value.														
EQUAL	Sets search to trigger when the data is equal to the qualifier value.														
UNEQual	Sets search to trigger when the data is not equal to the qualifier value.														
LESSEQual	Sets search to trigger when the data is less than or equal to the qualifier value.														
MOREEqual	Sets search to trigger when the data is more than or equal to the qualifier value.														
LESSthan	Sets search to trigger when the data is less than the qualifier value.														
Example	<pre>:SEARCH:TRIGger:BUS:B1:LIN:DATA:QUALifier? &gt;EQUAL :SEARCH:TRIGger:BUS:B1:LIN:DATA:QUALifier THAN :SEARCH:TRIGger:BUS:B1:LIN:DATA:QUALifier? &gt;THAN</pre>														

### 3-21-46. :SEARCH:TRIGger:BUS:B1:LIN:DATa:SIZE




Description	Sets or returns the length of the data string in bytes for the LIN search trigger.  Note: Only applicable when the condition is set to DATA or IDANDDATA.
Syntax	:SEARCH:TRIGger:BUS:B1:LIN:DATa:SIZE {<NR1> ?}
Parameter/ Return parameter	<NR1> 1~8 (bytes)

Example

```
:SEARCH:TRIGger:BUS:B1:LIN:DATa:SIZE?  
>1  
:SEARCH:TRIGger:BUS:B1:LIN:DATa:SIZE 2  
:SEARCH:TRIGger:BUS:B1:LIN:DATa:SIZE?  
>2
```

### 3-21-47. :SEARCH:TRIGger:BUS:B1:LIN:DATa:VALue




Description	Sets or returns the binary data string to be used for the LIN search trigger.  Note: Only applicable when the condition is set to DATA or IDANDDATA.
Related Commands	:SEARCH:TRIGger:BUS:B1:LIN:DATa:SIZE
Syntax	:SEARCH:TRIGger:BUS:B1:LIN:DATa:VALue {<string> ?}
Parameter/ Return parameter	<string> The size of the string depends on the data size setting. The string must be enclosed in double quotes, "string".  String contents: x = don't care 1 = binary 1 0 = binary 0

Example


```
:SEARCH:TRIGger:BUS:B1:LIN:DATa:SIZE 1  
:SEARCH:TRIGger:BUS:B1:LIN:DATa:VALue  
"01010X1X"  
:SEARCH:TRIGger:BUS:B1:LIN:DATa:VALue?  
>01010X1X
```

## 3-21-48. :SEARCH:TRIGger:BUS:B1:LIN:ERRTYPE




Description	Sets or returns the error type be used for the LIN search trigger.
Syntax	:SEARCH:TRIGger:BUS:B1:LIN:ERRTYPE {SYNC PARIty CHECKsum ?}
Parameter/ Return parameter	SYNC Sets the LIN error type to SYNC. PARIty Sets the LIN error type to parity. CHECKsum Sets the LIN error type to checksum.
Example	:SEARCH:TRIGger:BUS:B1:LIN:ERRTYPE? >SYNC :SEARCH:TRIGger:BUS:B1:LIN:ERRTYPE CHECKSUM :SEARCH:TRIGger:BUS:B1:LIN:ERRTYPE? >CHECKSUM

## 3-21-49. :SEARCH:TRIGger:BUS:B1:LIN:IDentifier:VALue




Description	Sets or returns the binary address string to be used for the LIN search trigger.  Note: Only applicable when the condition is set to DATA or IDANDDATA.
Syntax	:SEARCH:TRIGger:BUS:B1:LIN:IDentifier:VALue {<string> ?}
Parameter/ Return parameter	<string> The size of the string depends on the data size setting. The string must be enclosed in double quotes, "string". String contents: x = don't care 1 = binary 1 0 = binary 0
Example	:SEARCH:TRIGger:BUS:B1:LIN:CONDITION ID :SEARCH:TRIGger:BUS:B1:LIN:IDentifier:VALue "00X1X01X" :SEARCH:TRIGger:BUS:B1:LIN:IDentifier:VALue? >01100X1X01X

## 3-21-50. :SEARCH:FFTPeak:METHod




Description	Sets or returns the FFT peak method type.	
Related Commands	:SEARCH:TRIGger:TYPe :SEARCH:FFTPeak:METHod:MPEak :SEARCH:TRIGger:LEVel	
Syntax	:SEARCH:FFTPeak:METHod {MPEak   LEVel   ?}	
Parameter/ Return parameter	MPEak	Sets the peak method to the Max Peak type. LEVel
Example	:SEARCH:FFTPeak:METHod LEVel :SEARCH:FFTPeak:METHod? >LEVEL :SEARCH:TRIGger:LEVel? >1.000E+00 :SEARCH:TRIGger:LEVel 2 :SEARCH:TRIGger:LEVel? >2.000E+00	

## 3-21-51. :SEARCH:FFTPeak:METHod:MPEak



Description	Sets the active peak number (1 ~ 10) or return the frequency of the active peak number.	
Related Commands	:SEARCH:TRIGger:TYPe :SEARCH:FFTPeak:METHod	
Syntax	:SEARCH:FFTPeak:METHod:MPEak {<NR1>   ?}	
Parameter	<NR1>	Active peak number.
Return parameter	<NR3>	Frequency of the active peak.
Example	:SEARCH:FFTPeak:METHod MPEak :SEARCH:FFTPeak:METHod? >MPEAK :SEARCH:FFTPeak:METHod:MPEak? >1.000E+00 :SEARCH:FFTPeak:METHod:MPEak 2 :SEARCH:FFTPeak:METHod:MPEak? >2.000E+00	

### 3-21-52. :SEARCH:FFTPeak:SINFO




Description	Sets or returns the State Info to "Mark" or "Peak".	
Related Commands	:SEARCH:TRIGger:TYPE	
Syntax	:SEARCH:FFTPeak:SINFO {MARK   PEAK   ?}	
Parameter/ Return parameter	MARK	Sets the State Info to Mark.
	PEAK	Sets the State Info to Peak.
Example	<pre>:SEARCH:FFTPeak:SINFO? &gt;PEAK :SEARCH:FFTPeak:SINFO mark :SEARCH:FFTPeak:SINFO? &gt;MARK</pre>	

## 3-22. Label Commands


3-22-1. :CHANnel<X>:LABEL .....	155
3-22-2. :CHANnel<X>:LABEL:DISPLAY .....	156
3-22-3. :REF<X>:LABEL.....	156
3-22-4. :REF<X>:LABEL:DISPLAY .....	157
3-22-5. :BUS1:LABEL .....	157
3-22-6. :BUS1:LABEL:DISPLAY .....	158
3-22-7. :SET<X>:LABEL.....	158

### 3-22-1. :CHANnel<X>:LABEL




Description	Sets or returns the file label for the selected channel.	
Syntax	:CHANnel<X>:LABEL {<string>   ?}	
Related commands	:CHANnel<X>:LABEL:DISPLAY	
Parameter	<X>	Channel 1, ,2, 3, 4
	<string>	The string must be no more than 8 characters and only contain alphanumeric characters in addition to period, dash and underscore characters. The string must be enclosed in double quotes, "string".
Return parameter	<string>	Returns the label for the selected channel. No return indicates that there has not been a file label assigned for the selected channel.
Example1	<pre>:CHANnel1:LABEL "CH1_lab" Sets the channel 1 label as "CH1_lab".</pre>	
Example2	<pre>:CHANnel1:LABEL? CH1_lab</pre>	

### 3-22-2. :CHANnel<X>:LABel:DISPlay




Description	Turns the label on/off for the selected channel or returns its status.						
Syntax	:CHANnel<X>:LABel:DISPlay { OFF   ON   ? }						
Related commands	:CHANnel<X>:LABel						
Parameter	<table border="0"> <tr> <td>&lt;X&gt;</td> <td>Channel 1, 2, 3, 4</td> </tr> <tr> <td>OFF</td> <td>Turns the file label off for the selected channel.</td> </tr> <tr> <td>ON</td> <td>Turns the file label on for the selected channel.</td> </tr> </table>	<X>	Channel 1, 2, 3, 4	OFF	Turns the file label off for the selected channel.	ON	Turns the file label on for the selected channel.
<X>	Channel 1, 2, 3, 4						
OFF	Turns the file label off for the selected channel.						
ON	Turns the file label on for the selected channel.						
Return parameter	Returns the status of the file label for the selected channel (ON, OFF).						
Example	<pre> :CHANnel1:LABel "CH1" :CHANnel1:LABel:DISPlay ON :CHANnel1:LABel:DISPlay? ON Sets the channel 1 label to "CH1" and then turns the label display on. The query return shows that the label is on.   </pre>						

### 3-22-3. :REF<X>:LABel




Description	Sets or returns the file label for the selected reference waveform.				
Syntax	:REF<X>:LABEL {<string>   ?}				
Related commands	:REF<X>:LABEL:DISPLAY				
Parameter	<table border="0"> <tr> <td>&lt;X&gt;</td> <td>REF 1, 2, 3, 4</td> </tr> <tr> <td>&lt;string&gt;</td> <td>The string must be no more than 8 characters and only contain alphanumeric characters in addition to period, dash and underscore characters. The string must be enclosed in double quotes, "string".</td> </tr> </table>	<X>	REF 1, 2, 3, 4	<string>	The string must be no more than 8 characters and only contain alphanumeric characters in addition to period, dash and underscore characters. The string must be enclosed in double quotes, "string".
<X>	REF 1, 2, 3, 4				
<string>	The string must be no more than 8 characters and only contain alphanumeric characters in addition to period, dash and underscore characters. The string must be enclosed in double quotes, "string".				
Return parameter	<string> Returns the label for the selected reference waveform. No return indicates that there has not been a file label assigned for the selected reference waveform.				
Example1	<pre> :REF1:LABel "REF1_lab" Sets the REF1 label as "REF1_lab".   </pre>				
Example2	<pre> :REF1:LABel? REF1_lab   </pre>				

### 3-22-4. :REF<X>:LABEL:DISPLAY




Description	Turns the label on/off for the selected reference waveform or returns its status.	
Syntax	:REF<X>:LABEL:DISPLAY { OFF   ON   ? }	
Related commands	:REF<X>:LABEL	
Parameter	<X>	Reference waveform 1, 2, 3, 4
	OFF	Turns the file label off for the selected reference waveform.
	ON	Turns the file label on for the selected reference waveform.
Return parameter	Returns the status of the file label for the selected reference waveform (ON, OFF).	
Example	<pre>:REF1:LABEL "REF1" :REF1:LABEL:DISPLAY ON :REF1:LABEL:DISPLAY? ON</pre> <p>Sets the label for reference waveform 1 to "REF1" and then turns the label display on. The query return shows that the label is on.</p>	

### 3-22-5. :BUS1:LABEL




Description	Sets or returns the file label for the bus.	
Syntax	:BUS1:LABEL {<string>   ?}	
Related commands	:BUS1:LABEL:DISPLAY	
Parameter	<string>	The string must be no more than 8 characters and only contain alphanumeric characters in addition to period, dash and underscore characters. The string must be enclosed in double quotes, "string".
Return parameter	<string>	Returns the label for the bus. No return indicates that there has not been a file label assigned for bus.
Example1	<pre>:BUS1:LABEL "Bus" Sets the bus label as "Bus".</pre>	
Example2	<pre>:BUS1:LABEL? Bus</pre>	

### 3-22-6. :BUS1:LABEL:DISPLAY



Description	Turns the label on/off for the bus or returns its status.	
Syntax	:BUS1:LABEL:DISPLAY { OFF   ON   ? }	
Related commands	:BUS1:LABEL	
Parameter	OFF	Turns the file label off for the bus.
	ON	Turns the file label on for the bus.
Return parameter	Returns the status of the file label for the bus (ON, OFF).	
Example	<pre>:BUS1:LABEL "Bus" :BUS1:LABEL:DISPLAY ON :BUS1:LABEL:DISPLAY? ON</pre> <p>Sets the label for the bus to "Bus" and then turns the label display on. The query return shows that the label is on.</p>	

### 3-22-7. :SET<X>:LABEL



Description	Sets or returns the file label for the selected setup.	
Syntax	:SET<X>:LABEL {<string>   ?}	
Related commands	:SET<X>:LABEL:DISPLAY	
Parameter	<X>	Setup number 1 to 20
	<string>	The string must be no more than 8 characters and only contain alphanumeric characters in addition to period, dash and underscore characters. The string must be enclosed in double quotes, "string".
Return parameter	<string>	Returns the label for the selected setup. No return indicates that there has not been a file label assigned for the selected setup.
Example1	<pre>:SET1:LABEL "SET1_lab" Sets the label for setup 1 as "SET1_lab".</pre>	
Example2	<pre>:SET1:LABEL? SET1_lab</pre>	


### **3-23. Segment Commands**

---

3-23-1. :SEGMENTS:STATE .....	159
3-23-2. :SEGMENTS:CURRent .....	160
3-23-3. :SEGMENTS:TOTalnum .....	160
3-23-4. :SEGMENTS:TIME .....	160
3-23-5. :SEGMENTS:DISPALL .....	161
3-23-6. :SEGMENTS:MEASure:MODE .....	161
3-23-7. :SEGMENTS:MEASure:PLOT:SOURce .....	161
3-23-8. :SEGMENTS:MEASure:PLOT:DIVide .....	162
3-23-9. :SEGMENTS:MEASure:PLOT:SElect .....	162
3-23-10. :SEGMENTS:MEASure:PLOT:RESults .....	162
3-23-11. :SEGMENTS:MEASure:TABLE:SOURce .....	163
3-23-12. :SEGMENTS:MEASure:TABLE:SElect .....	163
3-23-13. :SEGMENTS:MEASure:TABLE:LIST .....	163
3-23-14. :SEGMENTS:MEASure:TABLE:SAVe .....	164
3-23-15. :SEGMENTS:SAVe .....	164
3-23-16. :SEGMENTS:SAVe:SOURce .....	164
3-23-17. :SEGMENTS:SAVe:SElect:STARt .....	164
3-23-18. :SEGMENTS:SAVe:SElect:END .....	165


---

#### **3-23-1. :SEGMENTS:STATE**




Description	Turns the segmented memory function on/off or queries its state.	
Syntax	:SEGMENTS:STATE { OFF   ON   ? }	
Related commands	:RUN ; :STOP	
Parameter/	OFF	Turns the segmented memory off.
Return parameter	ON	Turns the segmented memory on.
Example1	:SEGMENTS:STATE ON Turns segmented memory on.	

### 3-23-2. :SEGMENTS:CURREnt




Description	Sets or queries the current segment.	
Syntax	:SEGMENTS:CURREnt (SETTOMIN SETTOMAX NR1 ?)	
Related commands	:SEGMENTS:STATE ; :SEGMENTS:TOTAlnum	
Parameter/ Return parameter	SETTOMIN SETTOMAX <NR1>	Current segment = min segment Current segment = max segment 1~2048
Example1	:SEGMENTS:CURREnt 10 Sets the current segment to segment number 10.	

### 3-23-3. :SEGMENTS:TOTAlnum




Description	Sets or queries the total number of segments for the segmented memory function.	
Syntax	:SEGMENTS:TOTAlnum (SETTOMIN SETTOMAX <NR1> ?)	
Related commands	:SEGMENTS:STATE ; :SEGMENTS:CURREnt	
Parameter/ Return parameter	SETTOMIN SETTOMAX <NR1>	Sets to the minimum number Sets to the maximum number 1~2048
Example1	:SEGMENTS:TOTAlnum SETTOMAX Sets the number of segments to max number (2048).	

### 3-23-4. :SEGMENTS:TIME




Description	Returns the time of the current segment in relation to the first segment.	
Syntax	:SEGMENTS:TIME?	
Related commands	:SEGMENTS:STATE ; :SEGMENTS:CURREnt	
Return parameter	The segment time as <NR3>.	
Example	:SEGMENTS:TIME? >8.040E-03 Returns the segment time.	

### 3-23-5. :SEGMENTS:DISPALL




Description	Sets or queries whether all the segments are displayed on the screen.	
Syntax	:SEGMENTS:DISPALL {OFF ON ?}	
Related commands	:SEGMENTS:STATE ; :SEGMENTS:CURREnt	
Parameter/ Return parameter	OFF      Turns the display all function off. ON      Turns the display all function on.	
Example1	:SEGMENTS:DISPALL ON Turns the display all function on.	

### 3-23-6. :SEGMENTS:MEASure:MODE




Description	Sets or queries the measurement mode.	
Syntax	:SEGMENTS:MEASure:MODE {OFF PLOT TABLE ?}	
Related commands	:MEASurement:MEAS<x>	
Parameter/ Return parameter	OFF      Disables the automatic measurement function for the segments measurement. PLOT     Sets the measurement mode to Statistics. TABLE    Sets the measurement mode to a measurement list.	
Example1	:SEGMENTS:MEASure:MODE? >PLOT Returns the measurement mode as Statistics.	

### 3-23-7. :SEGMENTS:MEASure:PLOT:SOURce




Description	Sets or queries the statistics source.	
Syntax	:SEGMENTS:MEASure:PLOT:SOURce {<NR1>   ?   }	
Related commands	:SEGMENTS:MEASure:MODE ; :SEGMENTS:MEASure:PLOT:DIVide ; :SEGMENTS:MEASure:PLOT:SElect ; :SEGMENTS:MEASure:PLOT:RESults	
Parameter/ Return parameter	<NR1>    1~8 (automatic measurement item)	
Example1	:SEGMENTS:MEASure:PLOT:SOURce 1 Sets the source as first automatic measurement.	

### 3-23-8. :SEGMENTS:MEASure:PLOT:DIVide




Description	Sets or queries the number of bins for the statistics function.
Syntax	:SEGMENTS:MEASure:PLOT:DIVide {<NR1>   ?   }
Related commands	:SEGMENTS:MEASure:PLOT:SOURce ; :SEGMENTS:MEASure:PLOT:SElect
Parameter/ Return parameter	<NR1> 1~20
Example1	:SEGMENTS:MEASure:PLOT:DIVide 5 Sets the number bins to 5 for the statistics function.

### 3-23-9. :SEGMENTS:MEASure:PLOT:SElect




Description	Sets or queries which bin to view the statics of.
Syntax	:SEGMENTS:MEASure:PLOT:SElect {<NR1>   ?   }
Related commands	:SEGMENTS:MEASure:PLOT:SOURce ; :SEGMENTS:MEASure:PLOT:DIVide
Parameter	<NR1> 1~20 (cannot exceed the number of bins)
Return parameter	Return the bin number as <NR3>.
Example1	:SEGMENTS:MEASure:PLOT:SElect 5 Set to bin number 5.

### 3-23-10. :SEGMENTS:MEASure:PLOT:REStuls




Description	Returns the results of the currently selected bin for the statistics measurement.
Syntax	:SEGMENTS:MEASure:PLOT:REStuls?
Related commands	:SEGMENTS:MEASure:PLOT:SOURce ; :SEGMENTS:MEASure:PLOT:DIVide ; :SEGMENTS:MEASure:PLOT:SElect
Return parameter	Returns the statistics measurements as a string.
Example	:SEGMENTS:MEASure:PLOT:REStuls? > MAX:240mv,MIN:200mv,MEAN:206mv,Bin Statistics:15 of 20,Percent:0.00%,Count:0,Measured:345,Unmeasured:0,Bin Range:228~230mv

### 3-23-11. :SEGMENTS:MEASure:TABLE:SOURce




Description	Sets or queries the source of the measurement list.	
Syntax	:SEGMENTS:MEASure:TABLE:SOURce {CH1   CH2   CH3  CH4   ?   }	
Related commands	:SEGMENTS:MEASure:MODE ; :SEGMENTS:MEASure:TABLE:SElect ; :SEGMENTS:MEASure:TABLE:LIST	
Parameter/ Return parameter	CH1~CH4	Channel 1 to 4
Example1	:SEGMENTS:MEASure:TABLE:SOURce CH1 Sets the source to CH1.	

### 3-23-12. :SEGMENTS:MEASure:TABLE:SElect



Description	Sets or queries a segment to view in the measurement table.	
Syntax	:SEGMENTS:MEASure:TABLE:SElect {<NR1>   ?   }	
Related commands	:SEGMENTS:TOTalnum	
Parameter	<NR1> 1~2048	
Return parameter	Returns the number of segments as <NR3>.	
Example1	:SEGMENTS:MEASure:TABLE:SElect 10 Select segment number 10.	

### 3-23-13. :SEGMENTS:MEASure:TABLE:LIST



Description	Returns the measurement results of each segment in the list.
Syntax	:SEGMENTS:MEASure:TABLE:LIST?
Return parameter	The table header is followed by a binary header, and the measured value [LF] of each segment is continuous by the number of segments. Please obtain and expand the data length byte count. Binary header is in the format of # [data length digit number] [data length].
Example	SEGMENTS:MEASure:TABLE:LIST? Segment Summary:CH1; Seg,Time,Pk-Pk(V),Amp (V);[LF] #510130 1,0.000s,7.99m,7.20m,[LF] 2,6.281ms,46.4m,0.00,[LF]
Note	The response format is changed in Ver1.37.

### 3-23-14. :SEGMENTS:MEASure:TABLE:SAVe

 Set →

Description	Saves the list of segment automatic measurement results.
-------------	--

Syntax	:SEGMENTS:MEASure:TABLE:SAVe
--------	------------------------------

### 3-23-15. :SEGMENTS:SAVe

 Set →

Description	Saves the segments.
-------------	---------------------

Syntax	:SEGMENTS:SAVe
--------	----------------

Related Commands	:SEGMENTS:SAVE:SOURce ; :SEGMENTS:SAVE:SElect: START ; :SEGMENTS:SAVE:SElect:END
------------------	---

Example	:SEGMENTS:SAVE:SOURce CH1 :SEGMENTS:SAVE:SElect:STARt 1 :SEGMENTS:SAVE:SElect:END 10 :SEGMENTS:SAVe
---------	--

### 3-23-16. :SEGMENTS:SAVe:SOURce

 Query →


Description	Sets or queries the source segment waveform to save.
-------------	--

Syntax	:SEGMENTS:SAVe:SOURce {CH1   CH2   CH3  CH4   ?   }
--------	--

Parameter/ Return parameter	CH1~CH4 Channel 1 to 4.
--------------------------------	-------------------------

Example	:SEGMENTS:SAVe:SOURce CH1 >Sets the source to CH1.
---------	---

### 3-23-17. :SEGMENTS:SAVe:SElect:STARt

 Set →

 Query →

Description	Sets or queries the starting segment to save from.
-------------	--


Syntax	:SEGMENTS:SAVe:SElect:STARt {SETTOMIN   SETTOMAX   <NR1>   ? }
--------	---

Related commands	:SEGMENTS:TOTalnum
------------------	--------------------

Parameter/ Return parameter	SETTOMIN Sets the starting segment to min segment. SETTOMAX Sets the starting segment to the max segment. <NR1> Sets the segment to 1~2048.
--------------------------------	--

Example	:SEGMENTS:SAVe:SElect:STARt 2 Sets the starting segment to segment number 2.
---------	---

### 3-23-18. :SEGMENTS:SAVe:SElect:END




Description	Sets or queries the ending segment to save from.	
Syntax	:SEGMENTS:SAVe:SElect:END {SETTOMIN   SETTOMAX   <NR1>   ? }	
Related commands	:SEGMENTS:TOTalnum	
Parameter/ Return parameter	SETTOMIN SETTOMAX <NR1>	Sets the starting segment to min segment. Sets the starting segment to the max segment. Sets the segment to 1~2048.
Example	:SEGMENTS:SAVe:SElect:END 10 Sets the ending segment to segment number 10.	

### 3-24. DVM Commands


3-24-1. :DVM:STATE .....	165
3-24-2. :DVM:SOURce.....	165
3-24-3. :DVM:MODe .....	166
3-24-4. :DVM:VALue .....	166

#### 3-24-1. :DVM:STATE




Description	Sets or queries the DVM state to on or off.	
Syntax	:DVM:STATE {OFF   ON   ? }	
Related commands	:DVM:SOURce ; :DVM:MODe	
Parameter/ Return parameter	OFF ON	Turns the DVM off. Turns the DVM on.
Example	:DVM:STATE ON Turns the DVM state on.	

#### 3-24-2. :DVM:SOURce



Description	Sets or queries the source of the DVM.	
Syntax	:DVM:SOURce {CH1 CH2 CH3 CH4 ?}	
Related commands	:DVM:SOURce ; :DVM:MODe	
Parameter/ Return parameter	CH1~CH4	Channel 1 to 4.
Example	:DVM:SOURce CH1 Sets the DVM source to channel 1.	

### 3-24-3. :DVM:MODE



Description	Sets or queries the DVM mode.	
Syntax	:DVM:MODE {ACRMS DC DCRMS DUTY FREQuency ?}	
Related commands	:DVM:SOURce ; :DVM:STATE	
Parameter/	ACRMS	Sets the mode of the DVM to AC RMS
Return parameter	DC	Sets the mode of the DVM to DC
	DCRMS	Sets the mode of the DVM to DC RMS
	DUTY	Sets the mode of the DVM to AC Duty
	FREQuency	Sets the mode of the DVM to AC frequency
Example	:DVM:MODE DUTY Sets the DVM mode to DUTY.	

### 3-24-4. :DVM:VALue



Description	Returns the measurement value of the selected mode.	
Syntax	:DVM:VALue?	
Related commands	:DVM:SOURce ; :DVM:STATE, :DVM:MODE	
Return parameter	<NR3>	Returns the measurement value as <NR3>.
Example	:DVM:VALue? >8.410E-04	

### 3-25. Go\_NoGo Commands

The GoNoGo APP must first be launched (or use the command, ":GONogo:SCRipt") before any of the Go\_NoGo or Template commands can be used.

---

3-25-1. :GONogo:CLEar.....	167
3-25-2. :GONogo:EXECute .....	167
3-25-3. :GONogo:FUNCTION .....	167
3-25-4. :GONogo:NGCount.....	168
3-25-5. :GONogo:NGDefine .....	168
3-25-6. :GONogo:SOURce.....	168
3-25-7. :GONogo:VIOLation .....	169
3-25-8. :GONogo:SCRipt .....	169
3-25-9. :TEMPLATE:MODE .....	169
3-25-10. :TEMPLATE:MAXimum .....	170
3-25-11. :TEMPLATE:MINimum .....	170
3-25-12. :TEMPLATE:POStion:MAXimum .....	170
3-25-13. :TEMPLATE:POStion:MINimum .....	171
3-25-14. :TEMPLATE:SAVE:MAXimum .....	171
3-25-15. :TEMPLATE:SAVE:MINimum .....	171
3-25-16. :TEMPLATE:TOLERance.....	171
3-25-17. :TEMPLATE:SAVE:AUTO .....	171

---

#### 3-25-1. :GONogo:CLEar



---

Description	Clears the Go/NoGo counter.
Syntax	:GONogo:CLEar

---

#### 3-25-2. :GONogo:EXECute



---

Description	Enables or disables the Go/NoGo function or queries its state.
Syntax	:GONogo:EXECute {OFF ON ?}
Parameter/	OFF      Disabled
Return Parameter	ON      Enabled
Example	:GONogo:EXECute OFF Turns Go/NoGo off.

---

#### 3-25-3. :GONogo:FUNCTION



---

Description	Initializes the Go/NoGo APP. This must be run after the Go/NoGo APP has been started.
Syntax	:GONogo:FUNCTION

---

### 3-25-4. :GONogo:NGCount

→Query

Description	Returns the Go/NoGo counter.
Syntax	:GONogo:NGCount {?}
Return parameter	Returns a string in the following format “number of violations,total tests”
Example	:GONogo:NGCount? > 3,25 Indicates that 3 violations occurred over 25 tests.

### 3-25-5. :GONogo:NGDefine

Set →

→Query

Description	Sets the Go/NoGo “When” conditions.	
Syntax	:GONogo:NGDefine {EXITs ENTers ?}	
Parameter/ Return Parameter	EXITs	Sets the NoGo condition to when the input signal exceeds the limit boundary.
	ENTers	Sets the NoGo condition to when the input signal stays within the limit boundary.
Example	:GONogo:NGDefine EXITs Sets the Go/NoGo condition to EXITs.	


### 3-25-6. :GONogo:SOURce

Set →

→Query


Description	Sets the source for the Go/NoGo signal.	
Syntax	:GONogo:SOURce {CH1 CH2 CH3 CH4 ?}	
Parameter/ Return Parameter	CH1~CH4	Channel 1 to 4.
Example	:GONogo:SOURce CH1 Sets the source to CH1.	

### 3-25-7. :GONogo:VIOLation




Description	Sets or returns actions for the Go/NoGo violations.	
Syntax	:GONogo:VIOLation {STOP STOP_Beep CONTInue CONTINUE_Beep ?}	
Parameter/ Return Parameter	STOP STOP_Beep CONTInue CONTINUE_Beep	The waveform will be frozen. The waveform will be frozen and a beep will be output. Ignore the violation. Output a beep, but continue to monitor the signal.
Example	:GONogo:VIOLation STOP	Sets violation action to STOP.

### 3-25-8. :GONogo:SCRipt




Description	Activates/Deactivates the Go/NoGo APP or queries its state.	
Syntax	:GONogo:SCRipt {OFF   ON   ?}	
Parameter/ Return Parameter	ON OFF	Turns Go/NoGo APP on. Turns the Go/NoGo APP off.
Example	:GONogo:SCRipt? >ON The Go/NoGo script is on.	

### 3-25-9. :TEMPlate:MODE




Description	Sets or returns the Go/NoGo template mode.	
Syntax	:TEMPlate:MODE{MAXimum MINimum AUTO ?}	
Parameter/ Return Parameter	MAXimum MINimum AUTO	Maximum template Minimum template Auto template
Example	:TEMPlate:MODE AUTO	Sets the template mode to AUTO.

### 3-25-10. :TEMPlate:MAXimum




Description	Defines or queries which waveform memory (REF1 or W1~W20) is set to the maximum template.
Syntax	:TEMPlate:MAXimum{REF1 W1~W20 ?}
Parameter/	REF1 Reference one
Return Parameter	W1~W20 Waveform memory 1 to 20
Example	:TEMPlate:MAXimum REF1 Saves the maximum template to REF1.

### 3-25-11. :TEMPlate:MINimum




Description	Defines or queries which waveform memory (REF1 or W1~W20) is set to the minimum template.
Syntax	:TEMPlate:MINimum{REF2 W1~W20 ?}
Parameter/	REF2 Reference one
Return Parameter	W1~W20 Waveform memory 1 to 20
Example	:TEMPlate:MINimum REF2 Saves the minimum template to REF2.

### 3-25-12. :TEMPlate:POSITION:MAXimum



Description	Sets or queries the position of the maximum template.
Syntax	:TEMPlate:POSITION:MAXimum{NR2 ?}
Parameter	<NR2> Desired template position (-12.0 ~ +12.0 divisions)
Return parameter	Returns the position in the following format: "<NR2>Div"
Example	:TEMPlate:POSITION:MAXimum 3.00 Sets the maximum template position to 3.00 divisions.

### 3-25-13. :TEMPPlate:POSIon:MINimum




Description	Sets or queries the position of the minimum template.
Syntax	:TEMPPlate:POSITION:MAXimum{NR2 ?}
Parameter	<NR2> Desired template position (-12.0 ~ +12.0 divisions)
Return parameter	Returns the position in the following format: "<NR2>Div"
Example	:TEMPPlate:POSIon:MINimum 3.00 Sets the minimum template position to 3.00 divisions.

### 3-25-14. :TEMPPlate:SAVe:MAXimum




Description	Saves the maximum template.
Syntax	:TEMPPlate:SAVe:MAXimum

### 3-25-15. :TEMPPlate:SAVe:MINimum



Description	Saves the minimum template.
Syntax	:TEMPPlate:SAVe:MINimum

### 3-25-16. :TEMPPlate:TOLerance



Description	Sets or queries the tolerance as a percentage.
Syntax	:TEMPPlate:TOLerance{NR2 ?}
Parameter/	<NR2> The auto tolerance range (0.4% ~ 40%)
Return Parameter	
Example	:TEMPPlate:TOLerance 10 Sets the tolerance to 10%.

### 3-25-17. :TEMPPlate:SAVe:AUTo




Description	Saves the AUTO template (maximum and minimum templates).
Syntax	:TEMPPlate:SAVe:AUTo

### 3-26. Data Logging Commands


3-26-1. :DATALOG:STATE .....	172
3-26-2. :DATALOG:SOURce .....	172
3-26-3. :DATALOG:SAVE .....	173
3-26-4. :DATALOG:INTerval .....	173
3-26-5. :DATALOG:DURation .....	173

#### 3-26-1. :DATALOG:STATE



Description	Sets or queries the state of the data logging app.	
Syntax	:DATALOG:STATE{OFF ON ?}	
Related commands	:DATALOG:SOURce :DATALOG:SAVe :DATALOG:INTerval :DATALOG:DURation	
Parameter/	OFF      Turns the data logging off.	
Return parameter	ON      Turns the data logging on.	
Example	DATALOG:STATE ON Turns the data logging app on.	

#### 3-26-2. :DATALOG:SOURce



Description	Sets or queries the data logging source channel.	
Syntax	:DATALOG:SOURce {CH1~CH4 all ?}	
Related commands	:DATALOG:STATE :DATALOG:SAVe :DATALOG:INTerval :DATALOG:DURation	
Parameter/	CH1~CH4      Channel 1 to 4.	
Return parameter	all      All displayed channels.	
Example	:DATALOG:SOURce CH1 Sets the source to CH1.	

### 3-26-3. :DATALOG:SAVe

Set →  
→ Query

Description	Sets or queries the save format as image or waveform.	
Syntax	:DATALOG:SAVe {IMAGE WAVEform ?}	
Related commands	:DATALOG:STATE :DATALOG:SOURce :DATALOG:INTerval :DATALOG:DURation	
Parameter/ Return parameter	IMAGE Save as images. WAVEform Save as waveforms.	
Example	:DATALOG:SAVe WAVEform Sets the save format to waveform.	

### 3-26-4. :DATALOG:INTerval

Set →  
→ Query

Description	Sets or queries the recording interval time in seconds.	
Syntax	:DATALOG:INTerval {<NR1> ?}	
Related commands	:DATALOG:STATE :DATALOG:SOURce :DATALOG:SAVe :DATALOG:DURation	
Parameter/ Return parameter	<NR1>	Sets returns the interval time in discrete seconds: 2, 3, 4, 5, 10, 20, 30, 60, 120, 300, 600, 1200
Example	:DATALOG:INTerval 2 Sets the recording interval to 2 seconds.	

### 3-26-5. :DATALOG:DURation


Set →  
→ Query

Description	Sets or queries the recording duration time in minutes.	
Syntax	:DATALOG:DURation {<NR1> ?}	
Related commands	:DATALOG:STATE :DATALOG:SOURce :DATALOG:SAVe :DATALOG:INTerval	
Parameter/ Return parameter	<NR1>	Sets returns the duration time in discrete minutes: 5, 10, 15, 20, 25, 30, 60, 90, 120, 150, 180, 210, 240, 270, 300, 330, 360, 390, 420, 450, 480, 510, 540, 570, 600, 1200, 1800, 2400, 3000, 3600, 4200, 4800, 5400, 6000
Example	:DATALOG:DURation 10 Sets the recording duration to 10 minutes.	

### 3-27. Remote DiskCommands


3-27-1. :REMOTEDisk:IPADDress .....	174
3-27-2. :REMOTEDisk:PATHName .....	174
3-27-3. :REMOTEDisk:USERName .....	174
3-27-4. :REMOTEDisk:PASSWord.....	175
3-27-5. :REMOTEDisk:MOUNT.....	175
3-27-6. :REMOTEDisk:AUTOMount .....	175

#### 3-27-1. :REMOTEDisk:IPADDress




Description	Sets or returns the IP address of remote disk.	
Syntax	:REMOTEDisk:IPADDress {<string>} ?}	
Parameter/	<string>	IP address enclosed in double quotes.
Return parameter		Eg., 172.16.20.255
Example	:REMOTEDisk:IPADDress "172.16.20.255" Sets the remote disk IP address as 172.16.20.255.	

#### 3-27-2. :REMOTEDisk:PATHName




Description	Sets or returns the file path of the remote disk.	
Syntax	:REMOTEDisk:PATHName {<string>} ?}	
Parameter/	<string>	File path in enclosed in double quotes eg.,
Return parameter		"remote_disk"
Example	:REMOTEDisk:PATHName "remote_disk" Sets the file path to c:/remote_disk.	

#### 3-27-3. :REMOTEDisk:USERName




Description	Sets or queries the account username for the remote disk.	
Syntax	:REMOTEDisk:USERName {<string>}   ? }	
Parameter/Return	<string>	User name enclosed in double quotes eg., "User_Name".
parameter		
Example	:REMOTEDisk:USERName "User_Name" Sets the account name as User_Name.	

### 3-27-4. :REMOTEDisk:PASSWord




Description	Sets or queries the account password for the remote disk.
Syntax	:REMOTEDisk:PASSWord {<string>   ? }
Parameter/Return parameter	<string> Username password enclosed in double quotes eg., "Password".
Example	:REMOTEDisk:PASSWord "Password" Sets the account password as Password.

### 3-27-5. :REMOTEDisk:OUNT



Description	Turns remote disk on/off or queries its state.
Syntax	:REMOTEDisk:OUNT { OFF   ON   ? }
Parameter/Return parameter	OFF Unmount remote disk ON Mount remote disk
Example	:REMOTEDisk:IPADDress "172.16.5.154" :REMOTEDisk:PATHName "remote_disk" :REMOTEDisk:USERName "guest" :REMOTEDisk:PASSWord "password" :REMOTEDisk:OUNT ON Sets the remote disk parameters and mounts the remote disk.

### 3-27-6. :REMOTEDisk:AUTOMount



Description	Turns automount on/off or queries its state. The remote disk must be configured beforehand.
Syntax	:REMOTEDisk:AUTOMount { OFF   ON   ? }
Parameter/Return parameter	OFF Don't mount the remote disk at start up. ON Automatically mount the remote disk on start up.
Example	:REMOTEDisk:AUTOMount ON Turns the automount function on.

## 4. APPENDIX

### 4-1. Error messages

The following error messages may be returned from the :SYSTEm:ERRor? query.

No.	Description	No.	Description
0	"No error."	-200	"Execution error"
-100	"Command error"	-201	"Invalid while in local"
-101	"Invalid character"	-202	"Settings lost due to rtl"
-102	"Syntax error"	-203	"Command protected"
-103	"Invalid separator"	-210	"Trigger error"
-104	"Data type error"	-211	"Trigger ignored"
-105	"GET not allowed"	-212	"Arm ignored"
-108	"Parameter not allowed"	-213	"Init ignored"
-109	"Missing parameter"	-214	"Trigger deadlock"
-110	"Command header error"	-215	"Arm deadlock"
-111	"Header separator error"	-220	"Parameter error"
-112	"Program mnemonic too long"	-221	"Settings conflict"
-113	"Undefined header"	-222	"Data out of range"
-114	"Header suffix out of range"	-223	"Too much data"
-115	"Unexpected number of parameters"	-224	"Illegal parameter value"
-120	"Numeric data error"	-225	"Out of memory"
-121	"Invalid character in number"	-226	"Lists not same length"
-123	"Exponent too large"	-230	"Data corrupt or stale"
-124	"Too many digits"	-231	"Data questionable"
-128	"Numeric data not allowed"	-232	"Invalid format"
-130	"Suffix error"	-233	"Invalid version"
-131	"Invalid suffix"	-240	"Hardware error"
-134	"Suffix too long"	-241	"Hardware missing"
-138	"Suffix not allowed"	-250	"Mass storage error"
-140	"Character data error"	-251	"Missing mass storage"
-141	"Invalid character data"	-252	"Missing media"
-144	"Character data too long"	-253	"Corrupt media"
-148	"Character data not allowed"	-254	"Media full"
-150	"String data error"	-255	"Directory full"
-151	"Invalid string data"	-256	"File name not found"
-158	"String data not allowed"	-257	"File name error"
-160	"Block data error"	-258	"Media protected"
-161	"Invalid block data"	-260	"Expression error"
-168	"Block data not allowed"	-261	"Math error in expression"
-170	"Expression error"	-270	"Macro error"
-171	"Invalid expression"	-271	"Macro syntax error"
-178	"Expression data not allowed"	-272	"Macro execution error"
-180	"Macro error"	-273	"Illegal macro label"
-181	"Invalid outside macro definition"	-274	"Macro parameter error"
-183	"Invalid inside macro definition"	-275	"Macro definition too long"
-184	"Macro parameter error"	-276	"Macro recursion error"

No.	Description
-277	"Macro redefinition not allowed"
-278	"Macro header not found"
-280	"Program error"
-281	"Cannot create program"
-282	"Illegal program name"
-283	"Illegal variable name"
-284	"Program currently running"
-285	"Program syntax error"
-286	"Program runtime error"
-290	"Memory use error"
-291	"Out of memory"
-292	"Referenced name does not exist"
-293	"Referenced name already exists"
-294	"Incompatible type"
-300	"Device-specific error"
-310	"System error"
-311	"Memory error"
-312	"PUD memory lost"
-313	"Calibration memory lost"
-314	"Save/recall memory lost"
-315	"Configuration memory lost"
-320	"Storage fault"
-321	"Out of memory"
-330	"Self-test failed"
-340	"Calibration failed"
-350	"Queue overflow"
-360	"Communication error"
-361	"Parity error in program message"
-362	"Framing error in program message"
-363	"Input buffer overrun"
-365	"Time out error"
-400	"Query error"
-410	"Query INTERRUPTED"
-420	"Query UNTERMINATED"
-430	"Query DEADLOCKED"
-440	"Query UNTERMINATED after indefinite response"



## TEXIO TECHNOLOGY CORPORATION

7F Towa Fudosan Shin Yokohama Bldg., 2-18-13, Shin Yokohama, Kohoku-ku,  
Yokohama, Kanagawa, 222-0033, Japan.

<https://www.texio.co.jp/>